

5

A DESIGN APPARATUS AND A METHOD FOR GENERATING AN
IMPLEMENTABLE DESCRIPTION OF A DIGITAL SYSTEM

INSAI

Field of the invention

10

The present invention is situated in the field of design of systems. More specifically, the present invention is related to a design apparatus for digital systems, generating implementable descriptions of said systems.

The present invention is also related to a method for generating implementable descriptions of said systems.

20 State of the art

The current need for digital systems forces contemporary system designers with ever increasing design complexities in most applications where dedicated processors and other digital hardware are used, demand for new systems is rising and development time is shortening. As an example, currently there is a high interest in digital communication equipment for public access networks. Examples are modems for Asymmetric Digital Subscriber Loop (ADSL) applications, and up- and downstream Hybrid Fiber-Coax (HFC) communication. These modems are preferably implemented in all-digital hardware using digital signal processing (DSP) techniques. This is because of the

5 as possible.

15 VERILOG.

environments support the design of complex DSP systems.

20 uses the data-vector as the basic semantical feature.

25 simulation of these kind of systems. SPW is typically used

in the systems appears in two different formats, (a simulatable and a synthesizable version) which results in

possible inconsistency.

COSSAP of *Synopsys* performs the same kind of system exploration as SPW.

DC and BC are products of *Synopsys* that support system synthesis. These products do not provide sufficient algorithm exploration functions.

Because all of these tools support only part of the desired functionality, contemporary digital systems are designed typically with a mix of these environments.

10 For example, a designer might do algorithmic exploration in MATLAB, then do architecture definition with SPW, and finally map the architecture definition to an implementation in DC.

15 Aims of the invention

It is an aim of the present invention to disclose a design apparatus that allows to generate from a behavioral description of a digital system, an implementable description for said system.

20 It is another aim of the present invention to disclose a the design apparatus that allows for design, digital systems starting from a data vector or data flow description and generating an implementable level such as VHDL. A further aim is to perform such design tasks within

25 one object oriented environment.

Another aim is to provide a means comprised in said design apparatus for simulating the behavior of the system at any level of the design stage or trajectory.

30 Summary of the invention

A first aspect of the present invention concerns a design apparatus compiled on a computer

09873553-060401

environment for generating from a behavioral description of a system comprising at least one digital system part, an implementable description for said system, said behavioral description being represented on said computer environment
5 as a first set of objects with a first set of relations therebetween, said implementable description being represented on said computer environment as a second set of objects with a second set of relations therebetween, said first and second set of objects being part of a design
10 environment.

A behavioral description is a description which substantiates the desired behavior of a system in a formal way. In general, a behavioral description is not readily implementable since it is a high-level description,
15 and it only describes an abstract version of the system that can be simulated. An implementable description is a more concrete description that is, in contrast to a behavioral description, detailed enough to be implemented in software to provide an approximative simulation of real-
20 life behavior or in hardware to provide a working semiconductor circuit.

With design environment is meant an environment in which algorithms can be produced and run by interpretation or compilation.

25 With objects is meant a data structure which shows all the characteristics of an object from an object oriented programming language, such as described in "Object Oriented Design" (G. Booch, Benjamin/Cummings Publishing, Redwood City, Calif., 1991).

30 Said first and second set of objects are preferably part of a single design environment.

Said design environment comprises preferably

an Object Oriented Programming Language (OOPL). Said OOPL can be C++.

Said design environment is preferably an open environment wherein new objects can be created. A closed
5 environment will not provide the flexibility that can be obtained with an open environment and will limit the possibilities of the user.

Preferably, at least part of the input signals and output signals of said first set of objects are
10 at least part of the input signals and output signals of said second set of objects. Essentially all of the input signals and output signals of said first set of objects can be essentially all of the input signals and output signals of said second set of objects.

15 At least part of the input signals and output signals of said behavioral description are preferably at least part of the input signals and output signals of said implementable description. Essentially all of the input signals and output signals of said behavioral description
20 can be essentially all of the input signals and output signals of said implementable description.

Said first set of objects has preferably first semantics and said second set of objects has preferably second semantics. With semantics is meant the
25 model of computation. Said first semantics is preferably a data-vector model and/or a data-flow model. Said second semantics is preferably a Finite State Machine Data Path (FSMD) data structure, comprising a control part and a data processing part, the data processing part being
30 modeled by a signal flow graph (SFG) data structure and the control part being modeled by a FSM data structure. The terms FSMD and SFG are used interchangeably throughout the

text.

Preferably, the impact in said implementable description of at least a part of the objects of said second set of objects is essentially the same as the impact
5 in said behavioral description of at least a part of the objects of said first set of objects.

Preferably, the impact in said implementable description of essentially all of the objects of said second set of objects is essentially the same as the impact
10 in said behavioral description of essentially all of the objects of said first set of objects.

With impact is meant not only the function, but also the way the object interacts with its environment from an external point of view. A way of rephrasing this is
15 that the same interface for providing input and collecting output is present. This does not mean that the actual implementation of the data-processing between input and output is the same. The implementation is embodied by objects, which can be completely different but perform a
20 same function. In an OOPL, the use of methods of an object without knowing its actual implementation is referred to as information hiding.

The design apparatus preferably further comprises means for simulating the behavior of said system
25 said means simulating the behavior of said behavioral description, said implementable description or any intermediate description therebetween. Said intermediate description can be obtained after one or several refining steps from said behavioral description.

30 Preferably, at least part of said second set of objects is derived from objects belonging to said first set of objects. This can be done by using the inheritance

functionalities provided in an OOPL. Essentially all of said second set of objects can be derived from objects belonging to said first set of objects.

Said implementable description can be at least partly obtained by refining said behavioral description. Said implementable description can be essentially obtained by refining said behavioral description. Preferably, said refining comprises the refining of objects.

The design apparatus can further comprise means to derive said first set of objects from a vector description, preferably a MATLAB description, describing said system as a set of operations on data vectors, means for simulating statically or demand-driven scheduled dataflow on said dataflow description and/or means for clock-cycle true simulating said digital system using said dataflow description and/or one or more of said SFG data structures.

In a preferred embodiment, said implementable description is an architecture description of said system, said system advantageously further comprising means for translating said architecture description into a synthesizable description of said system, said synthesizable description being directly implementable in hardware. Said synthesizable description is preferably a netlist of hardware building blocks. Said hardware is preferably a semiconductor chip or a electronic circuit comprising semiconductor chips.

A synthesizable description is a description of the architecture of a semiconductor that can be synthesized without further processing of the description. An example is a VHDL description.

Said means for translating said architecture description into a synthesizable description can be Cathedral-3 or Synopsys DC.

5 A second aspect of the present invention is a method for designing a system comprising at least one digital part, comprising a refining step wherein a behavioral description of said system is transformed into an implementable description of said system, said
10 behavioral description being represented as a first set of objects with a first set of relations therebetween and said implementable description being represented as a second set of objects with a second set of relations therebetween.

Said refining step preferably comprises
15 translating behavioral characteristics at least partly into structural characteristics. Said refining step can comprise translating behavioral characteristics completely into structural characteristics.

Said method can further comprise a simulation
20 step in which the behavior of said behavioral description, said implementable description and/or any intermediate description therebetween is simulated.

Said refining step can comprises the addition of new objects, permitting interaction with existing
25 objects, and adjustments to said existing objects allowing said interaction.

Preferably, said refining step is performed in an open environment and comprises expansion of existing objects. Expansion of existing objects can include the
30 addition to an object of methods that create new objects. Said object is said to be expanded with the new objects. The use of expandable objects allows to use meta-code

generation: creating expandable objects implies an indirect creation of the new objects.

Said behavioral description and said implementable description are preferably represented in a single design environment, said single design environment advantageously being an Object Oriented Programming Language, preferably C++.

Preferably, said first set of objects has first semantics and said second set of objects has second semantics. Said first semantics is preferably a data-vector model and/or a data-flow model. Said second semantics is preferably an SFG data structure.

The refining step comprises preferably a first refining step wherein said behavioral description being a data-vector model is at least partly transformed into a data-flow model. Advantageously, said data-flow model is an untimed floating point data-flow model.

Said refining step preferably further comprises a second refining step wherein said data-flow model is at least partly transformed into an SFG model. Said data-flow model can be completely transformed into an SFG model.

In a preferred embodiment, said first refining step comprises the steps of determining the input vector lengths of input, output and intermediate signals, determining the amount of parallelism of operations that process input signals under the form of a vector to output signals, determination of objects, connections between objects and signals between objects of said data-flow model, and determining the wordlength of said signals between objects. In the sequel of this application, the term "actors" is also used to denote objects. Connections

between objects are denoted as "edges" and signals between objects are denoted as "tokens". Said step of determining the amount of parallelism can preferably comprise determining the amount of parallelism for every data vector and reducing the unspecified communication bandwidth of said data-vector model to a fixed number of communication buses in said data-flow model. Said step of determination of actors, edges and tokens of said data-flow model preferably comprises defining one or a group of data vectors in said first data-vector model as actors; defining data precedences crossing actor bounds, as edges, said edges behaving like queues and transporting tokens between actors; construct a system schedule and run a simulation on a computer environment. Said second refining step comprises preferably transforming said tokens from floating point to fixed point. Preferably, said SFG model is a timed fixed point SFG model.

Said second set of objects with said second set of relations therebetween are preferably at least partly derived from said first set of objects with said first set of relations therebetween. Objects belonging to said second set of objects are preferably new objects, identical with and/or derived by inheritance from objects from said first set of objects, or a combination thereof.

Several of said SFG models can be combined with a finite state machine description resulting in an implementable description. Said implementable description can be transformed to synthesizable code, said synthesizable code preferably being VHDL code.

Another aspect of the present invention is a method for simulating a system, wherein a description of a system is transformed into compilable C++ code.

Preferably, said description is an SFG data structure and said compilable C++ code is used to perform clock cycle true simulations.

Several SFG data structures can be combined
5 with a finite state machine description resulting in an implementable description, said implementable description being said compilable C++ code suitable for simulating said system as software.

A clock-cycle true simulation of a system
10 uses one or more SFG data structures.

Said clock-cycle true simulation can be an expectation-based simulation, said expectation-based simulation comprising the steps of: annotating a token age
15 to every token; annotating a queue age to every queue; increasing token age according to the token aging rules and with the travel delay for every queue that has transported the token; increasing queue age with the iteration time of the actor steering the queue, and; checking whether token
20 age is never smaller than queue age throughout the simulation.

Another aspect of the present invention is a hardware circuit or a software simulation of a hardware circuit designed with the design apparatus as recited
25 higher.

Another aspect of the present invention is a hardware circuit or a software simulation of a hardware circuit designed with the method as recited higher.

30 Detailed description of the invention

The present invention will be further explained by means of examples, which does not limit the

scope of the invention as claimed.

Short description of the drawings

In figures 1A, 1B, 1C and 1D, the overall design methodology according to an embodiment of the invention is described.

In figure 2, a targeted architecture of a system that is to be designed according to the invention is described.

In figure 3, the C++ modeling levels of target architecture are depicted.

In figure 4, an SDF model of the PN correlator of the target architecture of figure 2 is shown.

In figure 5, a CSDF model of the PN correlator is described.

In figure 6, a MATLAB Dataflow model of the PN correlator is shown.

In figure 7, the SFG modeling concepts are depicted.

In figure 8, the implied description of the **max** actor is described.

In figure 9, example implementations for different expectations are given.

In figure 10, an overview of expectation based simulation is shown.

In figure 11, the code in OCAPI, or design environment of the invention, for a correlator processor is given.

In figure 12, the resulting circuit for datapath and controller is hierarchically drawn.

Figure 13 describes a DECT Base station setup.

Figure 14 shows the front-end processing of the DECT transceiver.

In Figure 15, a part of the central VLIW controller description for the DECT transceiver ASIC is shown.

In figure 16, the use of overloading to construct the signal flowgraph data structure is shown.

In figure 17, an example C++ code fragment and its corresponding data structure is described.

- 5 In figure 18, a graphical and C++-textual description of the same FSM is shown.

In figure 19, the final system architecture of the DECT transceiver is shown.

In figure 20, a data-flow target architecture is shown.

- 10 In figure 21, the simulation of one cycle in a system with three components is shown.

In figure 22, the implementation and simulation strategy is depicted.

- 15 In figure 23, an end-to-end model of a QAM transmission system is shown.

In figure 24, the system contents for the QAM transmission system is described.

- 20 The present invention can be described as a design environment for performing subsequent gradual refinement of descriptions of digital systems within one and the same object oriented programming language environment. The lowest level is semantically equivalent to a behavioral description at the register transfer (RT)
- 25 level.

- A preferred embodiment of the invention comprising the design method according to the invention is called OCAPI. OCAPI is part of a global design methodology concept SOC++. OCAPI includes both a design environment in
- 30 an object oriented programming language and a design method. OCAPI differentiates from current systems that support architecture definition (SPW, COSSAP) in the way

that a designer is guided from the MATLAB level to the register transfer level. This way, combined semantic and syntactic translations in the design flow are avoided.

- The designer is offered a single coding framework in an object oriented programming language, such as C++, to express refinements to the behavior. An open environment is used, rather than the usual interface-and-module approach.
- The coding framework is a container of design concepts, used in traditional design practice. Some example design concepts currently supported are simulation queues, finite state machines, signal flowgraphs, hybrid floating/fixed point data types, operation profiling and signal range statistics. The concepts take the form of object oriented programming language objects (referred to as object in the remainder of this text), that can be instantiated and related to each other.
- With this set of objects, a gradual refinement design route is offered: more abstract design concepts can be replaced with more detailed ones in a gradual way. Also, design concepts are combined in an orthogonal way: quantization effects and clock cycles (operation/operator mapping) for instance are two architecture features that can be investigated separately. Next, the different design hierarchies can be freely intermixed because of this object-oriented approach. For instance, it is possible to simulate half of the description at fixed point level, while the other half is still in floating point.
- The use of a single object oriented programming language framework in OCAPI allows fast design iteration, which is

not possible in the typical nowadays hybrid approach.

Comparing to existing data-flow-based systems like SPW and COSSAP we see that the algorithm iterations can be freely chosen. Comparing to existing hardware design environments like DC or BC, we see that we can start from a specification level that is more abstract than the connection of blocks.

Two concepts of **scaleable parallelism** and **expectation based simulation** are introduced. The designer is given an environment to check the feasibility of what the designer thinks that can be done. In the development process, the designer creates his library of Signal FlowGraph (SFG) versions of abstract MATLAB operations.

15 Description of OCAPI, a preferred embodiment of the present invention

OCAPI is a C++ library intended for the design of digital systems. It provides a short path from a system design description to implementation in hardware. The library is suited for a variety of design tasks, including:

- Fixed Point Simulations
- System Performance Estimation
- System Profiling
- 25 • Algorithm-to-Architecture Mapping
- System Design according to a Dataflow Paradigm
- Verification and Testbench Development

Development flow

30 The flow layout

The design flow according to an embodiment of the present invention, as shown in figure 1D, starts off with an untimed, floating point C++ system description 101. Since data-processing intensive applications such as all-
5 digital transceivers are targeted, this description uses data-flow semantics. The system is described as a network of communicating components.

At first, the design is refined, and in each component, features expressing hardware implementation are
10 introduced, including time (clock cycles) and bittrue rounding effects. The use of C++ allows to express this in an elegant way. Also, all refinement is done in a single environment, which greatly speedups the design effort.

Next, the timed, bittrue C++ description 103
15 is translated into an equivalent HDL description by code generation. For each component, a controller description 105 and a datapath description 107 can be generated. Also for each component a single HDL description can be generated, this description preferably jointly representing
20 the control processing and data processing of the component. This is done because OCAPI relies on separate synthesis tools for both parts, each one optimized towards controller or else datapath synthesis tasks. Through the use of an appropriate object modeling hierarchy the
25 generation of datapath and controller HDL can be done fully automatic.

For datapath synthesis 109, OCAPI relies on the Cathedral-3 datapath synthesis tools, that allow to obtain a bitparallel hardware implementation starting from
30 a set of signal flowgraphs. Controller synthesis 111 on the other hand is done by the logic synthesis of Synopsys DC. This divide and conquer strategy towards synthesis allows

each tool to be applied at the right place.

During system simulation, the system stimuli 113 are also translated into testbenches that allow to verify the synthesis result of each component. After 5 interconnecting all synthesized components into the system netlist, the final implementation can also be verified using a generated system testbench 115.

The system model

10

The system machine model that is used is a set of concurrent processes. Each process translates to one component in the final system implementation.

At the system level, processes execute using 15 data flow simulation semantics. That is, a process is described as an iterative behavior, where inputs are read in at the start of an iteration, and outputs are produced at the end. Process execution can start as soon as the required input values are available.

20

Inside of each process, two types of description are possible. The first one is an untimed description, and can be expressed using any C++ constructs available. A firing rule is also added to allow dataflow simulation. Untimed processes are not subject to hardware 25 implementation but are needed to express the overall system behavior. A typical example is a channel model used to simulate a digital transceiver.

The second flavor of processes is timed. These processes operate synchronously to the system clock. 30 One iteration of such a process corresponds to one clock cycle of processing. Such a process falls apart in two pieces: a control description and a data processing

09873553-0604041
T04090"ESSEZ860

description.

The control description is done by means of a finite state machine, while the data description is a set of instructions. Each instruction consists of a series of signal assignments, and can also define process in- and outputs. Upon execution, the control description is evaluated to select one or more instructions for execution. Next, the selected instructions are executed. Each instruction thus corresponds to one clock cycle of RT behavior.

For system simulation, two schedulers are available. A dataflow scheduler is used to simulate a system that contains only untimed blocks. This scheduler repeatedly checks process firing rules, selecting processes for execution as their inputs are available. When the system also contains timed blocks however, a cycle scheduler is used. The cycle scheduler manages to interleave execution of multi-cycle descriptions, but can incorporate untimed blocks as well.

The standard program

The library of OCAPI has been developed with the g++ C++ GNU compiler. The best mode embodiment uses the g++ 2.8.1 compiler, and has been successfully compiled and run under the HP-UX 10 (HP-UX10) operating system platform. It is also possible to use a g++ 2.7.2 compiler, allowing for compilation and run under operating system platforms such as HP-UX-9 (HPRISC), HP-UX-10 (HP-UX10), SunOS (SUN4), Solaris (SUN5) and Linux 2.0.0 (LINUX).

The layout of the 'standard' g++ OCAPI program will be explained, including compilation and

09873553-060404

linking of this program.

First of all, g++ is a preferred standard compilation environment. On Linux, this is already the case after installation. Other operating system vendors however usually have their own proprietary C++ compiler. In such cases, the g++ compiler should be installed on the operating system, and the PATH variable adapted such that the shell can access the compiler.

The OCAPI library comes as a set of include files and a binary lib. All of these are put into one directory, which is called the BASE directory.

The 'standard program' is the minimal contents of an OCAPI program. It has the following layout.

```

15         include ``qlib.h''

           int main()
           {
20             // your program goes here
           }

```

The include "qlib.h" includes everything you need to access all classes within OCAPI.

If this program is called "standard.cxx", then the following makefile will transform the source code into an executable for you:

```

HOSTTYPE = HPUX10

BASE      = /imec/vsdm/OCAPI/release/v0.9
CC        = g++
5  QFLAGS = -c -g -Wall -I${BASE}
LIBS      = -lm

%.o: %.cxx
      $(CC) $(QFLAGS) $< -o $@
10

TARGET = standard

all: $(TARGET)

15  define lnkqlib
      $(CC) $^ -o $@ $(LIBS)
      endef

OBJS = standard.o
20

standard:${OBJS} $(BASE)/lib$(HOSTTYPE)qlib.a
      ${lnkqlib}

clean:
25  rm -f *.o $(TARGET)

```

This is a makefile for GNU's "make"; other "make" programs
 30 can have a slightly different syntax, especially for the
 definition of the "lnkqlib" macro. It is not the shortest
 possible solution for a makefile , but it is one that works

on different platforms without making assumptions about standard compilation rules.

The compilation flags "QFLAGS" mean the following: "-c" selects compilation-only, "-g" turns on debugging information, and "-Wall" is the warning flag. The debugging flag allows you to debug your program with "gdb", the GNU debugger.

Even if you don't like a debugger and prefer "printf()" debugging, "gdb" can at least be of great help in the case the program core dumps. Start the program under "gdb" (type "gdb standard" at the shell prompt), type "run" to let "standard" crash again, and then type "bt". One now see the call trace.

Calculation

OCAPI processes both floating point and fixed point values. In contrast to the standard C++ data types like "int" and "double", a "hybrid" data type class is used, that simulates both fixed point and floating point behavior.

The dfix class

25

This class is called "dfix". The particular floating/fixed point behavior is selected by the class constructor. The standard format of this constructor is

```
30 dfix a;      // a floating point value
    dfix a(0.5); // a floating point value with initial value
    dfix a(0.5, 10, 8);
```

T04090" E55E2860

```
// a fixed point value with initial value,
// 10 bits total word-length, 8 fractional bits
```

- 5 A fixed point value has a maximal precision of the mantissa precision of a C++ "double". On most machines, this is 53 bits.

A fixed point value can also select a representation, an
10 overflow behavior, and a rounding behavior. These flags are, in this order, optional parameters to the "dfix" constructor. They can have the following values.

- Representation flag: "dfix::tc" for two's complement
15 signed representation, "dfix::ns" for unsigned representation.
- Overflow flag: "dfix::wp" for wrap-around overflow, "dfix::st" for saturation.
- Rounding flag: "dfix::fl" for truncation (floor),
20 "dfix::rd" for rounding behavior.

Some examples are

```
dfix a(0.5, 10, 8);
25 // the default is two's complement, wrap-around,
// truncated quantisation
dfix a(0.5, 10, 8, dfix::tc, dfix::st, dfix::rd);
// two's complement, saturation, rounding quantisation
dfix a(0.5, 10, 8, dfix::ns);
30 // unsigned, wrap-around, truncated quantisation
```

When working with fixed point "dfix"es, it is important to

keep the following rule in mind: "*quantisation occurs only when a value is defined or assigned*". This means that a large expression with several intermediate results will never have these intermediate values quantised. Especially
 5 when writing code for hardware implementation, this should be kept in mind. Also intermediate results are stored in finite hardware and therefore will have some quantisation behavior. There is however a "cast" operator that will come at help here.

10

The dfix operators

The operators on "dfix" are shown below

- | | |
|----|--|
| 15 | <ul style="list-style-type: none"> • +, -, *, /
Standard addition, subtraction (including unary minus), multiplication and division. • +=, -=, *=, /=
In-place versions of previous operators. |
| 20 | <ul style="list-style-type: none"> • abs
Absolute value. • <<, >>
Left and right shifts. • <<=, >>=
In place left and right shifts. |
| 25 | <ul style="list-style-type: none"> • msbpos
Most-significant bit position. • &, , ^, ~
Bitwise and, or, exor, and not operators. |
| 30 | <ul style="list-style-type: none"> • frac() (member call)
Fractional part. • ==, !=, <=, >=, <, > |

Relational operators: equal, different, smaller then ,or equal to, greater then or equal to, smaller then, greater then. These return an "int" instead of a "dfix".

5

All operators with exception of the bitwise operators work on the maximal fixed point precision (53 points). The bitwise operators have a precision of 32 bits (a C++ "long"). Also, they assume the fixed point representation
10 contains no fractional bits.

In addition to the arithmetic operators, several utility methods are available for the "dfix" class.

15 dfix a,b;

```
// cast a to another type
b = cast(dfix(0, 12, 10), a);
```

```
20 // assign b to a, retaining the quantisation of a
a = b;
```

```
// assign b to a, including the quantisation
a.duplicate(b);
```

25

```
// return the integer part of b
int c = (int) b;
```

```
// retrieve the value of b as a double
```

```
30 double d,e;
d = b.Val();
e = Val(b);
```

F04090" E55E2860

```

// return quantisation characteristics of a
a.TypeW();    // returns the number of bits
a.TypeL();    // returns the number of fractional bits
5 a.TypeSign();    // returns dfix::tc or dfix::ns
a.TypeOverflow(); // returns dfix::wp or dfix::st
a.TypeRound();  // returns dfix::fl or dfix::rd

// check if two dfixes are identical in value and
10 quantisation
   identical(a,b);

// see wether a is floating or fixed point
a.TypeMode(); // returns dfix::fixpoint or dfix::floatpoint
15 a.isDouble();
   a.isFix();

// write a to cout
cout << a;
20

// write a to stdout, in float format,
// on a field of 10 characters
write(cout, a, 'f', 10);

25 // now use a fixed-format
write(cout, a, 'g', 10);
// next assume a is a fixed point number, and write out an
// integer representation (considering the decimal point at
// the lsb of a) use a hexadecimal format
30 write(cout, a, 'x', 10);

// use a binary format

```

0907353-060404
104050" E55E2860

```

write(cout, a, 'b', 10);
// use a decimal format
write(cout, a, 'd', 10);

```

```

5 // read a from stdin
  cin >> a;

```

Communication

10 Apart from values, OCAPI is concerned with the communication of values in between blocks of behavior. The high level method of communication in OCAPI is a FIFO queue, of type "dfbfix". This queue is conceptually infinite in length. In practice it is bounded by a sysop
 15 phonecall telling that you have wasted up all the swap space of the system.

The dfbfix class

20 A queue is declared as

```
dfbfix a(``a'');
```

This creates a queue with name a. The queue is intended to
 25 pass value objects of the type "dfix". There is also an alias type of "dfbfix", known as "FB" (flow buffer). So you can also write

```
FB a(``a'');
```

30

The dfbfix operations

The basic operations on a queue allow to store and retrieve "dfix" objects. The operations are

```

dfix k;
5  dfix j(0.5);
    dfbfix a("`a'");

    // insert j at the front of a
    a.put(j);
10 // operator format for an insert
    a << j;

    // insert j at position 5, with position 0 corresponding to
    // the front of a.
15 a.putIndex(j,5);

    // read one element from the back of a
    k = a.get();

20 // operator format for a read
    a >> j;

    // peek one element at position 1 of a
    k = a.getIndex(1);
25

    // operator format for peek
    k = a[1];

    // retrieve one element from a and throw it
30 a.pop();

    // throw all elements, if any, from a

```

```
a.clear();
```

```
// return the number of elements in a as an int
int n = a.getSize();
```

5

```
// return the name of the queue
char *p = a.name();
```

Whenever you perform an access operation that reads past
10 the end of a FIFO, a runtime error results, showing

```
Queue Underflow @ get in queue a
```

Utility calls for dfbfix

15

Besides the basic operations on queues, there are some additional utility operations that modify a queue behavior

```
// make a queue of length 20. The default length of a queue
20 // is 16. Whenever this length is exceeded by a put, the
// storage in the queue is dynamically expanded by a factor
// of 2.
```

```
dfbfix a("`a'", 20);
```

```
25 // After the asType() call, the queue will have an input
// "`quantizer'" that will quantize each element inserted
// into the queue to that of the quantizer type
```

```
dfix q(0, 10, 8);
```

```
a.asType(q);
```

```
30 // After an asDebug() call, the queue is associated with a
// file, that will collect every value written into the
// queue. The file is opened as the queue is initialized
```

"09073333"050401

```

// and closed when the queue object is destroyed.
a.asDebug(``thisfile.dat'');
// Next makes a duplicate queue of a, called b. Every write
// into a will also be done on b. Each queue is allowed to
5 // have at most ONE duplicate queue.
dfbfix b(``b'');
a.asDup(b);

// Thus, when another duplicate is needed, you write is as
10 dfbfix c(``c'');
b.asDup(c);

```

During the communication of "dfix" objects, the queues keep track of some statistics on the values that are passed

15 through it. You can use the "<<" operator and the member function "stattitle()" to make these statistics visible.

The next program demonstrates these statistics

```

20          #include "qlib.h"

          void main()
          {
              dfbfix a("a");
              25      a << dfix(2);
              a << dfix(1);
              a << dfix(3);

              a.stattitle(cout);
              30      cout << a;
          }

```

When running this program, the following appears on screen

```
Name put get MinVal @idx MaxVal @idx Max# @idx
  A   3   0 1.0000e+00   2 3.0000e+00   3   3   3
```

The first line is printed by the "stattitle()" call as a
 5 mnemonic for the fields printed below. The next line is the
 result of passing the queue to the standard output stream
 object. The fields mean the following:

- Name The name of the queue
- 10 • put The total number of elements "put()" into the
 queue
- get The total number of elements "get()" from the
 queue
- MinVal The lowest element put onto the queue
- 15 • @idx The put sequential number that passed this
 lowest element
- MaxVal The highest element put onto the queue
- @idx The put sequential number that passed this
 highest element
- 20 • Max# The maximal queue length that occurred
- @idx The put sequential number that resulted ion
 this maximal queue length

Globals and derivatives for dfbfix

25

There are two special derivates of "dfbfix". Both are
 derived classes such that you can use them wherever you
 would use a "dfbfix". Only the first will be discussed
 here, the other one is related to cycle-true simulation and

is discussed in section "Faster Communications".

The "dfbfix_nil" object is like a "/dev/null" drain. Every "dfix" written into this queue is thrown. A read operation
5 from such a queue results in a runtime error.

There are two global variables related to queues. The "listOfFB" is a pointer to a list of queues, containing every queue object you have declared in your program. The
10 member function call "nextFB()" will return the successor of the queue in the global list. For example, the code snippet

```
dfbfix *r;
15 for ( r = listOfFB ; r ; r = r->nextFB() )
    {
        ...
    }
```

20 will walk through all the queues present in the OCAPI program.

The other global variable is "nilFB", which is of the type "dfbfix_nil". It is intended to be used as a global
25 trashcan.

The basic block

OCAPI supports the dataflow simulation paradigm. In order
30 to define the actors to the system, one "base" class is used, from which all actors will inherit. In order to do untimed simulations, one should follow a standard template

to which new actor classes must conform. In this section, the standard template will be introduced, and the writing style is documented.

5 Basic block include and code file

Each new actor in the system is defined with one header file and one source code C++ file. We define a standard block, "add", which performs an addition.

10

The include file, "add.h", looks like

```
#ifndef ADD_H
```

```
#define ADD_H
```

15

```
#include ``qlib.h''
```

```
class add : public base
```

```
{
```

20

```
    public:
```

```
        add(char *name, FB & _in1, FB & _in2, FB & _o1);
```

```
        int run();
```

```
    private:
```

```
        FB *in1;
```

25

```
        FB *in2;
```

```
        FB *o1;
```

```
};
```

```
#endif
```

30

This defines a class "add", that inherits from "base". The "base" object is the one that OCAPI likes to work with, so

you must inherit from it in order to obtain an OCAPI basic block.

The private members in the block are pointers to
 5 communication queues. Optionally, the private members
 should also contain state, for example the tap values in a
 filter. The management of state for untimed blocks is
 entirely the responsibility of the user; as far as OCAPI is
 concerned, it does not care what you use as extra
 10 variables.

The public members include a constructor and an execution
 call "run". The constructor must at least contain a name,
 and a list of the queues that are used for communication.
 15 Optionally, some parameters can be passed, for instance in
 case of parametrized blocks (filters with a variable number
 of taps and the like).

The contents of the adder block will be described in
 20 "add.cxx".

```
#include ``add.cxx``

adder::adder(char *name,  FB & _in1, FB & _in2, FB & _o1) :
25  base(name)
  {
      in1 = _in1.asSource(this);
      in2 = _in2.asSource(this);
      o1 = _o1.asSink  (this);
30  }
```

```
int adder::run()
```

```

{
    // firing rule
    if (in1->getSize() < 1)
        return 0;
5    if (in2->getSize() < 1)
        return 0;

    ol->put(in1->get() + in2->get());
    return 1;
10 }

```

The constructor passes the name of the object to the "base" class it inherits from. In addition, it initializes private members with the other parameters. In this example, the communication queue pointers are initialized. This is not done through simple pointer assignment, but through function calls "asSource" and "asSink". This is not obligatory, but allows OCAPI to analyze the connectivity in between the basic blocks. Since a queue is intended for point-to-point communication, it is an error to use a queue as input or output more than once. The function calls "asSource" and "asSink" keep track of which blocks source/sink which queues. They will return a runtime error in case a queue is sourced or sinked more than once. The constructor can optionally also be used to perform initialization of other private data (state for instance). The "run()" method contains the operations to be performed when the block is invoked. The behavior is described in an iterative way. The "run" function must return an integer value, 1 if the block succeeded in performing the operation, and 0 if this has failed.

This behavior consists of two parts: a firing rule and an operative part. The firing rule must check for the availability of data on the input queues. When no sufficient data is present (checked with the "getSize()" member call), it stops execution and returns 0. When sufficient data is present, execution can start. Execution of an untimed behavior can use the different C++ control constructs available. In this example, the contents of the two input queues is read, the result is added and put into the output queue. After execution, the value 1 is returned to signal the behavior has completed.

Predefined standard blocks: file sources and sinks

15 The OCAPI library contains three predefined standard blocks, which is a file source "src", a file sink "snk", and a ram storage block "ram".

The file sources and sinks define operating system interfaces and allow you to bring file data into an OCAPI simulation, and to write out resulting data to a file. The examples below show various declarations of these blocks. Data in these files is formatted as floating point numbers separated by white space. For output, newlines are used as whitespace.

```
// define a file source block, with name a, that will read
// data from the file ``in.dat'' and put it into the queue k
```

```
dfbfix k(``k'');
30 src a(``a'', k, ``in.dat');
```

```
// an alternative definition is
```

```

dfbfix k(``k'');
src a(``a'', k);
a.setAttr(src::FILENAME, 'in.dat');

5 // which also gives you a complex version
dfbfix k1(``k1'');
dfbfix k2(``k2'');
src a(``a'', k1, k2);
a.setAttr(src::FILENAME, 'in.dat');

10 // define a sink block b, that will put data from queue o
// into a file ``out.dat''.
dfbfix o(``o'');
snk b(``b'', o, ``out.dat'');

15 // an alternative definition is
dfbfix o(``o'');
snk b(``b'', o);
b.setAttr(snk::FILENAME, ``out.dat');

20 // which gives one also a complex version
dfbfix o1(``o1'');
dfbfix o2(``o2'');
snk b(``b'', o1, o2);

25 b.setAttr(snk::FILENAME, ``out.dat');

// the snk mode has also a matlab-goodie which will format
// output data into a matrix A that can be read in directly
// by Matlab.

30 dfbfix o(``o'');
snk b(``b'', o, ``out.m'');
b.setAttr(snk::FILENAME, ``out.m');

```

```
b.setAttr(snk::MATLABMODE, 1);
```

Predefined standard blocks: RAM

- 5 The ram untimed block is intended to simulate single-port storage blocks at high level. By necessity, some interconnect assumptions had to be made on this block. On the other hand, it is supported all the way through code generation.

10

OCAPI does not generate RAM cells. However, it will generate appropriate connections in the resulting system netlist, onto which a RAM cell can be connected.

- 15 The declaration of a ram block is as follows.

```
// make a ram a, with an address bus, a data input bus, a
// data output bus, a read command line, a write command
// line, with 64 locations
```

20

```
dfbfix address(``address'');
dfbfix data_in(``data_in'');
dfbfix data_out(``data_out'');
dfbfix read_c(``read_c'');
```

25 dfbfix write_c(``write_c');

```
ram a(``a'',address,data_in,data_out,write_c,read_c,64);
```

```
// clear the ram
```

30 a.clear();

```
// fill the ram with the linear sequence data = k1+address
```

T04090" E55E2860

```

// * k2;
a.fill(k1, k2);

// dump the contents of a to cout
5 a.show();

```

The execution semantics of the ram are as follows. For each read or write, an address, a read command and a write command must be presented. If the read command equals

10 "dfix(1)", a read will be performed, and the value stored at the location presented through "address" will be put on "data_out". If the read command equals any other value, a dummy byte will be presented at "data_out". If no read command was presented, no data will be presented on

15 "data_out". For writes, an identical story holds for reads on the "data_in" input: whenever a write command is presented, the data input will be consumed. When the write command equals 1, then the data input will be stored in the location provided through "address". When a read and write

20 command are given at the same time, then the read will be performed before the write. The ram also includes an online "purifier" that will generate a warning message whenever data from an unwritten location is read.

25 Untimed simulations

Given the descriptions of one or more untimed blocks, a simulation can be done. The description of a simulation requires the following to be included in a standard C++

30 "main()" procedure:

- The instantiation of one or more basic blocks.

- The instantiation of one or more communication queues that interconnect the blocks
 - The setup of stimuli. Either these can be included at runtime by means of the standard file source blocks, or
5 else dedicated C++ code can be written that fills up a queue with stimuli.
 - A schedule that drives the execution methods of the basic blocks.
- 10 A schedule, in general, is the specification of the sequence in which block firing rules must be tested (and fired if necessary) in order to run a simulation. There has been quite some research in determining how such a schedule can be constructed automatically from the interconnection
15 network and knowledge of the block behavior. Up to now, an automatic mechanism for a general network with arbitrary blocks has not been found. Therefore, OCAPI relies on the designer to construct such a schedule.

20 *Layout of an untimed simulation*

In this section, the template of the standard simulation program will be given, along with a description of the "scheduler" class that will drive the simulation. A
25 configuration with the "adder" block (described in the section on basic blocks) is used as an example.

```
#include ``qlib.h''
#include ``add.h''
```

30

```
void main()
{
```

```

dfbfix i1("i1");
dfbfix i2("i2");
dfbfix o1("o1");

5      src SRC1("SRC1", i1,"SRC1");
      src SRC2("SRC2", i2,"SRC2");
      add ADD ("ADD" , i1, i2, o1);
      snk SNK1("SNK1", o1,"SNK1");

10     schedule S1("S1");
      S1.next(SRC1);
      S1.next(SRC2);
      S1.next(ADD );
      S1.next(SNK1);

15     while (S1.run());

      i1.stattitle(cout);
      cout << i1;
20     cout << i2;
      cout << o1;

}

```

The simulation above instantiates three communication
 25 buffers, that interconnect four basic blocks. The
 instantiation defines at the same time the interconnection
 network of the simulation. Three of the untimed blocks are
 standard file sources and sinks, provided with OCAPI. The
 "add" block is a user defined one.

30

After the definition of the interconnection network, a
 schedule must be defined. A simulation schedule is

constructed using "schedule" objects. In the example, one schedule object is defined, and the four blocks are assigned to it by means of a "next()" member call.

5 The order in which "next()" calls are done determines the order in which firing rules will be tested. For each execution of the schedule object "S1", the "run()" methods of "SRC1", "SRC2", "ADD" and "SNK1" are called, in that order. The execution method of a scheduler object is called
 10 "run()". This function returns an integer, equal to one when at least one block in the current iteration has executed (i.e. the "run()" of the block has returned one). When no block has executed, it returns zero.

15 The while loop in the program therefore is an execution of the simulation. Let us assume that the directory of the simulator executable contains the two required stimuli files, "SRC1" and "SRC2". Their contents is as follows

20	SRC1	SRC2	-- not present in the file
	----	----	-- not present in the file
	1	4	
	2	5	
	3	6	

25

When compiling and running this program, the simulator responds:

```

*** INFO: Defining block SRC1
30 *** INFO: Defining block SRC2
*** INFO: Defining block ADD
*** INFO: Defining block SNK1

```

Name	put	get	MinVal	@idx	MaxVal	@idx	Max#	@idx
i1	3	3	1.0000e+00	1	3.0000e+00	3	1	1
i2	3	3	4.0000e+00	1	6.0000e+00	3	1	1
o1	3	3	5.0000e+00	1	9.0000e+00	3	1	1

and in addition has created a file "SNK1", containing

SNK1 -- not present in the file

5 ---- -- not present in the file

5.000000e+00

7.000000e+00

9.000000e+00

- 10 The "INFO" message appearing on standard output are a side effect of creating a basic block. The table at the end is produced by the print statements at the end of the program.

More on schedules

15

If you would examine closely which blocks are fired in which iteration, (for instance with a debugger) then you would find

20 iteration 1

run SRC1 => i1 contains 1.0

run SRC2 => i2 contains 4.0

run ADD => o1 contains 5.0

run SNK1 => write out o1

25 schedule.run() returns 1

iteration 2

run SRC1 => i1 contains 2.0

run SRC2 => i2 contains 5.0

T04090"060401

```

run ADD => o1 contains 7.0
run SNK1 => write out o1

schedule.run() returns 1
iteration 3
5      run SRC1 => i1 contains 3.0
      run SRC2 => i2 contains 6.0
      run ADD  => o1 contains 9.0
      run SNK1 => write out o1

schedule.run() returns 1
10 iteration 4

      run SRC1 => at end-of-file, fails
      run SRC2 => at end-of-file, fails
      run ADD  => no input tokens, fails
      run SNK1 => no input tokens, fails

15 schedule.run() returns 0 => end simulation

```

There are two schedule member functions, "traceOn()" and "traceOff()", that will produce similar information for you. If you insert

```

20 S.traceOn();

```

just before the while loop, then you see

```

25 *** INFO: Defining block SRC1
    *** INFO: Defining block SRC2
    *** INFO: Defining block ADD
    *** INFO: Defining block SNK1
    S1 [ SRC1 SRC2 ADD SNK1 ]
30 S1 [ SRC1 SRC2 ADD SNK1 ]
    S1 [ SRC1 SRC2 ADD SNK1 ]
    S1 [ ]

```

Name	put	get	MinVal	@idx	MaxVal	@idx	Max#	@idx
i1	3	3	1.0000e+00	1	3.0000e+00	3	1	1
i2	3	3	4.0000e+00	1	6.0000e+00	3	1	1
o1	3	3	5.0000e+00	1	9.0000e+00	3	1	1

appearing on the screen. This trace feature is convenient during schedule debugging.

- 5 In the simulation output, you can also notice that the maximum number of tokens in the queues never exceeds one. When you had entered another schedule sequence, for example

```
schedule S1("S1");
```

```
10         S1.next(ADD );
           S1.next(SRC2);
           S1.next(SRC1);
           S1.next(SNK1);
```

- 15 then you would notice that the maximum number of tokens on the queues would result in different figures. On the other hand, the resulting data file, "SNK1", will contain exactly the same results. This demonstrates one important property of dataflow simulations: any arbitrary but consistent
- 20 schedule yields the same results. Only the required amount of storage will change from schedule to schedule.

- In multirate systems, it is convenient to have different schedule objects and group all blocks working on the same
- 25 rate in one schedule.

Profiling in untimed simulations

Untimed simulations are not targeted to circuit implementation. Rather, they have an explorative character. Besides the queue statistics, OCAPI also enables you to do precise profiling of operations. The requirement for this
 5 feature is that

- You use "schedule" objects to construct the simulation
- You describe block behavior with "dfix" objects

10 Profiling is by default enabled. To view profiling results, you send the schedule object under consideration to the standard output stream. In the "main" example program given above, you can modify this as

```

15 include ``qlib.h''
   include ``add.h''

   void main()
   {
20         ...
           schedule S1("S1");
           ...
           cout << S1;
   }
25
```

When running the simulation, you will see the following appearing on stdout:

```

*** INFO: Defining block SRC1
30 *** INFO: Defining block SRC2
*** INFO: Defining block ADD
*** INFO: Defining block SNK1
```

Name	put	get	MinVal	@idx	MaxVal	@idx	Max#	@idx
i1	3	3	1.0000e+00	1	3.0000e+00	3	1	1
i2	3	3	4.0000e+00	1	6.0000e+00	3	1	1
o1	3	3	5.0000e+00	1	9.0000e+00	3	1	1

Schedule S1 ran 4 times:

```

                SRC1    3
                SRC2    3
5              ADD     3
                +       3
                SNK1    3

```

For each schedule, it is reported how many times it was
 10 run. Inside each schedule, a firing count of each block is
 given. Inside each block, an operation execution count is
 given. The simple "add" block gives the rather trivial
 result that there were three additions done during the
 simulation.

15 The gain in using operation profiling is to estimate the
 computational requirement for each block. For instance, if
 you find that you need to do 23 multiplications in a block
 that was fired 5 times, then you would need at least five
 20 multipliers to guarantee the block implementation will need
 only one cycle to execute.

Finally, if you want to suppress operation profiling for
 some blocks, then you can use the member function call
 "noOpsCnt()" for each block. For instance, writing

25
 ADD.noOpsCnt();

suppresses operation profiling in the ADD block.

Implementation

The features presented in the previous sections contain
 5 everything you need to do untimed, high level simulations.
 These kind of simulations are useful for initial
 development. For real implementation, more detail has to be
 added to the descriptions.

10 OCAPI makes few assumptions on the target architecture of
 your system. One is that you target bitparallel and
 synchronous hardware. Synchronicity is not a basic
 requirement for OCAPI. The current version however
 constructs single-thread simulations, and also assumes that
 15 all hardware runs at the same clock. If different clocks
 need to be implemented, then a change to the clock-cycle
 true simulation algorithm will have to be made. Also, it is
 assumed that one basic block will eventually be implemented
 into one processor.

20

One question that comes to mind is how hardware sharing
 between different basic blocks can be expressed. The answer
 is that you will have to construct a basic block that
 merges the two behaviors of two other blocks. Some
 25 designers might feel reluctant to do this. On the other
 hand, if you have to write down merged behavior, you will
 also have to think about the control problems that are
 induced from doing this merging. OCAPI will not solve this
 problem for you, though it will provide you with the means
 30 to express it.

Before code generation will translate a description to an

HDL, one will have to take care of the following tasks:

- One will have to specify wordlengths. The target hardware is capable of doing bitparallel, fixed point operations, but not of doing floating point operations. One of the design tasks is to perform the quantisation on floating point numbers. The "dfix" class discussed earlier contains the mechanisms for expressing fixed point behavior.
- One will have to construct a clock-cycle true description. In constructing this description, one will not have to allocate actual hardware, but rather express which operations one expects to be performed in which clock cycle. The semantical model for describing this clock cycle true behavior consists of a finite state machine, and a set of signal flow graphs. Each signal flow graph expresses one cycle of implemented behavior. This style of description splits the control operations from data operations in your program. In contrast, the untimed description you have used before has a common representation of control and data.

OCAPI does not force an ordering on these tasks. For instance, one might first develop a clock cycle true description on floating point numbers, and afterwards tackle the quantization issues. This eases verification of the clock-cycle true circuit to the untimed high level simulation.

The final implementation also assumes that all communication queues will be implemented as wiring. They will contain no storage, nor they will be subject to buffer

synthesis. In a dataflow simulation, initial buffering values can however be necessary (for instance in the presence of feedback loops). In OCAPI, such a buffer must be implemented as an additional processor that incorporates
 5 the required storage. The resulting system dataflow will become deadlocked because of this. The cycle scheduler however, that simulates timed descriptions, is clever enough to look for these 'initial tokens' inside of the descriptions.

10

In the next sections, the classes that allow you to express clock cycle true behavior are introduced.

Signals and signal flowgraphs

15

Some initial considerations on signals are introduced first.

Hardware versus Software

20

Software programs always use memory to store variables. In contrast, hardware programs work with signals, which might or might not be stored into a register. This feature can be expressed in OCAPI by using the "_sig" class. Simply
 25 speaking, a "_sig" is a "dfix" for which one has indicated whether it needs storage or not.

In implementation, a signal with storage is mapped to a net driven by a register, while an immediate signal is mapped
 30 to a net driven by an operator.

Besides the storage issue, a signal also departs from the

09073353-060401

concept of "scope" one uses in a program. For instance, in a function one can use local variables, which are destroyed (i.e. for which the storage is reclaimed) after one has executed the function. In hardware however, one controls
 5 the signal-to-net mapping by means of the clock signal.

Therefore one have to manage the scope of signals. The signal scope is expressed by using a signal flowgraph object, "sfg". A signal flowgraph marks a boundary on
 10 hardware behavior, and will allow subsequent synthesis tools to find out operator allocation, hardware sharing and signal-to-net mapping.

The _sig class and related operations

15

Hardware signals can expressed in three flavors. They can be plain signals, constant signals, or registered signals. The following example shows how these three can be defined.

```
20 // define a plain signal a, with a floating point dfix
    // inside of it.
    _sig a(``a'');
```

```
    // define a plain signal b, with a fixed point dfix inside
25 // of it.
    _sig b(``b'', dfix(0,10,8));
```

```
    // define a registered signal c, with an initial value k
    // and attached to a clock ck.
30 dfix k(0.5);
    clk ck;
    _sig c(``c'', ck, k);
```

```
// define a constant signal d, equal to the value k
_sig d(k);
```

5 The registered signals, and more in particular the clock object, are explained more into detail when signal flowgraphs and finite state machines are discussed. This section concentrates on operations that are available for signals.

10

Using signals and signal operations, one can construct expressions. The signal operations are a subset of the operations on "dfix". This is because there is a hardware operator implementation behind each of these operations.

15

- +, -, *

Standard addition, subtraction (including unary minus), multiplication

- &, |, ^, ~

20 Bitwise and, or, exor, and not operators

- ==, !=, <=, >=, <, >

Relational operators

- <<, >>

Left and right shifts

25 • s.cassign(s1,s2)

Conditional assignment with s1 or s2 depending on s

- cast(T,s)

Convert the type of s to the type expressed in "dfix" T

- lu(L,s)

30 Use s as in index into lookuptable L and retrieve

- msbpos(s)

09673653-060404

Return the position of the msb in s

Precision considerations are the same as for "dfix". That is, precision is at most the mantissa precision of a double (53 bits). For the bitwise operations, 32 bits are assumed (a long). "cast", "lu" and "msbpos" are not member but friend functions. In addition, "msbpos" expects fixed-point signals.

```

10 _sig a(``a'');
    _sig b(``b'');
    _sig c(``c'');

    // some simple operations
15 c = a + b;
    c = a - b;
    c = a * b;

    // bitwise operations works only on fixed point signals
20 _sig e(dfex(0xff, 10, 0));
    _sig d(``d'',dfex(0,10,0));
    _sig f(``f'',dfex(0,10,0));
    f = d & e;
    f = d | e;
25 f = ~d;
    f = d ^ _sig(dfex(3,10,0));

    // shifting
    // a dfex is automatically promoted to a constant _sig
30 f = d << dfex(3,8,0);

    // conditional assignment

```

```

f = (d < dfix(2,10,0)).cassign(e,d);

// type conversion is done with cast
_sig g(``g'',dfix(0,3,0));
5 g = cast(dfix(0,3,0), d);

// a lookup table is an array of unsigned long
unsigned long j = {1, 2, 3, 4, 5};
// a lookuptable with 5 elements, 3 bits wide
10 lookupTable j_lookup(``j_lookup'', 5, dfix(0,3,0)) = j;
// find element 2
g = lu(j_lookup, dfix(2,3,0));

```

If one is interested in simulation only, then one should
 15 not worry too much about type casting and the like.
 However, if one intends implementation, then some rules are
 at hand. These rules are induced by the hardware synthesis
 tools. If one fails to obey them, then one will get a
 runtime error during hardware synthesis.

20

- All operators, apart from multiplication, return a signal with the same wordlength as the input signal.
- Multiplication returns a wordlength that is the sum of the input wordlengths.
- 25 • Addition, subtraction, bitwise operations, comparisons and conditional assignment require the two input operands to have the same wordlength.

Some common pitfalls that result of this restriction are
 30 the following.

- Intermediate results will, by default, not expand

wordlength. In contrast, operations on `dfix` do not lose precision on intermediate results. For example, shifting an 8 bit signal up 8 positions will return you the value of zero, on 8 bits. If you want to keep up the precision, then you must first cast the operation to the desired output wordlength, before doing the shift.

- The multiplication operator increases the wordlength, which is not automatically reduced when you assign the result to a signal of smaller width. If you want to reduce wordlength, then you must do this by using a cast operation.

For complex expressions, these type promotion rules look a bit tedious. They are however used because they allow you to express behavior precisely down to the bit level. For example, the following piece of code extracts each of the bits of a three bit signal:

```

_sig threebits(dfix(6,3,0));
dfix bit(0,1,0);

_sig bit2(``bit2''), bit1(``bit1''), bit0(``bit0'');

bit2 = cast(bit, threebits >> dfix(2));
bit1 = cast(bit, threebits >> dfix(1));
bit0 = cast(bit, threebits);

```

These bit manipulations were not possible without the given type promotion rules.

For hardware implementation, the following operators are

present.

- Addition and subtraction are implemented on ripple-carry adder/subtractors.
- 5 • Multiplication is implemented with a booth multiplier block.
- Casts are hardwired.
- Shifts are either hardwired in case of constant shifts, or else a barrel shifter is used in case of variable shifts.
- 10 • Comparisons are implemented with dedicated comparators (in case of constant comparisons), or subtractions (in case of variable comparisons).
- Bitwise operators are implemented by their direct gate equivalent at the bit level.
- 15 • Lookup tables are implemented as PLA blocks that are mapped using two-level or multi-level random logic.
- Conditional assignment is done using multiplexers.
- Msbit detection is done using a dedicated msbit-detector.
- 20

Globals and utility functions for signals

There are a number of global variables that directly relate to the "_sig" class, as well as the embedded "sig" class. In normal circumstances, you do not need to use these functions.

The variables "glbNumberOf_Sig" and "glbNumberOfSig" contain the number of "_sig" and "sig" that your program has defined. The variable "glbNumberOfReg" contains the

number of "sig" that are of the register type. This represents the word-level register count of your design. The "glbSigHashConflicts" contain the number of hash conflicts that are present in the internal signal data structure organization. If this number is more then, say 5% of "glbNumberOf_Sig", then you might consider knocking at OCAPIs complaint counter. The simulation is not bad if you exceed this bound, only it will go slower.

- 10 The variable "glbListOfSig" contains a global list of signals in your system. You can go through it by means of

```
sig *run;
for (run = glbListOfSig; run; run = run->nextsig())
15 {
    ...
}
```

For each such a "sig", you can access a number of utility
20 member functions.

- "isregister()" returns 1 when a signal is a register.
- "isconstant()" returns 1 when a signal is a constant value.
- 25 • "isterm()" returns 1 when you have defined this signal yourself. These are signals which are introduced through "_sig()" class constructors. OCAPI however also adds signals of its own.
- "getname()" returns the "char *" name you have used to
30 define the signal.
- "get_showname()" returns the "char *" name of the signal

that is used for code generation. This is equal to the original name, but with a unique suffix appended to it.

The sfg class

5

In order to construct a timed (clocked) simulation, signals and signals expressions must be assigned to a signal flowgraph. A signal flowgraph (in the context of OCAPI) is a container that collects all behavior that must be
10 executed during one clock cycle.

The sfg behavior contains

- A set of expressions using signals
- 15 • A set of inputs and outputs that relate signals to output and input queues

Thus, a signal flowgraph object connects local behavior (the signals) to the system through communications queues.

20 In hardware, the indication of input and output signals also results in ports on your resulting circuit.

A signal flowgraph can be a marker of hardware scope. This is also demonstrated by the following example.

25

```
_sig a(``a'');
_sig b(``b'');
_sig c(dfix(2));
```

```
30 dfbfix A(``A'');
dfbfix B(``B'');
```

```

// a signal flowgraph object is created
sfg add_two, add_three;

// from now on, every signal expression written down will
5 // be included in the signal flowgraph add_two
add_two.starts();
a = b + c;

// You must also give a name to add_two, for code
10 // generation
add_two << ``add_two'';

// also, inputs and outputs have to be indicated.
// you use the input and output objects ip and op for this
15 add_two << ip(b, B);
add_two << op(a, A);

// next expression will be part of add_three
add_three.starts();
20 a = b + dfix(3);

add_three << ``add_three'';
add_three << ip(b,B);
add_three << op(a,A);

25

// you can also to semantical checks on signal flowgraphs
add_two.check();
add_three.check();

The semantical check warns you for the following
30 specification errors:

```

- Your signal flowgraph contains a signal which is not

declared as a signal flowgraph input and at the same time, it is not a constant or a register. In other words, your signal flowgraph has a dangling input.

- You have written down a combinatorial loop in your signal flowgraph. Each signal must be ultimately dependent on registered signals, constants, or signal flowgraph inputs. If any other dependency exists, you have written down a combinatorial loop for which hardware synthesis is not possible.

10

Execution of a signal flowgraph

A signal flowgraph defines one clock cycle of behavior. The semantics of a signal flowgraph execution are well defined.

15

- At the start of an execution, all input signals are defined with data fetched from input queues.
- The signal flowgraph output signals are evaluated in a demand driven way. That is, if they are defined by an expression that has signal operands with known values, then the output signal is evaluated. Otherwise, the unknown values of the operands are determined first. It is easily seen that this is a recursive process. Signals with known values are: registered signals, constant signals, and signals that have already been calculated in the current execution.
- The execution ends by writing the calculated output values to the output queues.

30 Signal flowgraph semantics are somewhat related to untimed blocks with firing rules. A signal flowgraph needs one

09876543210

token to be present on each input queue. Only, the firing rule on a signal flowgraph is not implemented. If the token is missing, then the simulation crashes. This is a crude way of warning you that you are about to let your hardware

5 evaluate a nonsense result.

The relation with untimed block firing rules will allow to do a timed simulation which consist partly of signal flowgraph descriptions and partly of untimed basic blocks.

10 The section "Timed simulations will treat this more into detail.

Running a signal flowgraph by hand

15 A signal flowgraph is only part of a timed description. The control component (an FSM) still needs to be introduced. There can however be situations in which you would like to run a signal flowgraph directly. For instance, in case you have no control component, or if you have not yet developed

20 a control description for it.

The "sfg" member function "run()" performs the execution of the signal flowgraph as described above. An example is used to demonstrate this.

25

```
#include "qlib.h"
```

```
void main()
```

```
30 {
        _sig a("a");
        _sig b("b");
```

```

        _sig c(dfix(2));

        dfbfix A("A");
        dfbfix B("B");

5         sfg add_two;
          add_two.starts();
          a = b + c;
          add_two << "add_two";
10         add_two << ip(b, B);
          add_two << op(a, A);

          add_two.check();

15         B << dfix(1) << dfix(2);

          // running silently
          add_two.eval();
          cout << A.get() << "\n";

20         // running with debug information
          add_two.eval(cout);
          cout << A.get() << "\n";

25         add_two.eval(cout);
          }

```

When running this simulation, the following appears on the screen.

```

30  3.000000e+00
    add_two(      b      2)

```

```

:      a      4
=>     a      4

```

```
4.000000e+00
```

```
add_two(Queue Underflow @ get in queue B
```

5

The first line shows the result in the first "eval()" call. When this call is given an output stream as argument, some additional information is printed during evaluation. For each signal flowgraph, a list of input values is printed.

10 Intermediate signal values are printed after the ":" at the beginning of the line. The output values as they are entered in the output queues are printed after the "=>". Finally, the last line shows what happens when "eval()" is called when no inputs are available on the input queue "B".

15

For signal flowgraphs with registered signals, you must also control the clock of these signals. An example of an accumulator is given next.

```
20 #include "qlib.h"
```

```
void main()
{
```

```
    clk ck;
```

25

```
    _sig a("a",ck,dfix(0));
    _sig b("b");
```

```
    dfbfix A("A");
```

30

```
    dfbfix B("B");
```

```
    sfg accu;
```

09876543210

```

accu.starts();
a = a + b;
accu << "accu";
accu << ip(b, B);
5  accu << op(a, A);
accu.check();

B << dfix(1) << dfix(2) << dfix(3);
while (B.getSize())
10 {
    accu.eval(cout);
    accu.tick(ck);
}
15

```

The simulation is controlled in a while loop that will consume all input values in queue "B". After each run, the clock attached to registered signal "a" is triggered. This is done indirectly through the "sfg" member call "tick()",

20 that updates all registered signals that have been assigned within the scope of this "sfg". Running this simulation results in the following screen output

```

accu      (      b      1)
25         :      a      0/      1
          =>      a      0/      1

accu      (      b      2)
          :      a      1/      3
          =>      a      1/      3

30 accu    (      b      3)
          :      a      3/      6
          =>      a      3/      6

```

The registered signal "a" has two values: a present value (shown left of "/"), and a next value (shown right of "/"). When the clock ticks, the next value is copied to the present value. At the end of the simulation, registered signal "a" will contain 6 as its present value. The output queue "A" however will contain the 3, the "present value" of "a" during the last iteration.

- 10 Finally, if you want to include a signal flowgraph in an untimed simulation, you must make sure that you implement a firing rule that guards the sfg evaluation.

An example that incorporates the accumulator into an untimed basic block is the following.

```
#include "qlib.h"

class accu : public base
20 {
    public:
        accu(char *name, dfbfix &i, dfbfix &o);
        int run();
    private:
25     dfbfix *ipq;
        dfbfix *opq;
        sfg _accu;
        clk ck;
    }
30
accu::accu(char *name, dfbfix &i, dfbfix &o) : base(name)
{
```

F04030"ESSEZ860

```

        ipq = i.asSource(this);
        opq = o.asSink(this);

        _sig a("a",ck,dfix(0));
5      _sig b("b");
        _accu.starts();
        a = a + b;
        _accu << "accu";
        _accu << ip(b, *ipq);
10     _accu << op(a, *opq);
        _accu.check();
    }

    int accu::run()
15 {
        if (ipq->getSize() < 1)
            return 0;
        _accu.eval();
        _accu.tick(ck);
20 }

```

In this example, the signal flowgraph `_accu` is included into the private members of class `_accu`.

25 *Globals and utility functions for signal flowgraphs*

The global variable "glbNumberOfSfg" contains the number of "sfg" objects that you have constructed in your present OCAPI program. Given an "sfg()" object, you have also a

30 number of utility member function calls.

- "getname()" returns the "char *" name of the signal flowgraph.
- "merge()" joins two signal flowgraphs.
- "getisig(int n)" returns a "sig *" that indicates which
5 signal corresponds to input number "i" of the signal flowgraph. If 0 is returned, this input does not exist.
- "getiqueue(int n)" returns the queue ("dfbfix *") assigned to input number "i" of the signal flowgraph. If 0 is returned, then this input does not exist.
- 10 • "getosig(int n)" returns a "sig *" that indicates which signal corresponds to output number "i" of the signal flowgraph. If 0 is returned, this output does not exist.
- "getoqueue(int n)" returns the queue ("dfbfix *")
15 assigned to output number "i" of the signal flowgraph. If 0 is returned, then this output does not exist.

You should keep in mind that a signal flowgraph is a data structure. The source code that you have written helps to
20 build this data structure. However, a signal flowgraph is not executed by running your source code. Rather, it is interpreted by OCAPI. You can print this data structure by means of the "cg(ostream)" member call.

25 For example, if you appended

```
accu.cg(cout);
```

to the "running-an-sfg-by-hand" example, then the following
30 output would be produced:

sfg accu

```

        inputs    { b_2 }
        outputs    { a_1 }
        code {
5           a_1 = a_1_at1 + b_2;
        };

```

Finite state machines

- 10 With the aid of signals and signal flowgraphs, you are able to construct clock-cycle true data processing behavior. On top of this data processing, a control sequencing component can be added. Such a controller allows to execute signal flowgraphs conditionally. The controller is also the
- 15 anchoring point for true timed system simulation, and for hardware code generation. A signal flowgraph embedded in an untimed block cannot be translated to a hardware processor: you have to describe the control component explicitly.

20 *The ctlfsm and state classes*

The controller model currently embedded in OCAPI is a Mealy-type finite state machine. This type of FSM selects the transition to the next state based on the internal

25 state and the previous output value.

In an OCAPI description, you use a "ctlfsm" object to create such a controller. In addition, you make use of "state" objects to model controller states. The following

30 example shows the use of these objects.

```
#include ``qlib.h''
```

```

void main()
{
    sfg dummy;
5    dummy << ``dummy'';

    // create a finite state machine
    ctlfsm f;

10    // give it a name
    f << ``theFSM'';
    // create 2 states for it
    state rst;
    state active;
15    // give them a name
    rst << ``rst'';
    active << ``active'';

    // identify rst as the initial state of
20    // ctlfsm f
    f << deflt(rst);
    // identify active as a plain state of ctlfsm
    // f
    f << active;

25    // create an unconditional transition from
    // rst to active
    rst << always << active;
    // always' is a historical typo and will be
30    // replaced by "always" in the future

    // create an unconditional transition from

```

09873453-060401

```

// active to active, executing the dummy sfg.
active << always << dummy << active;

// show what's inside f
5      cout << f;
      }

```

There are two states in this fsm, "rst" and "active". Both are inserted in the fsm by means of the "<<" operator. In addition, the "rst" state is identified as the default state of the fsm, by embedding it into the "deflt" object. An fsm is allowed to have one default state. When the fsm is simulated, then the state at the start of the first clock cycle will be "rst". In the hardware implementation, a "reset" pin will be added to the processor that is used to initialize the fsm's state register with this state.

Two transitions are defined. A transition is written according to the template: starting state, conditions, actions, target state, all of this separated by the "<<" operator. The condition "always" is a default condition that evaluates to true. It is used to model unconditional transitions.

The last line of the example shows a simple operation you can do with an fsm. By relating it to the output stream, the following will appear on the screen when you compile and execute the example.

```

30 digraph g
    {
        rst [shape=box];

```

```

        rst->active;
        active->active;
    }

```

- 5 This output represent a textual format of the state transition diagram. The format is that of the "dotty" tool, which produces a graphical layout of your state transition diagram.

"dotty" is commercial software available from AT&T.

10

You cannot simulate a "ctlfsm" object on itself. You must do this indirectly through the "sysgen" object, which is introduced in the section "Timed Simulations".

15 *The cnd class*

Besides the default condition "allways", you can use also boolean expressions of registered signals. The signals need to be registered because we are describing a Mealy-type

20 fsm. You construct conditions through the "cnd" object, as shown in the next example.

```
#include "qlib.h"
```

25 void main()

```

{
    clk ck;
    _sig a("a",ck, dfix(0));
    _sig b("b",ck, dfix(0));
    30 _sig a_input("a");
    _sig b_input("a");
    dfbfix A("A");

```

```
dfbfix B("B");
```

```
sfg some_operation;
```

```
// some operations go here ...
```

5

```
sfg readcond;
```

```
readcond.starts();
```

```
a = a_input;
```

```
b = b_input;
```

10

```
readcond << "readcond";
```

```
readcond << ip(a_input,A);
```

```
readcond << ip(binput,B);
```

```
readcond.check();
```

15

```
// create a finite state machine
```

```
ctl fsm f;
```

```
f << "theFSM";
```

```
state rst;
```

20

```
state active;
```

```
state wait;
```

```
rst << "rst";
```

```
active << "active";
```

25

```
wait << "wait";
```

```
f << deflt(rst);
```

```
f << active;
```

```
f << wait;
```

30

```
rst << always << readcond << active;
```

```
active << _cnd(a) << readcond << some_operation  
<< wait;
```

F04030-030401

```

wait      << (_cnd(a) && _cnd(b)) << readcond
          << wait;
wait      << (!_cnd(a) || !_cnd(b)) << readcond << active;
}

```

5

A FAQ is why condition signals must be registers, and whether they can be plain signals also. The answer is simple: no, they can't. The fsm control object is a stand-alone machine that must be able to 'boot' every clock
 10 cycle. During one execution cycle, it will first select the transition to take (based on conditions), and then execute the signal flowgraphs that are attached to this transition. If "immediate" transition conditions had to be expressed, then the signals should be read in before the fsm
 15 transition is made, which is not possible: the execution of an sfg can only be done when a transition is selected, in other words: when the condition signals are known. Besides this semantical consideration, the registered-condition requirement will also prevent you from writing
 20 combinatorial control loops at the system level.

The first signal flowgraph "readcond" takes care of reading in two values "a" and "b" that are used in transition conditions. The sfg reads the signals "a" and "b" in
 25 through the intermediate signals "a_input" and "b_input". This way, "a" and "b" are explicitly assigned in the signal flowgraph, and the semantical check "readcond.check()" will not complain about unassigned signals.

30 The fsm below it defines three states. Besides an initial state "rst" and an operative state "active", a wait state "wait" is defined, that is entered when the input signal

09873353-060401

"a" is high. This is expressed by the "_cnd(a)" transition condition in the second fsm transition. You must use "_cnd()" instead of "cnd()" because of the same reason that you must use "_sig()" instead of "sig()": The underscore-
 5 type classes are empty boxes that allocate the objects that do the real work for you. This allocation is dynamic and independent of the C++ scope.

Once the wait state is entered, it can leave it only when
 10 the signals "a" or "b" go low. This is indicated in the transition condition of the third fsm transition. A "&&" operator is used to express the and condition. If the signals "a" and "b" remain high, then the wait state is not left. The transition condition of the last transition
 15 expresses this. It uses the logical not "!" and logical or "||" operators to express this.

The "readcond" signal flowgraph is executed at all transitions. This ensures that the signals "a" and "b" are
 20 updated every cycle. If you fail to do this, then the value of "a" and "b" will not change, potentially creating a deadlock.

To summarize, you can use either "always" or a logical
 25 expression of "_cnd()" objects to express a transition condition. The signals use in the condition must be registers. This results in a Mealy-type fsm description

Utility functions for fsm objects

30

A number of utility functions on the "ctrlfsm" and "state" classes are available for query purposes. This is only

0987355-060401
 004090-00000000

minimal: The objects are intended to be manipulated by the cycle scheduler and code generators.

```

sfg action;
5  ctrlfsm f;
   state s1;
   state s2;

   f << deflt(s1);
10  f << s2;

   s1 << always << s2;
   s2 << always << action << s1;

15  // run through all the state in f
   statelist *r;
   for (r = f.first; r; r = r->next)
   {
       ...
20  }

   // print the nuymber of states in f,
   // print the number of transitions in f,
   // print the name of f,
   // print the number of sfg's in f
25  cout << f.numstates() << ``\n'';
   cout << f.numtransitions() << ``\n'';
   cout << f.getname() << ``\n'';
   cout << f.numactions() << ``\n'';

30  // print the name of a state
   cout << s1.getname() << ``\n'';

```

The basic block for timed simulations

Using signals, signal flowgraphs, finite state machines and states, you can construct a timed description of a block.

- 5 Having obtained such a description, it is convenient to merge it with the untimed description. This way, you will have one class that allows both timed and untimed simulation. Of course, this merging is a matter of writing style, and nothing forces you to actually have both a timed
10 and untimed description for a block.

The basic block example, that was introduced in the section "The basic block", will now be extended with a timed version. As before, both an include file and a code file
15 will be defined. The include file, "add.h", looks like the following code.

```

20 #ifndef ADD_H
    #define ADD_H

    #include ``qlib.h''

    class add : public base
    {
25         public:
            add(char *name, FB & _in1, FB & _in2, FB & _ol);

            // untimed
            int run();

30         // timed
            void    define();

```

```

        ctrlfsm  &fsm() {return _fsm};
    private:
        FB  *in1;
        FB  *in2;
5         FB  *o1;
        ctrlfsm  _fsm;
        sfg  _add;
        state  _go;
    };
10
#endif

```

The private members now also contain a control fsm object, in addition to signal flowgraph objects and states. If you
 15 feel this is becoming too verbose, you will find help in the section "Faster description using macros", that defines a macro set that significantly accelerates description entry.

20 In the public members, two additional member functions are declared: the "define()" function, which will setup the timed description data structure, and the "fsm()", which returns a pointer to the fsm controller. Through this pointer, OCAPI accesses everything it needs to do
 25 simulations and code generation.

The contents of the adder block will be described in "add.cxx".

```

30 #include ``add.h``

```

```

add::add(char *name,  FB & _in1, FB & _in2, FB & _o1) :

```

00873553.060401
 004090" 0052860

```

base(name)
{
    in1 = _in1.asSource(this);
    in2 = _in2.asSource(this);
5    o1 = _o1.asSink  (this);
    define();
}

int add::run()
10 {
    ...
}

void add::define()
15 {
    _sig i1(``i1'');
    _sig i2(``i2'');
    _sig ot(``ot'');

20    _add << ``add'';
    _add.starts();
    ot = i1 + i2;
    _add << ip(i1, *in1);
    _add << ip(i2, *in2);
25    _add << op(ot, *o1);

    _fsm << ``fsm'';
    _go  << ``go'';

30    _fsm << deflt(_go);
    _go << allways << _add << _go;
}

```

0907090"060401

If the timed description uses also registers, then a pointer to the global clock must also be provided (OCAPI generates single-clock, synchronous hardware). The easiest way is to extend the constructor of "add" with an additional parameter "clk &ck", that will also be passed to the "define" function.

Timed simulations

10

By obtaining timed descriptions for you untimed basic block, you are now ready to proceed to a timed simulation. A timed simulation differs from an untimed one in that it proceeds clock cycle by clock cycle. Concurrent behavior between different basic blocks is simulated on a cycle-by-cycle basis. In contrast, in an untimed simulation, this concurrency is present on an iteration by iteration basis.

The sysgen class

20

The "sysgen" object is for timed simulations the equivalent of a "scheduler" object for untimed simulations. In addition, it also takes care of code and testbench generation, which explains the name.

25

The sysgen class is used at the system level. The timed "add" class, defined in the previous section, is used as an example to construct a system which uses untimed file sources and sinks, and a timed "add" class.

30

```
#include ``qlib.h''
#include ``add.h''
```

```

void main()
{
    dfbfix i1("i1");
    dfbfix i2("i2");
    dfbfix o1("o1");

    src SRC1("SRC1", i1,"SRC1");
    src SRC2("SRC2", i2,"SRC2");
    add ADD ("ADD" , i1, i2, o1);
    snk SNK1("SNK1", o1,"SNK1");

    sysgen S1("S1");

    S1 << SRC1;
    S1 << SRC2;
    S1 << ADD.fsm();
    S1 << SNK1;
    S1.setinfo(verbose);
    clk ck;
    int i;
    for (i=0; i<3; i++)
    {
        S1.run(ck);
    }
}

```

The simulation is set up as before with queue objects and basic blocks. Next, a "sysgen" object is created, with name "S1". All basic blocks in the simulation are appended to the "sysgen" objects by means of the \$<<\$ operator. If a timed basic block is to be used, as for instance in case of

the "add" object, then the "fsm()" pointer must be presented to "sysgen" rather than the basic block itself. A "sysgen" object knows how to run and combine both timed and untimed objects. For the description shown above, untimed
 5 versions of the file sources and sink "src" and "snk" will be used, while the timed version of the "add" object will be used.

Next, three clock cycles of the system are run. This is
 10 done by means of the "run(ck)" member function call of "sysgen". The clock object "ck" is, because this simulation contains no registered signals, a dummy object. When running the simulator executable with stimuli file contents

```

15          SRC1    SRC2  -- not present in the file
          ----    ----  -- not present in the file
              1      4
              2      5
              3      6
  
```

20

you see the following appearing on the screen.

```

          *** INFO: Defining block SRC1
          *** INFO: Defining block SRC2
25          *** INFO: Defining block ADD
          *** INFO: Defining block SNK1
          fsm fsm: transition from go to go
          add#0
          add#1
30          in   i1   1
          in   i2   4
          sig  ot   5
  
```

T01090"CSSE4960

```

out' ot    5
fsm fsm: transition from go to go
add#0
add#1
5      in   i1   2
      in   i2   5
      sig  ot   7
      out' ot   7
fsm fsm: transition from go to go
10     add#0
      add#1
      in   i1   3
      in   i2   6
      sig  ot   9
15     out' ot   9

```

The debugging output produced is enabled by the "setinfo()" call on the "sysgen" object. The parameter "verbose" enables full debugging information. For each clock cycle, each fsm responds which transition it takes. The fsm of the "add" block is called "fsm", and as is seen it makes transitions from the single state "go" to the obvious destination. Each signal flowgraph during this simulation is executed in two phases (below it is indicated why).

25 During simulation, the value of each signal is printed.

Selecting the simulation verbosity

The "setinfo" member function call of "sysgen" selects the amount of debugging information that is produced during simulation. Four values are available:

- "silent" will cause no output at all. This can significantly speed up your simulation, especially for large systems containing several hundred of signal flowgraphs.
- 5 • "terse" will only print the transitions that fsm's make.
- "verbose" will print detailed information on all signal updates.
- 10 • "regcontents" will print a list the values of registered signals that change during the current simulation. This is by far the most interesting option if you are debugging at the system level: when nothing happens, for instance when all your timed descriptions are in some "hold" mode, then no output is produced. When there is a lot of activity, then you will be able to track all
- 15 registered signals that change.

This example is part of a simulation containing 484 registered signals and 483 signal flowgraphs. Using "setinfo(verbose)" here might require a good text editor to

20 see what is happening - if anything will happen before your quota is exceeded.

For instance, the code fragment

```

25  sysgen S(``S'');
    S.setinfo(regcontents);

    int cycle;
    for (cycle=0; cycle < 100; cycle++)
30  {
        cout << ``> Cycle `` << cycle << ``\n'';
```

```

        S.run(ck);
    }

```

can produce an output as shown below.

```

5
  > Cycle 18
      coef_ram_ir_2      0    1
      copy_step_flag     1    0
      ext_ready_out      1    0
10      pc               15   16
      step_flag          1    0
  > Cycle 19
      coef_ram_ir_2      1    0
      coef_wr_adr        12   13
15      hold_pc          0    16
      pc                 16   17
      pc_ctl_ir_1        1    0
  > Cycle 20
      step_clock          0    1
20  > Cycle 21
      copy_step_flag     0    1
      prev_step_clock     0    1
      step_flag           0    1

```

25 *Three phases are better*

Although you will be saved from the details behind two-phase simulation, it is worthwhile to see the motivation behind it.

30

When you run an "sfg" "by hand" using the "run()" method of an "sfg", the simulation proceeds in one phase: read

The origin is the following. In the presence of feedback loops, your system data flow simulation will need initial values on the communication queues in order to start the simulation. However, the code generator assumes the communication queues will translate to wiring. Therefore, there will never be storage in the implementation of a communication queue to hold these initial values. OCAPI works around this by producing these initial values at runtime. This gives rise to a three-phase simulation: in the first phase, initial values are produced, while in the second phase, they are consumed again. This process repeats every clock cycle.

The three-phase simulation mechanism is also able to detect combinatorial loops at the system level. If there exists such a loop, then the first phase of the simulation will not produce any initial value on the system interconnect. Consequently, in the last phase there will be at least one signal flowgraph that will not be able to complete execution in the current clock cycle. In that case, OCAPI will stop the simulation. Also, you get a list of all signal flowgraphs that have not completed the current clock cycle, in addition to the queue statistics that are attached to these signal flowgraphs.

30

OCAPI allows you to translate all timed descriptions to a synthesizable hardware description.

- For each timed description, you get a datapath ".dsfg" file, that can be entered into the Cathedral-3 datapath synthesis environment, converted to VHDL and postprocessed by Synopsys-dc logic synthesis.
- For each timed description, you also get a controller ".dsfg" file, which is synthesized through the same environment.
- You also get a glue cell, that interconnects the resulting datapath and controller VHDL file.
- You get a system interconnect file, that integrates all glue cells in your system. For this system interconnect file, you optionally can specify system inputs and outputs, scan chain interconnects, and RAM interconnects. The file is VHDL.
- Finally, you also get debug information files, that summarize the behavior of and ports on each processor.

Untimed blocks are not translated to hardware. The use of the actual synthesis environments will not be discussed in this section. It is assumed to be known by a person skilled in the art.

The generate() call

The member call "generate()" performs the code generation for you. In the adder example, you just have to add

```
S1.generate();
```

at the end of the main function. If you would compile this

description, and run it, then you would see things are not quite OK:

```

*** INFO: Generating System Link Cell
5 *** INFO: Component generation for S1
*** INFO: C++ currently defines 5 sig, 4 _sig, 1 sfg.
*** INFO: Generating FSMD fsm
*** INFO: FSMD fsm defines 1 instructions
DSFGGen: signal i1 has no wordlength spec.
10 DSFGGen: signal i2 has no wordlength spec.
DSFGGen: signal ot has no wordlength spec.
DSFGGen: not all signals were quantized. Aborting.
*** INFO: Auto-cleanup of sfg

15 Indeed, in the adder example up to now, nothing has been
entered regarding wordlengths. During code generation,
OCAPI does quite some consistency checking. The general
advice in case of warnings and errors is: If you see an
error or warning message, investigate it. When you
20 synthesize code that showed a warning or error during
generation, you will likely fail in the synthesis process
too.
```

The "add" description is now extended with wordlengths. 8
 25 bit wordlengths are chosen. You modify the "add" class to
 include the following changes.

```

void add::define()
{
30         dfix wl(0,8,0);
           _sig i1("`i1'",wl);
           _sig i2("`i2'",wl);
```

```

        _sig ot(`ot',wl);
        ...
    }

```

5 After recompiling and rerunning the OCAPI program, you now see:

```

*** INFO: Generating System Link Cell
*** INFO: Component generation for S1
10 *** INFO: C++ currently defines 5 sig, 4 _sig, 1 sfg.
*** INFO: Generating FSMD fsm
*** INFO: FSMD fsm defines 1 instructions
*** INFO: C++ currently defines 31 sig, 21 _sig, 3 sfg.
*** INFO: Auto-cleanup of sfg

```

15

In the directory where you ran this, you will find the following files:

- "fsm_dp.dsfg", the datapath description of "add"
- 20 • "fsm_fsm.dsfg", the controller description of "add"
- "fsm.vhd", the glue cell description of add
- "S1.vhd", the system interconnect cell
- "fsm.ports", a list of the I/O ports of "add".

25 The glue cell "fsm.vhd" has the following contents (only the entity declaration part is shown).

```

-- Cath3 Processor for FSMD design fsm

30 library IEEE;
   use IEEE.std_logic_1164.all;

```

T01090"060401

```

entity fsm is
    port (
        reset:    in std_logic;
5       clk: in std_logic;
        i1:  in std_logic_vector ( 7 downto 0 );
        i2:  in std_logic_vector ( 7 downto 0 );
        ot:  out std_logic_vector ( 7 downto 0 )
        );
10  end fsm;

```

Each processor has a reset pin, a clock pin, and a number of I/O ports, depending on the inputs and outputs defined in the signal flowgraphs contained in this processor. All
15 signals are mapped to "std_logic" or "std_logic_vector". The reset pin is used for synchronous reset of the embedded finite state machine. If you need to initialize registered signals in the datapath, then you have to describe this explicitly in a signal flowgraph, and execute this upon the
20 first transition out of the initial state.

The "fsm.ports" file, indicates which ports are read in in each transition. In the example of the "add" class, there is only one transition, which results in the following
25 ".ports" file

```
***** SFG fsmgogo0 *****
```

Port #	I/O	Port	Q
1	I	i1	i1
30 2	I	i2	i2
1	O	ot	o1

The name of an input or output signal is used as a port name, while the name of the queue associated to it relates to the system net name that will be connected to this port.

5 *System cell refinements*

The system link cell incorporates all glue cells of your current timed system description. These glue cells are connected if they read/write from the same system queue.

- 10 There are some refinements possible on the "sysgen" object that will also allow you to indicate system level inputs and outputs, scan chains, and RAM connections.

- System inputs and outputs are indicated with the "inpad()" and "outpad()" member calls of "sysgen". In the example, this is specified as

```
...
sysgen S1(``S1'');
20
dfix b8(0,8,0);

S1.inpad(i1, b8);
S1.inpad(i2, b8);
25 S1.outpad(o1, b8);
```

- Making these connections will make the "i1", "i2", "o1" signals appear in the entity declaration of the system cell "S1". The entity declaration inside of the file "S1.vhd"
- 30 thus looks like

entity S1 is

```

port (
    reset:    in std_logic;
    clk: in std_logic;
    i1:  in std_logic_vector ( 7 downto 0 );
5    i2:  in std_logic_vector ( 7 downto 0 );
    o1:  out std_logic_vector ( 7 downto 0 )
);

end S1;

```

- 10 Scan chains can be added at the system level, too. For each scan chain you must indicate which processors it should include. Suppose you have three basic blocks (including a timed description and registers) with names "BLOCK1", "BLOCK2", "BLOCK3". You attach the blocks to two scan
- 15 chains using the following code.

```

    scanchain SCAN1("scan1");
    scanchain SCAN2("scan2");

20  SCAN1.addscan(& BLOCK1. fsm());
    SCAN1.addscan(& BLOCK2. fsm());
    SCAN2.addscan(& BLOCK3. fsm());

```

- The "sysgen" object identifies the required scan chain
- 25 connections through the "fsm" objects that are assigned to it. In order to have reasonable circuit test times, you should not include more than 300 flip-flops in each scan chain. If you have a processor that contains more than 300 flip-flops, then you should use another scan chain
- 30 connection strategy.

Finally, you can generate code for the standard untimed

block RAM. There are two possible interconnection mechanisms: the first will include the untimed RAM blocks in "sysgen" as internal components of the system link cell. The second will include the RAM blocks as external components. This latter method requires you to construct a new "system-system link cell", that includes the RAM entities and the system link cell in a larger structure. However, it might be required in case you have to remap the standard RAM interface, or introduce additional asynchronous timing logic.

An example of the two methods is shown next

```
ram RAM1("ram1", addr1, di1, do1, wr, rd, 128);
15 ram RAM2("ram2", addr2, di2, do2, wr, rd, 128);
```

```
// types of address and data bus
```

```
dfix addrtype(0, 7, 0);
```

```
dfix dattype (0, 4, 0);
```

20

```
sysgen S1(``S1'');
```

```
// define an external ram
```

```
S1.extern_ram(RAM1, addrtype, dattype);
```

25

```
// define an internal ram
```

```
S1.intern_ram(RAM2, addrtype, dattype);
```

Pitfalls for code generation

30

As always, there are a number of pitfalls when things get complex. You should watch the following when diving into

OCAPI generates nicely formatted code, that you can investigate. To help you in this process, also the actual signal names that you have specified are regenerated in the VHDL and DSFG code. This implies that you have to stay away from VHDL and DSFG keywords, or else you will get an error from either Cathedral-3 or Synopsys.

- 25

Finally, the current set of hardware operators in Cathedral-3 is designed for signed representations. They work with unsigned representations also as long as you do not use relational operations (<, > and the like). In this last case, you should implement the unsigned operation as a signed one with one extra bit.

Verification and testbenches

Once you have obtained a gate level implementation of your circuit, it is necessary to verify the synthesis result.

- 5 OCAPI helps you with this by generating testbenches and testbench stimuli for you while you run timed simulations and do code generations.

The example of the "add" class introduced previously is
10 picked up again, and testbench generation capability is included to the OCAPI description.

Generation of testbench vectors

- 15 The next example performs a three cycle simulation of the "add" class and generates a testbench vectors for it.

```
#include "qlib.h"
```

```
20 void main()
```

```
{
```

```
    dfbfix i1("i1");
```

```
    dfbfix i2("i2");
```

```
    dfbfix o1("o1");
```

```
25
```

```
    src SRC1("SRC1", i1, "SRC1");
```

```
    src SRC2("SRC2", i2, "SRC2");
```

```
    add ADD ("ADD" , i1, i2, o1);
```

```
    snk SNK1("SNK1", o1, "SNK1");
```

```
30
```

```
    sysgen S1("S1");
```

F04090" ESE2860

5

10

}

Just before the timed simulation starts, you enable the generation of testbench vectors by means of a "tb_enable()" member call for each fsm that requires testbench vectors.

20

25

- 30

when the synthesis was successful.

- "fsm_tb.dat_info" documents the contents of the stimuli files by saying which stimuli vector corresponds to which signal

5

When compiling and running this OCAPI program, the following appears on screen.

```

*** INFO: Defining block SRC1
10 *** INFO: Defining block SRC2
*** INFO: Defining block ADD
*** INFO: Defining block SNK1
*** INFO: Creating stimuli monitor for testbench of FSMD
fsm
15 *** INFO: Generating stimuli data file for testbench
fsm_tb.
*** INFO: Testbench fsm_tb has 3 vectors.
```

20 Afterwards, you can take a look at each of the three generated testbenches.

```

-- file: fsm_tb.dat
00000001 00000100
00000010 00000101
25 00000011 00000110
-- file: fsm_tb.dat_hex
01 04 05
02 05 07
03 06 09
30 -- file: fsm_tb.dat_info
Stimuli for fsm_tb contains 3 vectors for
```

```

i1_stim      read
i2_stim      read

```

Next columns occur only in _hex.dat file and are outputs

5

```

o1_stim      write

```

You can now use the vectors in the simulator. But first, you must also generate a testbench driver in VHDL.

10

Generation of testbench drivers

To generate a testbench driver, simply call the "tb_enable()" member function of the "add" fsm before you initiate code generation. You will end up with a VHDL file "fsm_tb.vhd" that contains the following driver.

```

-- Test Bench for FSM design fsm

20 library IEEE;
   use IEEE.std_logic_1164.all;

   use IEEE.std_logic_textio.all;
   use std.textio.all;

25 library clock;
   use clock.clock.all;

   entity fsm_tb is
30 end fsm_tb;

architecture rtl of fsm_tb is

```

```

signal reset:    std_logic;
signal clk: std_logic;
signal i1:  std_logic_vector ( 7 downto 0 );
signal i2:  std_logic_vector ( 7 downto 0 );
5  signal ot:  std_logic_vector ( 7 downto 0 );
    component fsm
        port      (
            reset:    in std_logic;
            clk: in std_logic;
10         i1:  in std_logic_vector ( 7 downto 0 );
            i2:  in std_logic_vector ( 7 downto 0 );
            ot:  out std_logic_vector ( 7 downto 0 )
                );
        end component;
15
    begin
        crystal(clk, 50 ns);
        fsm_dut: fsm
            port map      (
20         reset =>    reset,
            clk =>  clk,
            i1 =>    i1,
            i2 =>    i2,
            ot =>    ot
25         );
        ini:  process
            begin
                reset <= '1';
                wait until clk'event and clk = '1';
30         reset <= '0';
                wait;
            end process;

```

```

input: process
    file stimuli : text is in "fsm_tb.dat";
    variable aline : line;
5    file stimulo : text is out "fsm_tb.sim_out";
    variable oline : line;
    variable v_i1: std_logic_vector ( 7 downto 0 );
    variable v_i2: std_logic_vector ( 7 downto 0 );
    variable v_ot: std_logic_vector ( 7 downto 0 );
10   variable v_i1_hx: std_logic_vector ( 7 downto 0 );
    variable v_i2_hx: std_logic_vector ( 7 downto 0 );
    variable v_ot_hx: std_logic_vector ( 7 downto 0 );
    begin
    wait until reset'event and reset = '0';
15   loop
        if (not(endfile(stimuli))) then
            readline(stimuli, aline);
            read(aline,    v_i1);
            read(aline,    v_i2);
20         else
            assert false
            report "End of input file reached"
            severity warning;
        end if;
25       i1 <= v_i1;
        i2 <= v_i2;
        wait for 50 ns;
        v_ot := ot;
        v_i1_hx := v_i1;
30       v_i2_hx := v_i2;
        v_ot_hx := v_ot;
        hwrite(oline, v_i1_hx);

```

F04090-2552850

```

write(oline, ' ');
hwrite(oline, v_i2_hx);
write(oline, ' ');
hwrite(oline, v_ot_hx);
5   write(oline, ' ');
    writeline(stimulo, oline);
    wait until clk'event and clk = '1';
    end loop;
    end process;
10  end rtl;

configuration tbc_rtl of fsm_tb is
for rtl
    for all : fsm
15      use entity work.fsm(structure);
    end for;
end for;
end tbc_rtl;

20  The testbench uses one additional library, "clock", which
    contains the "crystal" component. This component is a
    simple clock generator that drives a 50% duty cycle clk.

    This testbench will generate a file "fsm_tb.sim_out". After
25  running the testbench in VHDL, this file should be exactly
    the same as the "fsm_tb.dat_hex". You can use the unix
    "diff" command to check this. The only possible differences
    can occur in the first few simulation cycles, if the VHDL
    simulator initializes the registers to "X".

30  Using automatic testbench generation greatly speeds up the
    verification process. You should consider using it whenever

```

09873553-060404

you are into code generation.

Compiled code simulations

- 5 For large designs, simulation speed can become prohibitive. The restricting factor of OCAPI is that the signal flowgraph data structures are interpreted at runtime. In addition, runtime quantization (fixed point simulation) takes up quite some CPU power.

10

- OCAPI allows you to generate a dedicated C++ simulator, that runs compiled code instead of interpreted code. Also, additional optimizations are done on the fixed point simulation. The result is a simulator that runs one to two
15 orders of magnitude faster than the interpreted OCAPI simulation. This speed increase adds up to the order of magnitude that interpreted OCAPI already gains over event-driven VHDL simulation.

- 20 As an example, a 75Kgate design was found to run at 55 cycles per second (on a HP/9000). This corresponds to "4.1 million" gates per second, and motivates why C++ is the way to go for system synthesis.

25 *Generating a compiled code simulator*

The compiled code generator is integrated into the "sysgen" object. There is one member function, "compiled()", that will generate this simulator for you.

30

```
#include ``qlib.h''
#include ``add.h''
```

```

void main()
{
    dfbfix i1("i1");
5    dfbfix i2("i2");
    dfbfix o1("o1");
    add ADD ("ADD" , i1, i2, o1);

    sysgen S1("S1");
10    S1 << ADD.fsm();

    S1.compiled();
}
15

```

In this simple example, a compiled code generator is made for a design containing only one FSM. The generator allows to include several fsm blocks, in addition to untimed blocks.

20 When this program is compiled and run, it leaves behind a file "S1_ccs.cxx", that contains the dedicated simulator. For the OCAPI user, the simulator defines one procedure, "one_cycle()", that simulates one cycle of the system.

25 When calling this procedure, it also produces debugging output similar to the "setinfo(regcontents)" call for "ctlfsm" objects. This procedure must be linked to a main program that will execute the simulation.

30 If an untimed block is present in the system, then it will be included in the dedicated simulator. In order to declare

it, you must provide a member function "CCSdecl(ofstream &)" that generates the required C++ declaration. As an example, the basic RAM block declares itself as follows:

```

5          -- file: ram.h

          class ram : public base
          {
              public:
10                  ...

                  ram (char * name,
                      FB& _address,
                      FB& _data_in,
                      FB& _data_out,
15                      FB& _w,
                      FB& _r,
                      int _size);

                  void CCSdecl(ofstream &os);

                  ...
20          private:

                  ...

          };

          -- file: ram.cxx

25          void ram::CCSdecl(ofstream &os)
          {
              os << "  #include \"ram.h\"\\n";
              os << "  ram " << typeName() << "(";
30              os << "\"" << typeName() << "\", ";
              os << address.name() << ", ";
              os << data_in.name() << ", ";

```

```

os << data_out.name() << ", ";
os << w.name() << ", ";
os << r.name() << ", ";
os << size << ");\n";
5      }

```

This code enables the ram to reproduce the declaration by which it was originally constructed in the interpreted OCAPI program. Every untimed block that inherits from

10 "base", and that you wish to include in the compiled code simulator must use a similar "CCSdecl" function.

Compiling and running a compiled code simulator

15 The compiled code simulator is compiled and linked in the same way as a normal OCAPI program. You must however also provide a "main" function that drives this simulator.

The following code contains an example driver for the "add"

20 compiled code simulator.

```

#include "qlib.h"

void one_cycle();
25 extern FB i1;
extern FB i2;
extern FB o1;

void main()
30 {
    i1 << dfix(1) << dfix(2) << dfix(3);
    i2 << dfix(4) << dfix(5) << dfix(6);

```

```

        one_cycle();
        one_cycle();
        one_cycle();

```

5

```

        while (ol.getSize())
            cout << ol.get() << "\n";
    }

```

- 10 When run, this program will produce the same results as before. In contrast to the compiled simulation of your MPEG-4 image processor, you will not be able to notice any speed increase on this small example.

15 Faster communications

- OCAPI uses queues as a means to communicate during simulation. These queues however take up CPU power for queue management. To save this power, there is an additional queue type, "wireFB", which is used for the simulation of point-to-point wiring connections.

The dfbfix_wire class

- 25 A "wireFB" does not move data. In contrast, it is related to a registered driver signal. At any time, the value read of this queue is the value defined by the registered signal. Because of this signal requirement, a "wireFB" cannot be used for untimed simulations. The following example of an accumulator shows how you can use a "wireFB", or the equivalent "dfbfix_wire".

F04090" C55E/860

```

#include "qlib.h"

void main()
{
5   clk ck;

    _sig a("a",ck,dfix(0));
    _sig b("b");

10   dfbfix_wire A("A",a);
    dfbfix B("B");

    sfg accu;
    accu.starts();
15   a = a + b;
    accu << "accu";
    accu << ip(b, B);
    accu << op(a, A);
    accu.check();
20   B << dfix(1) << dfix(2) << dfix(3);
    while (B.getSize())
    {
        accu.eval(cout);
        accu.tick(ck);
25   }
}

```

A "wireFB" is identical in use as a normal "FB". Only, for each "wireFB", you indicate a registered driver signal in

30 the constructor.

Interconnect strategies

The "wireFB" object is related to the interconnect strategy that you use in your system. An interconnect strategy
5 includes a decision on bus-switching, bus-storage, and bus-arbitration. OCAPI does not solve this problem for you: it depends on your application what the right interconnection strategy is.

10 One default style of interconnection provided by OCAPI is the point-to-point, register driven bus scheme. This means that every bus carries only one signal from one processor to another. In addition, bus storage is included in the processor that drives the bus.

15 More complex interconnect strategies, like the one used in Cathedral-2, are also possible, but will have to be described in OCAPI explicitly. Thus, the freedom of target architecture is not without cost. In the section "Meta-code
20 generation", a solution to this specification problem is presented.

Meta-code generation

25 OCAPI internally uses meta-code generation. With this, it is meant that there are code generators that generate new "fsm", "sfg" and "sig" objects which in turn can be translated to synthesizable code.

30 Meta-code generation is a powerful method to increase the abstraction level by which a specification can be made. This way, it is also possible to make parametrized

descriptions, eventually using conditions. Therefore, it is the key method of soft-chip components, which are software programs that translate themselves to a wide range of implementations, depending on the user requirements.

5

The meta-code generation mechanism is also available to the user. To demonstrate this, a class will be presented that generates an ASIP datapath decoder.

10 *An ASIP datapath idiom*

An ASIP datapath, when described as a timed description within OCAPI, will consist of a number of signal flowgraphs and a finite state machine. The signal flowgraphs express
15 the different functions to be executed by the datapath. The fsm description is a degenerated one, that will use one transition per decoded instruction. The transition condition is expressed by the "instruction" input, and selects the appropriate signal flowgraph for execution.

20

Because the finite state machine has a fixed, but parametrizable structure, it is subject for meta-code generation. You can construct a "decoder" object, that generates the "fsm" for you. This will allow compact
25 specification of the instruction set.

First, the "decoder" object (which is present in OCAPI) itself is presented.

```
-- the include file
```

30

```
#define MAXINS 100
```

```

#include "qlib.h"

class decoder : public base
5  {
    public:
        decoder(char *_name, clk &ck, dfbfix &_insq);
        void dec(int _numinstr);
        ctlfsm &fsm();
10    void dec(int _code, sfg &);
        void dec(int _code, sfg &, sfg &);
        void dec(int _code, sfg &, sfg &, sfg &);
    private:
        char *name;
15    clk *ck;
        dfbfix *insq;

        int inswidth;
        int numinstr;
20    int codes[MAXINS];

        ctlfsm _fsm;
        state active;

25    sfg decode;
        _sigarray *ir;

        cnd * deccnd(int );
        void decchk(int );
30 };

```

-- the .cxx file

09873553-060401

```

#include "decoder.h"

static int numbits(int w)
5   {
    int bits = 0;
    while (w)
    {
        bits++;
10    w = w >> 1;
    }
    return bits;
}

15 int bitset(int bitnum, int n)
{
    return (n & (1 << bitnum));
}

decoder::decoder(char *_name, clk &_ck, dfbfix &_insq)
20 : base(_name)
{
    name = _name;
    insq = _insq.asSource(this);
    ck = &_ck;
25    numinstr = 0;
    inswidth = 0;

    _fsm << _name;
    // active << strapp(name, "_go_");
30    active << "go";
    _fsm << deflt(active);
}

```

```

void decoder::dec(int n)
{
    // define a decoder that decodes n instructions
    // instruction numbers are 0 to n-1
    // create also the instruction register
    if (!(n>0))
    {
        cerr << "*** ERROR: decoder " << name << " must
10      have at least one instruction\n";
        exit(0);
    }
    inswidth = numbits(n-1);
    if (n > MAXINS)
15    {
        cerr << "*** ERROR: decoder " << name << "
        exceeds decoding capacity\n";
        exit(0);
    }
20
    dfix bit(0,1,0,dfix::ns);
    ir = new _sigarray((char *) strapp(name,"_ir"),
    inswidth, ck, bit);
    decode.starts();
25    int i;
    SIGW(irw, dfix(0, inswidth, 0, dfix::ns));
    for (i=0; i<inswidth; i++)
    {
        if (i)
30      (*ir)[i] = cast(bit, irw >>
        _sig(dfix(i,inswidth,0,dfix::ns)));
        else

```

T04090"ESSEZ860

```

        (*ir)[i] = cast(bit, irw);
    }
    decode << strapp("decod", name);
    decode << ip(irw, *insq);
5
}

void decoder::decchk(int n)
{
10    // check if the decoder can decode this instruction
    int i;
    if (!inswidth)
    {
        cerr << "*** ERROR: decoder " << name << " must
15        first define an instruction width\n";
        exit(0);
    }
    if (n > ((1 << inswidth)-1))
    {
20        cerr << "*** ERROR: decoder " << name << "
        cannot decode code " << n << "\n";
        exit(0);
    }
    for (i=0; i<numinstr; i++)
25    {
        if (n == codes[i])
        {
            cerr << "*** ERROR: decoder " << name << "
            decodes code " << n << " twice\n";
30            exit(0);
        }
    }
}

```

T04030"ESSE/860

```

        codes[numinstr] = n;
        numinstr++;
    }

5   cnd *decoder::deccnd(int n)
    {
        // create the transition condition that corresponds
        // to the instruction number n
        int i;
10   cnd *cresult = 0;
        if (bitset(0, n))
            cresult = &_cnd((*ir)[0]);
        else
            cresult = &(!_cnd((*ir)[0]));

15   for (i = 1; i < inswidth; i++)
        {
            if (bitset(i, n))
                cresult = &(*cresult && _cnd((*ir)[i]));
20   else
                cresult = &(*cresult && !_cnd((*ir)[i]));
        }
        return cresult;
    }

25   void decoder::dec(int n, sfg &s)
    {
        // enter an instruction that executes one sfg
        decchk(n);
30   active << *deccnd(n) << decode << s << active;
    }

```

```

void decoder::dec(int n, sfg &s1, sfg &s2)
{
    // enter an instruction that executes two sfgs
    decchk(n);
5    active << *deccnd(n) << decode << s1 << s2 <<
    active;
}

void decoder::dec(int n, sfg &s1, sfg &s2, sfg &s3)
10 {
    // enter an instruction that executes three sfgs
    decchk(n);
    active << *deccnd(n) << decode << s1 << s2 << s3 <<
    active;
15 }
    ctrlfsm & decoder::fsm()
    {
        return _fsm;
    }
20

```

The main principles of generation are the following. Each instruction for the ASIP decoder is defined as a number, in addition to one to three signal flowgraphs that need to be executed when this instruction is decoded. The "decoder" object keeps track of the instruction numbers already used and warns you if you introduce a duplicate. When the instruction number is unique, it is split up into a number of instruction bits, and a fsm transition condition is constructed from these bits.

30

The ASIP datapath at work

The use of this object is quite simple. In a timed description were you want to use the decoder instead of a plain "fsm", you inherit from this decoder object rather than from the "base" class. Next, instead of the fsm
 5 description, you give the instruction list and the required signal flowgraphs to execute.

As an example, an add/subtract ASIP datapath is defined. We select addition with instruction number 0, and subtraction
 10 with instruction number 1. The following code (that also uses the supermacros) shows the specification. The inheritance to "decoder" also establishes the connection to the instruction queue.

```

15      -- include file
      #ifndef ASIP_DP_H
      #define ASIP_DP_H

      class asip_dp : public decoder
20      {
      public:
          asip_dp (char *name,
                  clk &ck,
                  FB &ins,
25          _PRT(in1),
          _PRT(in2),
          _PRT(o1));

      private:
          PRT(in1);
30          PRT(in2);
          PRT(o1 );

      };
  
```

```
-- code file
```

```
#include ``asip_dp.h''
```

```
dfix typ(0,8,0);
```

5

```
asip_dp::asip_dp      (char *name,
                        clk &ck,
                        FB &ins,
                        _PRT(in1),
10      _PRT(in2),
                        _PRT(o1)) :    decoder(name, ck, ins),
                                      IS_SIG(in1, typ),
                                      IS_SIG(in2, typ),
                                      IS_SIG(o1, typ)
```

15

```
{
  IS_IP(in1);
  IS_IP(in2);
  IS_OP(o1);
```

20

```
  SFG(add);
  GET(in1);
  GET(in2);
  o1 = in1 + in2;
  PUT(o1);
```

25

```
  SFG(sub);
  GET(in1);
  GET(in2);
  o1 = in1 - in2;
30  PUT(o1);
```

```
dec(2); // decode two instructions
```

T04090"ESSEZB60

}

10

Description of a design of systems according to the method of the invention

20

- The link design (1) is the requirement capture phase. Based on telecommunication properties such as transmission bandwidth, power, and data throughput (the link requirements), the system design space is explored using small subsystem simulations. The design space includes all algorithms which can be used by a transmitter/receiver pair to meet the link requirements. Out of receiver and transmitter algorithms with an identical functionality, those with minimal complexity are preferred. Besides this exploration, any expected transmission impairment must also be modeled into a software channel model.

• The **algorithm design** (2) phase selects and interconnects the algorithms identified in the link design phase. The output is a software algorithmic description in C++ of digital transmitter and receiver parts in terms of floating point operations. To express parallelism in the transmitter and receiver algorithms, a data-flow data model is used. Also, the transmission imperfections introduced by analog parts such as the RF front-ends are annotated to the channel model.

• The **architecture design** (3) refines the data model of the transmitter or receiver. The target architectural style is optimized for high speed execution, uses distributed control semantics and pipeline mechanisms. The resulting description is a fixed point, cycle true C++ description of the algorithms in terms of execution on bit-parallel operators. The architecture design is finished with a translation of this description to synthesizable VHDL.

• Finally, **circuit design** (4) refines the bit-parallel implementation to circuit level, including technology binding, the introduction of test hardware, and design rule checks.

Target Architecture

The target architecture (5), shown in figure 2, consists of a network of interconnected application specific processors. Each processor is made up of bit-parallel data-paths. When hardware sharing is applied, also a local control component is needed to perform instruction

sequencing. The processors are obtained by behavioral synthesis tools or RT level synthesis tools. In either case, circuits with a low amount of hardware sharing are targeted. The network is steered by one or multiple clocks.

- 5 Each clock signal defines a clock region. Inside a clock region the phase relations between all register clocks are manifest. Clock division circuits are used to derive the appropriate clock for each processor.
- 10 In between each processor, a hardware queue is present to transport data signals. They increase parallelism inside a clock region and maintain consistency between different streams of data arriving at one processor.
- 15 Across clock region boundaries, synchronization interfaces are used. These interfaces detect the presence of data at the clock region boundary and gate clock signals for the clock region that they feed. This way, non-manifest and variable data rates in between clock regions are supported.
- 20 The ensemble of clock dividers and handshake circuits forms a parallel scheduler in hardware, synchronizing the processes running on the bit-parallel processor.
- 25 Overview of the C++ modeling levels

An overview of the distinct C++ modeling levels used by OCAPI is given in figure 3. The C++ modeling spans three subsequent levels in the design flow: the link level, the algorithm level and the architecture level. The transition to the last level, the circuit level, is made by automated means through code generation. Usually, VHDL is used as the

The link level is available through data-vector modeling. Using a design mechanism called parallelism scaling, this level is refined to the algorithm level. The algorithm level uses data-flow semantics. Using two distinct refining mechanisms in the data-flow level, we can refine this level to a register transfer level.

- The last level, the architecture model, uses a signal
20 flowgraph to provide a behavioral description. Using this
description synthesizable code is generated. The resulting
code then can be mapped onto gates using a register-
transfer design tool such as DC of *Synopsys*.

The upper level of representation of a communication system is the link level. It has the following properties :

- ```
30 • It uses pure mathematical manipulation of functions. Time
 is explicitly manipulated and results in irregular-flow
 descriptions.
```

- It uses abstraction of all telecommunication aspects that are not relevant to the problem at hand.

In this representation level, MATLAB is used for simulation. MATLAB uses the data-vector as the basic data object. To represent time functions in MATLAB, they are sampled at an appropriate rate. Time is present as one of the many vector dimensions. For example, the MATLAB vector addition

$$a = b + c ;$$

can mean both sequential addition in time (if the  $b$  and  $c$  vectors are thought of as time-sequential), or parallel addition (if  $b$  and  $c$  happen to be defined at one moment in time). MATLAB simply make no distinction between these two cases.

15

Besides this time-space feature, MATLAB has a lot of other properties that makes it the tool-of-choice within this design level :

- The ease with which irregular flow of data is expressed with vector operations. For example, the operation **max(vector)**, or **std(vector)**.
- The flexibility of operations. A **maximum** operation on a vector of 10 elements or 1000 elements looks identically: **max(vector)**.
- The interactivity of the tool, and the transparency of data object management.
- The extended library of operations, that allow very dense description of functionality.
- Graphics and simulation speed.

30

This data-vector restriction is to be refined to a data-

flow graph representation of the system. Definition of the data-flow graph requires definition of all actors in the graph (actor contents as well as actor firing rules) and definition of the graph layout.

5

In order to design systems effectively with the SOC++ design flow, a smooth transition between the data-vector level and the data-flow level is needed. A script to perform this task is constructed as can be seen in the following example.

Example 1: design of a telecommunication system

Initial data-vector description

15 We consider a pseudonoise (PN) code correlator inside a direct sequence spread-spectrum (DS/SS) modem as an example (figure 4).

% input data

20 in = [1 2 1 3 3 4 1 2] ;

% spreading code

c = [1 -1 1 -1] ;

25 % correlate

ot = corr (in, c)

% find correlation peak

[max, maxpos] = max (ot) ;

30

A vector of input data in is defined containing 8 elements. These are subsequent samples taken from the chip

09873553-060401

demodulator in the spread spectrum modem. The dimension of `in` thus corresponds to the time dimension. The input vector `in` is in principle infinite in length. For simulation purposes, it is restricted to a data set which has the same  
 5 average properties (distribution) as the expected received data.

The samples of `in` are correlated with the PN-code vector of length 4, `c`. The output vector `ot` thus contains 5 samples,  
 10 corresponding to the five positions of `in` at which `c` can be aligned to. The `max` function locates the maximum value and position inside the correlated data. The position `maxpos` is subsequently used to synchronize the PN-code vector with the incoming data and thus is the desired output value of  
 15 the algorithm.

This code is an elegant and compact specification, yet it offers some open questions for the PN-correlator designer:

- The algorithm has an implicit startup-effect. The first  
 20 correlation value can only be evaluated after 4 input samples are available. From then on, each input sample yields an additional correlation value.
  - The algorithm misses the common algorithmic iteration found in digital signal processing applications: each  
 25 statement is executed only once.
  - For the implementation, no statement is made regarding the available cycle budget. This is however an important specification for the attainable acquisition speed of the modem.
- 30 All of these questions are caused by the parallelism of the data-vector description.

We now propose a way to make the parallelism of the operations more visible. Each of the MATLAB operations is easily interpreted. Inside the MATLAB simulation, the length of the operands will first be determined in order to  
 5 select the correct operation behavior. For example,

```
[max, maxpos] = max(ot)
```

determines the maximum on a vector of length 5 (which is  
 10 the length of the operand ot). It needs at least 4 scalar comparisons to evaluate the result. If ot would for example have a longer length, more scalar comparisons would be needed. To indicate this in the description, we explicitly annotate each specific instance of the generic operations  
 15 with the length of the input vectors.

```
% input data
```

```
in = [1 2 1 3 3 4 1 2] ;
```

```
8
```

```
20
```

```
% spreading code
```

```
c = [1 -1 1 -1] ;
```

```
4
```

```
25 % correlate
```

```
ot = corr (in, c)
```

```
5
```

```
8,4
```

```
% find correlation peak
```

```
30 [max, maxpos] = max (ot) ;
```

```
1
```

```
5
```

000353-060401  
 104090-0552060

This little annotation helps us to see the complexity of the operations more clearly. We will use this when considering implementation of the description in hardware. It is of course not the intention to force a user to do  
 5 this (MATLAB does this already for him/her).

When thinking about the implementation of this correlator, one can imagine different realizations each having a different amount of parallelism, that is, the mapping of  
 10 all the operations inside `corr()` and `max()` onto a time/space axis. This is the topic of the next section.

#### Scaled description

15 Consider again the definition of the PN code, as in:

```
% spreading code
c = [1 -1 1 -1] ;
 4
```

20

This MATLAB description defines the variable `c` to be a data-vector containing 4 different values. This vector assignment corresponds to 4 concurrent scalar assignments. We therefore say that the maximal attainable parallelism in  
 25 this statement is 4.

In order to achieve this parallelism in the implementation, there must be hardware available to perform 4 concurrent scalar assignments. Since a scalar assignment in hardware  
 30 corresponds to driving a data bus to a certain state, we need 4 busses in the maximal parallel implementation. If only one bus would be desired, then we would have to

09873153-060401  
 104030-5552860

indicate this. For each of the statements inside the MATLAB description, a similar story can be constructed. The indication of the amount of parallelism is an essential step in the transition from data-vectors to data-flow. We  
 5 call this the scaling of parallelism. It involves a restriction of the unspecified communication bandwidth in the MATLAB description to a fixed number of communication busses. It is indicated as follows in the MATLAB description.

10

```
% input data
```

```
in = [1 2 1 3 3 4 1 2] ;
```

15

```
8@1
```

```
% spreading code
```

```
c = [1 -1 1 -1] ;
```

```
4@4
```

20

```
% correlate
```

```
ot = corr (in, c)
```

```
5@1 8,4
```

25 % find correlation peak

```
[max, maxpos] = max (ot) ;
```

```
1@1 5
```

30 As is seen, each assignment is extended with a @i annotation, that indicates how the parallelism in the data vectors is ordered onto a time axis. For example, the 8

T04030" ESE4860

input values inside in are provided sequentially by writing 8@1. The 4 values of c on the other hand, are provided concurrently. We see that, whatever implementation of the corr operation we might use, at least 8 iterations will be required, simply to provide the data to the operation.

At this moment, the description is getting closer to the data-flow level, that uses explicit iteration. One more step is required to get to the data flow graph level. This is the topic of the next section.

#### Data flow graph definition

In order to obtain a graph, the actors and edges inside this graph must be defined. Inside the annotated MATLAB description, data precedences are already present through the presence of the names of the vectors. The only thing that is missing is the definition of actor boundaries; edges will then be defined automatically by the data precedences going across the actor boundaries.

This can be done by a new annotation to the MATLAB description. Three actors will be defined in the DS/SS correlator.

25

```
actor1 {
% input data
in = [1 2 1 3 3 4 1 2] ;
 8@1
30 }
```

```
actor2 {
```

09873553-060404

```

% spreading code
c = [1 -1 1 -1] ;
 4@4

% correlate
5 ot = corr (in, c)
 5@1 8,4
}

actor3 {
10 % find correlation peak
 [max, maxpos] = max (ot) ;
 1@1 5
}

```

15 Again the annotation should be seen as purely conceptual; it is not intended for the user to write this code. Given these annotations, a data flow graph can be extracted from the scaled MATLAB description in an unambiguous way.

- actor1 is an actor with no input, and one output, called
- 20 in.
- actor2 is an actor with 1 input in and one output ot.
- actor3 is an actor with 1 input ot and outputs maxpos and max.

25 Furthermore, the simulation uses queues to transport signals in between the actors. We need three queues, called in, ot and maxpos.

The missing piece of information for simulation of this

30 dataflow graph are the firing rules (or equivalently the definition of productions and consumptions on each edge). A naive data flow model is shown in figure 4 : actor1 (10)

produces 8 values, which are correlated by actor2 (11), while the maximum is selected inside actor3 (12).

This would however mask the parallelism scaling operation inside the MATLAB description. For example, it was chosen to provide the 8 values of the `in` vector in a sequential way over a parallel bus. It is believed that the multi-rate SDF model therefore is not a good container for the annotated MATLAB description.

10

Another approach is a cyclostatic description. In this case we have a graph as in figure 5.

We see that the determination of production patterns involves examining the latencies of operations internal to the actor. This increases the complexity of the design script. It is simpler to perform a demand driven scheduling of all actors. The firing rule only has to examine the availability of input tokens.

20 The desired dataflow format as in figure 6 is thus situated in between the multirate SDF level and the cyclostatic SDF level. It is proposed to annotate consumptions and productions in the same way as it was written down in the matlab description:

- 25 • 8@1 is the production of actor1. It means: 8 samples are produced one at a time.
- 8@1 and 5@1 is the consumption and production of actor2 respectively.
- 5@1 and 1@1, 1@1 are the consumption and productions for
- 30 actor3.

Data-flow simulation

0087353-060401

Given an annotated matlab description, a simulation can now be constructed by writing a high-level model for each actor, interconnecting these with queues and constructing a system schedule. OCAPI provides both a static scheduler and  
 5 a demand-driven scheduler.

Out of this simulation, several statistics are gathered:

- On each queue, put and get counts are observed, as well as signal statistics (minimum and maximum values). The  
 10 signal statistics provide an idea of the required buswidths of communication busses.
- The scheduler counts the firings per actor, and operation executions (+, -, \*, ...) per actor. This profiling helps the designer in deciding cycle budgets and hardware  
 15 operator allocation for each actor.

These statistics are gathered through a C++ operator overloading mechanism, so the designer gets them for free if he uses the appropriate C++ objects (schedule, queue and  
 20 token class types) for simulation.

We are next interested in the detailed clock-cycle true behavior of the actors and the required storage and handshake protocol circuits on the communication busses.  
 25 This is the topic of the next step, the actor definition.

#### Actor definition

The actor definition is based on two elements:

- 30 • Signal-flowgraph representation of behavior.
- Time-verification of the system.

The two problems can be solved independently using the annotated MATLAB code as specification. In OCAPI :

- The actor RT modeling proceeds in C++ and can be freely  
5 intermixed with high level descriptions regarding both  
operator wordlength effects and clock-cycle true timing.
- The time-verification approach allows the system  
feasibility to be checked at all times by warning the  
designer for deadlock and/or causality violations of the  
10 communication.

#### Signal flowgraph definition

Within the OCAPI design flow, a class library was developed  
15 to simulate behavior at RT-level. It allows

- To express the behavior of an algorithm with arbitrary  
implementation parallelism by setting up an signal flow  
graph (SFG) data structure.
- To simulate the behavior of an actor at a clock-cycle  
20 true level by interpreting this SFG data structure with  
instantiated token values.
- To specify wordlength characteristics of operations  
regarding sign, overflow and rounding behavior. Through  
explicit modeling of the quantization characteristic  
25 rather than the bit-vector representation (as in SPW),  
efficient simulation runtimes are obtained.
- To generate C++ code for this actor, and hence perform  
the clock cycle true simulation with compiled code.
- To generate VHDL code for this actor, and synthesize an  
30 implementation with Synopsys DC.
- To generate DSFG code for this actor, and synthesize an

T04030" E55E2850

implementation with Cathedral-3. It was observed that Cathedral-3 performs a better job with relation to both critical path and area of the obtained circuits than Synopsys DC. The best synthesis results are obtained by  
 5 first using Cathedral-3 to generate a circuit at gate level and then Synopsys-DC to perform additional logic optimization as a postprocessing.

An important observation was made regarding simulation  
 10 speed. For equivalent descriptions at different granularities, the following relative runtimes were found:

- 1 for the MATLAB simulation.
- 2 for the untimed, high level C++ data flow description.
- 4 for the timed, fixed point C++ description (compiled  
 15 code).
- 40 for the procedural, word-level VHDL description.

It is thus concluded that RT-modeling of systems within OCAPI is possible within half an order of magnitude of the  
 20 highest level of description. VHDL modeling however, is much slower. Currently the figure of 40 times MATLAB is even considered an under-estimate. Future clock-cycle based VHDL simulators can only solve half of this problem, since they still use bit-vector based simulation of tokens rather  
 25 then quantization based simulation.

Next, the modeling issues in C++ are shown in more detail. The C++ signal-flowgraph representation uses a **signal** data-type, that can be either a registered or else an immediate  
 30 value. With this data-type, expressions are formed using

the conventional scalar operations. (+, -, \*, shifts and logical operations). Expressions are grouped together in a signal flowgraph. A signal flowgraph interfaces with the system through the data-flow simulation queues. Several  
5 signal-flowgraphs can be grouped together to a SFG-sequence. A SFG sequence is an expression of behavior that spans several cycles. The specification is done through a finite state machine model, for which transition conditions can be expressed. The concept of SFG modeling is pictured  
10 in figure 7.

The combination of different SFG's in combination with a finite state machine make up the clock-cycle true actor model. Within the actor, SFG communication proceeds through  
15 registered signals. Communication over the boundaries of an actor proceeds through simulation queues.

When the actor is specified in this way, and all signal wordlengths are annotated to the description, an automated  
20 path to synthesis is available. Several different SFG's can be assigned to one datapath. Synthesizable code is generated in such a way that hardware sharing between different sfg's is possible. A finite state machine (FSM ) description is first translated to SFG format to generate  
25 synthesizable code in the same way. There is an implicit hierarchy available with this method: by assigning different FSM-SFG's to one datapath, an overall processor architecture is obtained that again has a mode port and therefore looks like a (multicycle) datapath. For macro  
30 control problems (such as acquisition/tracking algorithm switching in modems), this is a necessity.



```

SFG sfg0, sfg1,sfg2 ; //we use 3 sfg's

sfg0.starts() ; //code after this is for sfg0
5 currmax = inputvalue ;
 maxpos = one ;
 currpos = one ;

 //next, give sfg0 a mode and
 an input queue
10 sfg0 <<'m0'><<ip(inputvalue,qin) ;

 //code after this is for sfg1
 //this is a conditional
 assignment
15 currmax=(inputvalue>currmax).cassign(inputvalue,currmax);
 maxpos = (inputvalue > currmax).cassign(currpos, maxpos) ;
 currpos = currpos + 1 ;
 sfg1 <<'m1'><<ip(inputvalue,qin) ;

20 sfg2.starts() ; //the last SFG
 maxposout=(inputvalue>currmax).cassign(_sig(dfix(4)),maxpos);
 maxout=(inputvalue>currmax).cassign(inputvalue, currmax) ;
 sfg2 <<'m2'><< op(maxout,qout) << op(maxposout,q2out) ;

25 state s0('s0'), s1('s1'), s2('s2'), s3('s3') ;
 s0 >> !cnd(start) >> s0 ;
 s0 >> cnd(start) >> sfg0 s1 ;
 s1 >> always >> sfg1 >> s2 ;
 s2 >> always >> sfg1 >> s3 ;
30 s3 >> always >> sfg2 >> s0 ;
}

```

As an aid to interpret the C++ code, the equivalent behavior is shown in figure 8. The behavior is modeled as a 4-cycle description. Three SFG's (13,14,15) are needed, in addition to a 4-state controller (16). The controller is modeled as a Mealy machine.

The C++ description also illustrates some of the main contributions of OCAPI: register-transfer level aspects (signals, clocks, registers), as well as dataflow aspects (simulation queues) are freely intermixed and used as appropriate. By making use of C++ operator overloading and classes, these different design concepts are represented in a compact syntax format. Compactness is a major design issue.

Having this specification, we have all information to proceed with the detailed architectural design of the actor. This is however only part of the system design solution: we are also interested in how to incorporate the cycle-true result in the overall system.

20

#### Time verification

The introduction of time (clock cycles) in the simulation uses an expectation-based approach. It allows to use either a high level or else an SFG-type description of the actor, and simulate the complete system clock-cycle true. The simulation helps the designer in finding whether his 'high-level' description matches the SFG description, and secondly, whether the system is realizable.

30

A summary of the expectation based simulation is given in figure 10 and is used to illustrate the ideas mentioned

This is a different approach than when analysis is used (e.g. the evaluation of a compile-time schedule and token lifetimes) to force restrictions onto the actor implementation. This traditional approach gives the designer no clue on whether he is actually writing down a reasonable description.

Additionally, each queue in the simulation holds a queue age (say, 'the present') that is used to check the causality of the simulation: a token entering a queue should not be younger than this boundary. A queue is only able to delay tokens (registers), and therefore can only work with tokens that are older than the queue age.

25

The queue age is steered by the actor that drives it. For each actor the designer formulates an iteration time. The iteration time corresponds the cycle budget that the designer expects to need for the detailed actor description. Upon each actor firing, the queues driven by the actor are aged with the iteration time.

At the same time, the actor operations also increase the age of the tokens they process. For normal operations, the resulting token age is equal to the maximum of the operand token ages. For registered signals (only present in SFG-  
 5 level actor descriptions), the token age is increased by one. Besides aging by operation, aging inside of the queues is also possible by attaching a travel delay to each queue.

Like the high-level actor description, a queue is also  
 10 annotated with a number of expectations. These annotations reflect what the implementation of the queue as a set of communication busses should look like.

A communication bus contains one or more registers to  
 15 provide intermediate storage, and optionally also a handshake-protocol circuit. A queue then maps to one or more (for parallel communication) of these communication busses.

20 The expectations for a simulation queue are :

- The token concurrency, that expresses how many tokens of the same age can be present on one queue. To communicate a MATLAB vector annotated with 8@2 for example requires two communication busses. This is reflected in the high  
 25 level queue model by setting the token concurrency to two.
- In case the token concurrency is 1, it can be required that subsequent tokens are separated by a determined number of clock cycles. In combination with the travel  
 30 delay, this determines how many registers are needed on a communication bus. This expectation is called the token latency.

Example implementations for different expectations are shown in figure 9.

- 5 When the token concurrency is different from one, the token latency cannot be bigger than one. If it would, then the actor that provides the tokens can be designed more effectively using hardware sharing, and thus reducing the token concurrency.
- 10 A summary of the expectation based simulation is put as follows. First, there are several implicit adaptations to token ages and queue ages.
  - An actor description increases the queue age upon each actor iteration with the iteration time.
- 15 • A queue increases the age of communicated tokens with the travel delay.
- An SFG description increases token ages through the operations. The token age after a register is increased by one, all other operations generate a token with age
- 20 equal to the maximum of the operand ages.

The set of operations that modify the token age are referred to as token aging rules.

- 25 Next, a number of checks are active to verify the consistency of the simulation.
  - A token age cannot be younger (smaller) then a queue age.
  - The token concurrency on a queue cannot be exceeded.
- 30 • The token latency on a queue cannot be exceeded.

A successful clock-cycle true simulation should never fail any of these checks. In the case of such success, the expectations on the queue can be investigated more closely to devise a communication bus for it. In this description  
 5 we did not mention the use of handshake protocol circuits. A handshake protocol circuit can be used to synchronize tokens of different age at the input of an actor.

#### Implementation

10

The current library of OCAPI allows to describe a system in C++ by building on a set of basic classes.

- A simulation queue class that transports a token class  
 15 and allows to perform expectation-checks.
- An SFG/FSM class that allows clock cycle true specification, simulation and code generation.
- A token class that allows to simulate both floating point-type representation and fixed point type  
 20 representation.

One can simulate the MATLAB data-vector data-type with C++ simulation queues. For the common MATLAB operations, one can develop a library of SFG descriptions that reflect  
 25 different flavors of parallelism. For instance, a C++ version of the description

```
% input data
in = [1 2 1 3 3 4 1 2] ;
% spreading code
30 c = [1 -1 1 -1] ;
% correlate
ot = corr (in, c)
```

```

% find correlation peak
[max, maxpos] = max (ot) ;
looks, after scaling of the parallelism and defining the
actor boundaries, like
5 FB in, ot, maxp ;

 in.delay(1,0) ; //iteration time, travel delay
 ot.delay(1,0) ;
 maxp.delay(4,0) ;
10
 in.expect(1,1) ; //travel time, concurrency,
 latency
 ot.expect(1,1) ;
 maxp.expect(1,4) ;
15
 in = vector(1, 2, 1, 3, 3, 4, 1, 2) ;
 ot = corr(8, 4, in, vector(1, -1, 1, -1))
 maxp = maxpos(4, ot) ;

20 This C++ description contains all information necessary to
 simulate the system in mind at clock cycle true level and
 to generate the synthesizable code for the system and the
 individual actors.

25 Thus, the data-flow level has become transparent - it is
 not explicitly seen by the designer but rather it is
 implied through the expectations (pragma's) and the
 library.

30 Example 2: design of a 4-tap correlator processor

```

An example of processor design is given next to experience

hardware design when using OCAPI.

The task is to design a 4-tap correlator processor that evaluates a correlation value each two cycles. One coefficient of the correlation pattern needs to be  
 5 programmable and needs to be read in after a control signal is asserted. The listing in figure 11 gives the complete FSMD model of this processor.

The top of the listing shows how types are declared in OCAPI. For example, the type `T_sample` is 8 bits wide and  
 10 has 6 bits beyond the binary point.

For such a type declaration, a signed, wrap-around and truncating representation is assumed by default. This can be easily changed, as for instance in

```

15 // floating point
 dfix T_sample ;

 //unsigned
 dfix T_sample(8, 6, ns) ;
20

 //unsigned, rounding
 dfix T_sample(8, 6, ns, rd) ;

```

Below the type declarations we see coefficient  
 25 declarations. These are specified as plain `double` types, since they will be automatically quantized when read in into the coefficient registers. It is possible to intermix existing C/C++ constructs and types with new ones.

Following the coefficients, the FSMD definition of the  
 30 correlator processor is shown. This definition requires: the specification of the instruction set that is processed by this processor, and a specification of the control

behavior of the processor. For each of these, OCAPI uses dedicated objects.

First, the instruction set is defined. Each instruction performs data processing on signals, which must be defined first. The definitions include plain signals (`sample_in` and `corr_out`), registers (`accu`), and register arrays (`coef[]` and `sample[]`).

Next, each of the instructions are defined. A definition is started by creating a SFG object. All signal expressions that come after such an SFG definition are considered to make up part of it. A SFG definition is closed simply by defining a new SFG object.

The first instruction, `initialize_coefs`, initializes the coefficient registers `coef[]`. The `for` loop allows to express the initialization in a compact way. Thus, the `initialize_coefs` instruction is also equivalent to

```
coef[0] = W(T_coef, hardwired_coef[0]) ;
coef[1] = W(T_coef, hardwired_coef[1]) ;
20 coef[2] = W(T_coef, hardwired_coef[2]) ;
coef[3] = W(T_coef, hardwired_coef[3]) ;
```

The second instruction programs the value of the first coefficient. The new value, `coef_in`, is read from an input port of the FSMD with the same name. Beyond this port, we are 'outside' of the timed FSMD description and use dataflow semantics, and communicate via queues.

The third and fourth instruction, `correl_1` and `correl_2` describe the two phases of the correlation. It is very easy to express complex expressions just by using C++ operators. Also, a `cast` operation is included that limits the precision of the intermediate expression result. Although

The instruction `read_sample` shifts the data delay line. In addition to a `for` loop, an `if` expression is used to express the boundary value for the delay line. Use of simple C++ constructs such as these allow to express signal flow graph structure in a compact and elegant way. It is especially useful in parametric design.

Below all SFG definitions, the control behavior of the correlator processor is described. An FSM with three states is defined, using one initial state `rst`, and two normal states `phase_1` and `phase_2`. Next, four transitions are defined between those three states. Each transition specifies a start state, the transition condition, a set of instructions to execute, and a target state. For a designer used to finite state machine specification, this is a very compact and efficient notation.

The resulting fsm description is returned to OCAPI by the  
25 last **return** statement. The simulator and code generator can  
now process the object hierarchy in order to perform  
semantical checks, simulation, and code generation.

The translation to synthesizable VHDL and Cathedral-3 code is automatic and needs no extra designer effort. The  
30 resulting circuit for datapath and controller is shown in figure 12. The hierarchy of the generated code that is provided by OCAPI is also indicated. Each controller and

datapath are interlinked using a link cell. The link cell itself can be embedded into an automatically generated testbench or also in the system link cell that interconnects all components.

5

Example 3: design of Complex High Speed ASICs

The design of a 75 Kgate DECT transceiver is used as  
10 another example (figure 13).

The design consists of a digital radiolink transceiver ASIC, residing in a DECT base station (20) (figure 13). The chip processes DECT burst signals, received through a radio  
15 frequency front-end RF (21). The signals are equalized (22) to remove the multipath distortions introduced in the radio link. Next, they are passed to a wire-link driver DR (23), that establishes communication with the base station controller BSC (24). The system is also controlled locally  
20 by means of a control component CTL (25).

The specifications that come with the design of the digital transceiver ASIC in this system are as follows:

- 25 • The equalization involves complex signal processing, and is described and verified inside a high level design environment such as MATLAB.
- The interfacing towards the control component CTL and the wire-link driver DR on the other hand is described as a  
30 detailed clock-cycle true protocol.
- The allowed processing latency is, due to the real time operation requirements, very low: a delay of only 29 DECT

symbols (25.2  $\mu$ seconds) is allowed. The complexity of the equalization algorithm, on the other hand, requires up to 152 data multiplies per DECT symbol to be performed. This implies the use of parallel data processing, and  
 5 introduces a severe control problem.

- The scheduled design time to arrive from the heterogeneous set of specifications to the verified gate level netlist, is 18 person-weeks.
- 10 The most important degree of freedom in this design process is the target architecture, which must be chosen such that the requirements are met. Due to the critical design time, a maximum of control over the design process is required. To achieve this, a programming approach to implementation  
 15 is used, in which the system is modelled in C++. The object oriented features of this language allows to mix high-level descriptions of undesigned components with detailed clock-cycle true, bit-true descriptions. In addition, appropriate object modelling allows the detailed descriptions to be  
 20 translated to synthesizable HDL automatically. Finally, verification testbenches can be generated automatically in correspondence with the C++ simulation.

The result of this design effort is a 75 Kgate chip with a  
 25 VLIW architecture, including 22 datapaths, each decoding between 2 and 57 instructions, and including 7 RAM cells. The chip has a 194 die area in 0.7 CMOS technology.

The C++ programming environment allows to obtain results  
 30 faster then existing approaches. Related to register transfer design environments such as , it will be shown that C++ allows to obtain more compact, and consequently

T04090"ESSEZ850

less error prone descriptions of hardware. High level synthesis environments could solve this problem but have to fix the target architecture on beforehand. As will be described in the case of the DECT transceiver design, sudden changes in target architecture can occur due to hard initial requirements, that can be verified only at system implementation.

First, the system machine model is introduced. This model includes two types of description: high-level untimed ones and detailed timed blocks. Using such a model, a simulation mechanism is constructed. It will be shown that the proposed approach outperforms current synthesis environments in code size and simulation speed. Following this, HDL code generation issues and hardware synthesis strategies are described.

#### System Machine Model

Due to the high data processing parallelism, the DECT transceiver is best described with a set of concurrent processes. Each process translates to one component in the final system implementation.

At the system level, processes execute using data flow simulation semantics. That is, a process is described as an iterative behavior, where inputs are read in at the start of an iteration, and outputs are produced at the end. Process execution can start as soon as the required input values are available.

Inside of each process, two types of description are

1

- 5 The second flavour of processes is described at register transfer level. These processes operate synchronously to the system clock. One iteration of such a process corresponds to one clock cycle of processing.
- 10 For system simulation, two schedulers are available. A dataflow scheduler is used to simulate a system that contains only untimed blocks. This scheduler repeatedly checks process firing rules, selecting processes for execution as their inputs are available.
- 15 When the system also contains timed blocks, a cycle scheduler is used instead. The cycle scheduler manages to interleave execution of multi-cycle descriptions, but can incorporate untimed blocks as well.
- 20 Figure 14 shows the front-end processing of the DECT transceiver, and the difference between data-flow and cycle scheduling. At the top, the front-end processing is seen. The received signals are sampled by and A/D, and correlated
- 25 with a unique header pattern in the header correlator HCOR. The resulting correlations are detected inside a header detector block HDET. A simulation with high level descriptions uses the dataflow scheduler. An example dataflow schedule is seen in the middle of the figure. The
- 30 A/D high level description produces 3 tokens, which are put onto the interconnect communication queue. Next, the correlator high level description can be fired three times,

followed by the detector processing.

When a cycle true description of the A/D and header correlator on the other hand is available, this system can  
5 be simulated with the cycle scheduler as shown on the bottom of the figure. This time, behavior of the A/D block and correlator block are interleaved. As shown for the HCOR block, executions can take multiple cycles to perform. The remaining high level block, the detector, contains a firing  
10 rule and is executed as required. Related to the global clock grid, it appears as a combinatorial function.

Detailed process descriptions reflect the hardware behavior of a component at the same level of the implementation. To  
15 gain simulation performance and coding effort, several abstractions are made.

Finite Wordlength effects are simulated with a C++ fixed point library. It has been shown that the simulation of  
20 these effects is easy in C++ . Also, the simulation of the quantization rather than the bitvector representation allows significant simulation speedups .

The behavior is modelled with a mixed control/data processing description, under the form of a finite state  
25 machine coupled to a datapath. This model is common in the synthesis community. In high throughput telecommunications circuits such as the ones in the DECT transceiver ASIC, it most often occurs that the desired component architecture is known before the hardware description is made. The FSM model works well for these type of components.  
30

The two aspects, wordlength modelling and cycle true

modelling, are available in the programming environment as separate class hierarchies. Therefore, fixed point modelling can be applied equally well to high level descriptions.

5

As an illustration of cycle true modelling, a part of the central VLIW controller description for the DECT transceiver ASIC is shown in figure 15. The top shows a Mealy type finite state machine (30). As actions, the  
 10 signal flowgraph descriptions (31) below it are executed. The two states execute and hold correspond to operational and idle states of the DECT system respectively. The conditions are stored in registers inside the signal flowgraphs. In this case, the condition holdrequest is  
 15 related to an external pin.

In execute state, instructions are distributed to the datapaths. Instructions are retrieved out of a lookup table, addressed by a program counter. When holdrequest is  
 20 asserted, the current instruction is delayed for execution, and the program counter PC is stored in an internal register. During a hold, a nop instruction is distributed to the datapaths to freeze the datapath state. As soon as holdrequest is removed, the stored program counter holdpc  
 25 addresses the lookup table, and the interrupted instruction is issued to the datapaths for execution.

### Signals and Signal Flow Graphs

30 Signals are the information carriers used in construction of a timed description. Signals are simulated using C++ sig objects. These are either plain signals or else registered

T04090-ESSE4850

5

10

15

- 20

25

30

## Finite State Machines

After all instructions are described as SFG objects, the control behavior of the component has to be described. We  
 5 use a Mealy-type FSM model to do this.

Again, the use of C++ objects allow to obtain very compact and efficient descriptions. Figure 18 shows a graphical and C++-textual description of the same FSM. The correspondence  
 10 is obvious. To describe an equivalent FSM in an event driven HDL, one usually has to follow the HDL simulator semantics, and for **example** use multi-process modelling. By using C++ on the other hand, the semantics can be adapted depending on the type of object processed, all within the  
 15 same piece of source code.

## Architectural Freedom

An important property of the combined control/data model is  
 20 the architectural freedom it offers. As an example, the final system architecture of the DECT transceiver is shown in figure 19. It consists of a central (VLIW) controller (50), a program counter controller (51) and 22 datapath blocks. Each of these are modelled with the combined  
 25 control/data processing shown above. They exchange data signals that, depending on the particular block, are interpreted as instructions, conditions or signal values. By means of these interconnected FSMD machines, a more complex machine is constructed.

30

It is now motivated why this architectural freedom is necessary. For the DECT transceiver, there is a severe

0007355-050401  
 104090-0552050

latency requirement. Originally, a dataflow target architecture was chosen (figure 20), which is common for this type of telecommunications signal processing. In such an architecture, the individual components are controlled  
 5 locally and data driven. For example, the header detector processor signals a DECT header start (a correlation maximum), as soon as it is sure that a global maximum is reached.

Because of the latency requirement however, extra delay in  
 10 this component cannot be allowed, and it must signal the first available correlation maximum as a valid DECT header. In case a new and better maximum arrives, the header detector block must then raise an exception to subsequent blocks to indicate that processing should be restarted.  
 15 Such an exception has global impact. In a data driven architecture however, such global exceptions are very difficult to implement. This is far more easy in a central control architecture, where it will take the form of a jump in the instruction ROM. Because of these difficulties, the  
 20 target architecture was changed from data driven to central control. The FSMD machine model allowed to reuse the datapath descriptions and only required the control descriptions to be reworked. This architectural change was done during the 18-week design cycle.

25

### The Cycle Scheduler

Whenever a timed description is to be simulated, a cycle scheduler is used instead of a dataflow scheduler. The  
 30 cycle scheduler creates the illusion of concurrency between components on a clock cycle basis.

The operation of the cycle scheduler is best illustrated with an example. In figure 21, the simulation of one cycle in a system with three components is shown. The first two, components 1 (60) and 2 (61), are timed descriptions  
5 constructed using fsm and sfg objects. Component 3 (62) on the other hand is described at high level using a firing rule and a behavior. In the DECT transceiver, such a loop of detailed (timed) and high level (untimed) components occurs for instance in the RAM cells that are attached to  
10 the datapaths. In that case, the RAM cells are described at high level while the datapaths are described at clock cycle true level.

The simulation of one clock cycle is done in three phases.  
15 Traditional RT simulation uses only two; the first being an evaluation phase, and the second being a register update phase.

The three phases used by the cycle scheduler are a token  
20 production phase, an evaluation phase and a register update phase.

The three-phase simulation mechanism is needed to avoid apparent deadlocks that might exist at the system level. Indeed, in the example there is a circular dependency in  
25 between components 1, 2, and 3, and a dataflow scheduler can no longer select which of the three components should be executed first. In dataflow simulation, this is solved by introducing initial tokens on the data dependencies. Doing so would however require us to devise a buffer  
30 implementation for the system interconnect, and introduce an extra code generator in the system.

T0490"060401

The cycle scheduler avoids this by creating the required initial tokens in the token production phase. Each of the phases operates as follows.

- 5 [0] Each the start of clock cycle, the sfg descriptions to be executed in the current clock cycle are selected. In each fsm description, a transition is selected, and the sfg related to this transition are marked for execution.
- [1] Token production phase. For each marked sfg, look into
  - 10 the dependency graph, and identify the outputs that solely depend on registered signals and/or constant signals. Evaluate these outputs and put the obtained tokens onto the system interconnect.
  - [2] (a) Evaluation phase (case a). In the second phase,
    - 15 schedule marked sfg and untimed blocks for execution until all marked sfg have fired. Output tokens are produced if they are directly dependent on input tokens for timed sfg descriptions, or else if they are outputs of untimed blocks.
    - 20 [2] (b) Evaluation phase (case b). Outputs that are however only dependent on registered signals or constants will not be produced in the evaluation phase.
  - [3] Register update phase. For all registered signals in marked sfg, copy the next-value to the current-value.

25

The evaluation phase of the three-phase simulation is an iterative process. If a pre-set amount of iterations have passed, and there are still unfired components, then the system is declared to be deadlocked. This way, the cycle

30 scheduler identifies combinatorial loops in the system.

The clock-cycle true, bit-true description of system components serves a dual purpose. First, the descriptions have to be simulated in order to validate them. Next, the  
5 descriptions have also to be translated to an equivalent, synthesizable HDL description.

In view of these requirements, the C++ description itself  
10 can be treated in two ways in the programming environment. In case of a compiled code approach, the C++ description is translated to directly executable code. In case of an interpreted approach, the C++ description is preprocessed by the design system and stored as a data structure in  
15 memory.

Both approaches have different advantages and uses. For simulation, execution speed is of primary importance. Therefore, compiled code simulation is needed. On the other  
20 hand, HDL code generation requires the C++ description to be available as a data structure that can be processed by a code generator. Therefore, a code generator requires an interpreted approach.

25 We solve this dual goal by using a strategy as shown in figure 22. The clock-cycle true and bit-true description of the system is compiled and executed. The description uses C++ objects such as signals and finite state machine descriptions which translate themselves to a control/data  
30 flow data structure.

This data structure can next be interpreted by a simulator

for quick verification purposes. The same data structure is also processed by a code generator to yield two different descriptions.

- 5 A C++ description can be regenerated to yield an application-specific and optimized compiled code simulator. This simulator is used for extensive verification of the design because of the efficient simulation runtimes. A synthesizable HDL description can also be generated to  
10 arrive at a gate-level implementation.

The simulation performance difference between these three formats (interpreted C++ objects, compiled C++, and HDL) is illustrated in table 1. Simulation results are shown for  
15 the DECT header correlator processor, and also the complete DECT transceiver ASIC.

The C++ modelling gains a factor of 5 in code size (for the interpreted-object approach) over RT-VHDL modeling. This is  
20 an important advantage given the short design cycle for the system. Compiled code C++ on the other hand provides faster simulation and smaller process size then RT-VHDL.

For reference, results of netlist-level VHDL and Verilog  
25 simulations are given.

| Design | Size<br>(Gates) | Type                     | Source<br>Code<br>(# lines) | Simulation<br>Speed<br>(cycles/s) | Process<br>Size<br>(Mb) |
|--------|-----------------|--------------------------|-----------------------------|-----------------------------------|-------------------------|
| HCOR   | 6K              | C++ (interpreted<br>obj) | 230                         | 69                                | 3.8                     |

|      |     |                         |       |      |      |
|------|-----|-------------------------|-------|------|------|
|      |     | C++ (compiled)          | 1700  | 819  | 2.7  |
|      |     | VHDL (RT)               | 1600  | 251  | 11.9 |
|      |     | VHDL (Netlist)          | 77000 | 2.7  | 81.5 |
| DECT | 75K | C++(interpreted<br>obj) | 8000  | 2.9  | 20   |
|      |     | C++ (compiled)          | 26000 | 60   | 5.1  |
|      |     | Verilog<br>(Netlist)    | 59000 | 18.3 | 100  |

Table 1.

### Synthesis Strategy

5 Finally, the synthesis approach that was used for the DECT transceiver is documented. As shown in figure 1D, the clock-cycle true, bit-true C++ description can be translated from within the programming environment into equivalent HDL.

10

For each component, a controller description and a datapath description is generated, in correspondence with the C++ description. This is done because we rely on separate synthesis tools for both parts, each one optimized towards  
15 controller or else datapath synthesis tasks.

For datapath synthesis, we rely on the Cathedral-3 back-end datapath synthesis tools , that allow to obtain a bitparallel hardware implementation starting from a set of  
20 signal flowgraphs. These tools allow operator sharing at word level, and result in run times less than 15 minutes even for the most complex, 57-instruction data path of the DECT transceiver.

Controller synthesis on the other hand is done by logic synthesis such as Synopsys DC. For pure logic synthesis such as FSM synthesis, this tool produces efficient results. The combined netlists of datapath and controller  
 5 are also post-optimized by Synopsys DC to perform gate-level netlist optimizations. This divide and conquer strategy towards synthesis allows each tool to be applied at the right place.

10 During system simulation, the system stimuli are also translated into testbenches that allow to verify the synthesis result of each component. After interconnecting all synthesized components into the system netlist, the final implementation can also be verified using a generated  
 15 system testbench.

Example 4: design of a QAM transmission system with OCAPI (figure 23)

A QAM transmission system, that includes a transmitter, a  
 20 channel model, and a receiver is designed.

#### ***System Specification***

A system specification in OCAPI is an executable model: an  
 25 executable file, that can be run as a software program on a computer. The principle of executable specification, as it is called, is very important for system design. It allows one to check your specification using simulations. In this case, we are designing a QAM transmission system. A full  
 30 communications system contains a transmitter, a channel model, and a receiver. The ensemble of the transmitter, channel model and receiver organized as an executable

09873553-060401  
 T04090-2552860

specification is also called an end-to-end executable specification. The term end-to-end clearly indicates that the simulation starts with a user message, and ends with a (received) user message. In between, the complete digital transmission is modeled, as shown in figure 23.

In this text, the complete transmission system will be developed. The development of a component in such a system is never a one-shot process. Rather, development proceeds through a design flow: a collection of subsequent design levels connected by 'natural' design tasks. For a modem, the typical design levels are:

- a statistical level, to do high level explorations of algorithms. In OCAPI, this level is called the link level.
- 15 - a functional level, to assemble selected algorithms into a single operational modem. In OCAPI, this level is called the algorithm level.
- a structural level, to represent the modem as a machine that executes a functional description. In OCAPI, this level is called the architecture level. Each of these levels has an own set of requirements. Statistical requirements can be for example a bit error rate or a cell loss ratio. Functional requirements are for instance the set of modulation schemes to support.
- 20
- 25 Finally, structural requirements are requirements like type of interfaces, or preselected architectures.

Arranging the requirements besides the design levels yields the design flow, as shown in figure 1B. The dashed box contains the levels that will be coded in C++-OCAPI. The upper level (the statistical one) is described in a language like Matlab. It is not included in this text: We

will start from a complete functional specification. The functional specification is given herebelow in part A.

### *Design Flow in OCAPI-C++*

#### 5 Overall Design Flow

10 A design flow with OCAPI looks, from a high level point of view, as shown in figure 1C. The initial specification is an architecture model, constructed in C++. Through the use of refinement, we will construct an architecture model out of it. Next, relying on code generation, we obtain a synthesizable architecture model. This model can be converted to a technology-mapped architecture in terms of gates. OCAPI is 15 concerned with the C++ layers of this flow, an in addition takes care of code generation issues.

#### *Algorithmic Models*

20 The algorithmic models in OCAPI use the dataflow computational model. The construction of this code by small examples selected out of Part B (below) is discussed.

First, we consider the construction of an actor. An actor is a subalgorithm out of a dataflow system model. In OCAPI, each actor is defined by one class. As an 25 example of actor definition, we take the diffenc block out of the transmitter. The include file (3.3) defines a class diffenc (line 10) that inherits from a base class. This inheritance defines the class under definition as a dataflow actor. The dataflow actor 30 defines a constructor, a run method and a reset method. The run method (line 25) is the method that is called

09873553-060401  
T04090" 05532860

when the actor should be executed. This method takes along parameters that include the name (name), the I/O ports (`_sym 1`, `_symb2`) and other attributes (`_qpsk`, `_diff_mode`). The type FB (Flow-Buffer) is the type of a

5       FIFO queue. Looking at the implementation of `run` (??, line 26), we distinguish a firing rule in lines 29-30. The `getSize()` method of a queue returns the number of elements in that queue. The firing rule expresses that the `run()` method should return whenever there is no

10       data available in the queue. Otherwise, processing continues as described beyond line 32 (This processing is the implementation of the spec as described in Part A.

A dataflow system is constructed out of such actors.

15       The system code in 5.3 shows how the `diffenc` actor is instantiated (lines 57-61). Besides actors, the system code also creates interconnect queues (lines 42-48). By giving these as parameters in the constructor of actors, the required communication links are

20       established. Besides the interconnection of actors, the system code also needs to create a scheduler. This scheduler will repeatedly test firing rules in the actors (by calling their `run()` method). The system scheduler that steers the differential encoder is shown

25       on line 77 of 5.3. After this object is created, all dataflow actors that should be under control of it are "shifted into" it. The scheduler object has a method, `run()`, that tries firing all of the actors associated with the schedule just once.

An architecture model expresses the behavior of the algorithmic model in terms of operations onto hardware. The kind of hardware features that affect this depend of course on the target architectural style. OCAPI is intended for a bit-parallel, synchronous style. For this kind of style, two kinds of refinements are necessary: First, the data types need to be expressed in terms of fixed point numbers. Second, the execution needs to proceed in terms of clock cycles. The first kind of refinement is called fixed point modeling. The second kind is called cycle true modeling. These two refinements can be done in any order; for a complete architecture model, both are needed. We first give an example on how fixed point numbers are expressed in C++. Consider the ad block of the transmitter (3.2, line 24-27). The purpose of this block is to introduce a quantization effect, such as for instance would be encountered when the signal passes through an analog-digital or digital-analog converter. In this case, the high level algorithmic model is constructed with a fixed point number in order to perform this quantization. On line 32, an object of type dfix (called indfix) is created. This object represents a fixed point value. The constructor uses three parameters. The first, '0', provides an initial value. The following two (W and L) are parameters that represent the wordlength and fractional wordlength respectively. The operation of the ad block is as follows. When there is information in the input queue, the value read is assigned to the fixed point number indfix. At the moment of assignment, quantization happens, whether or not the input value was a floating

point value (The FIFO buffers are actually passing along objects of type dfix, so that floating as well as fixed point numbers can be passed from one block to the other). A next example will show how cycle true modeling is done. We consider the derandomizer function of the receiver (6.4). First, looking at the algorithmic model (line 6 9-102), we see that the block reads two inputs (byte\_in and syncro) and writes one output (byte\_out). In between, it performs some algorithmic processing (line 89-97). The architecture model is shown in the define() function starting at line 116. The first few lines are type definitions and signal declarations. Next, four instructions are defined (line 143-179), and a controller which sequences these instructions is specified (line 184-195). The architecture model makes heavily use of macros to ease the job of writing code. All of these are explained above. The goal of the define() function is to define an object hierarchy consisting of signals, expressions, states, etc ...that represents the cycle true behavior of a processor. At the top of the hierarchy is a finite state machine object. The member function fsm() (line 106) returns this object (which is a data member of the derandomizer class). The system integration of the derandomizer (5.3, line 169-176) is the same for the algorithmic and architecture model. The selection between algorithmic and architecture model is done by giving a system scheduler either a base object (as in line 186) or else the fsm object for simulation (as in line 206). Remember that the algorithmic model derives creates a class that derives

09873553-060401  
T04090-0552860

from the base object; while an architecture model defines a finite state machine object.

### *Code Generation*

5 Finally we indicate the output of the code generation process. When an architecture model is constructed, several code generators can be used. OCAPI currently can generate RT-VHDL code directly, or else also Cathedral-3 dsfg code. When the member function  
 10 generate() of a system scheduler is called, Cathedral-3 code will be produced, along with the required system link cells. The member function vhdlook() on the other hand produces RT-VHDL code. In this example, we have used the vhdlook() method (5.2, line 401). We consider  
 15 the derandomizer block in the receiver. The first place where this appears in the generated code is in the system netlist (6.13, line 70 and line 143). Next, we can find the definitions of the block itself: its entity declaration (6.14), the RTL code (6.15), and a  
 20 mapping cell from the fixed-point VHDL type FX to the more common VHDL type std\_logic (6.16). By using this last mapping cell, we can also hook up the VHDL code for derand in a generated testbench (6.17). This testbench driver reads stimuli recorded during the C++  
 25 simulation and feeds them into the VHDL simulation.

### Part A: System Specification

#### *System Contents*

30 The end-to-end model of the QAM transmission system under consideration is shown in figure 23. It consists of four main components:

- A byte generator GEN (201)
- A transmitter TX.(203)
- A channel model CHAN.(205)
- A receiver RX.(207)

5

The byte generator generates a sequence of random bytes. These are modulated inside of the transmitter to a QAM signal. The channel model next introduces distortions in the signal, similar to those occurring in a real channel.

- 10 Finally, the receiver demodulates the signal, returning a decoded byte sequence. If no bit errors occur, then this sequence should be the same as the one created by the byte generator.

- Next, the detailed operation of the transmitter, the  
15 channel and the receiver is discussed. For the internal construction of a component, one might however still refer to figure 24.

#### *Transmitter Specification*

- 20 The Transmitter includes

- rnd: A randomizer, which transforms a byte sequence into a pseudorandom byte sequence. This is done because of the more regular spectral properties of a randomized (or 'whitened') byte sequence.
- 25 - tuple: A tuplelizer, which chops the transmitted bytes into QAM/QPSK symbols.
- diffenc: A differential encoder which applies differential encoding to the symbols.
- map: A QAM symbol mapper, which translates QAM symbols  
30 to I/Q pulse sequence s.

09872553.060401

- shape: A pulse shaper, which transforms the pulse sequences to a continuous wave. In digital implementation, the temporal 'continuity' is achieved by applying oversampling.
- 5 - da: Finally, there is a block which applies quantization to the signal. This block simulates the effect of a digital-to-analog converter.

The transmitter reads in a byte sequence, and randomizes  
 10 this with a pseudorandom byte sequence. The sequence contains a synchronization word to align the receiver derandomizer to the transmitter randomizer. The pseudorandom sequence is generated by exoring a bitstream with a bitstream produced by a linear feedback shift  
 15 register (LFSR). The LFSR produces a bitstream according to the polynomial  $g(x) = 1 + x^5 + x^6$ . It next feeds the bytes to a tuplelizer that generates symbols out of the byte sequence according to the following scheme.

Given bits b7 b6 b5 b4 b3 b2 b1 b0,

20

| Bit position | QAM16      | QPSK          |
|--------------|------------|---------------|
| b7           | I symbol 0 | I[1] symbol 0 |
| b6           | Q symbol 0 | I[0] symbol 0 |
| b5           | I symbol 1 | Q[1] symbol 0 |
| b4           | Q symbol 1 | Q[0] symbol 0 |
| b3           | I symbol 2 | I[1] symbol 1 |
| b2           | Q symbol 2 | I[0] symbol 1 |
| b1           | I symbol 3 | Q[1] symbol 1 |
| b0           | Q symbol 3 | Q[0] symbol 1 |

The symbols values are next fed to the differential encoder that generates a diff encoded symbol sequence:

```
i=(((~(a ^ b)) & (a ^ glbIstate))|((a ^ b) & (b ^ glbQstate))) &1;
```

```
5 q=(((~(a ^ b)) & (b ^ glbQstate))|((a ^ b) & (a ^ glbIstate))) &1;
```

with i and q the output msbs of the differentially encoded symbol; glbIstate, glbQstate the previous values of i and q; and a and b the inputs msbs of the input symbol. The

10 lsbs are left untouched (only for qam16) The differentially encoded symbol sequence is next mapped to the actual symbol value using the following constellation for QPSK.

| QVal/Ival | -3 | +3 |
|-----------|----|----|
| +3        | 2  | 0  |
| -3        | 3  | 1  |

15 For QAM16, the following constellation will be used

| QVal/Ival | -3 | -1 | 1 | +3 |
|-----------|----|----|---|----|
| +3        | 11 | 9  | 2 | 3  |
| +1        | 10 | 8  | 0 | 1  |
| -1        | 14 | 12 | 4 | 6  |
| -3        | 15 | 13 | 5 | 7  |

After mapping, the resulting complex sequence is pulse shaped. A RRC shaping filter with oversampling  $n = 4$  is taken, with the rolloff factor set at  $r = 0.3$ . After pulse shaping, the sequence is upconverted to  $fc = fs/4$  in the multiplexer block (included in the shaper)

*Channel Model Specification*

The Channel Model contains

- FIR filter with programmable taps. The filter is used to simulate linear distortions such as multipath effects.
  - 5 - Noise injection block. The incoming signal is fed into a 20 tap filter. The second, third, fourth and 21th tap of the filter are programmable. Next a noise signal is added to the sequence. The noise distribution is gaussian;
- ```

10      X1 = sqrt(-2ln*(U1)) * cos(2*pi*U2)
        X2 = sqrt(-2ln*(U1)) * sin(2*pi*U2)

        U1, U2 are independent and uniform [0,1],
        X1 and X2 are independent and N(0,1)

```

15

Receiver Specification

The Receiver includes

- lmsff A feed forward, T/4 spaced LMS Equalizer.
- 20 • demap A demapper, translating a complex signal back to a QAM symbol.
- detuple A detupler, glueing individual symbols back to bytes.
- derand A derandomizer, translating the pseudonoise
- 25 sequence back to an unrandomized sequence.

It is not difficult to see that this signal processing corresponds to the reverse processing that was applied at the transmitter. The incoming signal is fed into an

30 equalizer block. The 4 tap oversampled FF equalizer is initialized with a downconverting RRC sequence. This way,

the equalizer will act at the same time as a matched filter, a symbol timing recovery loop, a phase recovery loop, and an intersymbol-interference removing device. It is a simple solution at the physical synchronization
 5 problem in QAM.

The equalizer is initialized as follows. Given the complex RRC

	tap0	tap1	tap2	tap3
I	i0	i1	i2	i3
Q	q0	q1	q2	q3

then the LMS should be initialized with

	tap0	tap1	tap2	tap3
I	i0	0	-i2	0
Q	0	q1	0	-q3

10

The coefficient adaption algorithm of the equalizer is of the Least Mean Square type. This algorithm is decision directed; such algorithms are able to do tracking in a
 15 synchronization loop, but not to do acquisition (initialization) of the same loops. For simplicity in this example, we will however make abstraction of this acquisition problem. Next, the inverse operations of the transmitter are performed: the demodulated complex signal
 20 is converter to a QAM symbol in the demapper. The resulting QAM symbol stream is differentially decoded and assembled to a byte sequence in the detupler. The differential decoding proceeds according to

$$a = (((\sim(i \wedge q)) \& (i \wedge \text{glbIstate})) | ((i \wedge q) \& (q \wedge \text{glbQstate}))) \& 1;$$

$$b = (((\sim(i \wedge q)) \& (q \wedge \text{glbQstate})) | ((i \wedge q) \& (i \wedge \text{glbIstate}))) \& 1;$$
 25

Finally, the pseudorandom encoding of the sequence is removed in the derandomizer.

Part B: C++ code of the QAM system

5

3 Transmitter Code

3.1 tx/ad.h

```

1 // ad.h
10 2 // All rights reserved -- Imec 1998
3 // @(#)ad.h1.2 03/20/98
4
5 #ifndef AD_H
6 #define AD_H
15 7
8 #include "qlib.h"
9
10 class ad : public base{
11     FB *in;
20 12     FB *ot;
13     double*W;
14     double*L; ;
15
16 public:
25 17     ad(char *name, FB & _in, FB & _ot, double& _W, double
    &_L);
18     int run();
19     int reset();
20 };
30 21
22 #endif

```

09073553-060404

3.2 tx/ad.cxx

```

1 // ad.cxx
5 2 // All rights reserved -- Imec 1998
3 // @(#)ad.cxx 1.4 03/31/98
4
5#include "ad.h"
6
10 7 ad::ad(char*name,
8     FB & _in,
9     FB & _ot,
10    double & _W,
11    double & _L): base(name)
15 12 {
13     in = _in.asSource(this);
14     ot = _ot.asSink(this);
15     W   = &_W;
16     L   = &_L;
20 17 }
18
19 int ad::reset() {
20     //return to initial state
21     return 1;
25 22 }
23
24 intad::run() {
25
26     //firing rule
30 27 if(in->getSize() < 1) {
28     return 0;
29 }

```

09873553-060404

```

30
31 //core functionality
32 dfix indfix(0,(int) (*W), (int) (*L));
33 indfix= in->get( ) ; // inputting+ quantization
5 assignment
34 ot->put(indfix) ; // outputing
35
36 return 1;
37 }
10 38

```

3.3 tx/diffenc.h

```

1 // diffenc.h
15 2 // All rights reserved -- Imec 1998
3 // @(#)diffenc.h 1.7 98/03/31
4
5 #ifndef DIFFENC_H
6 #define DIFFENC_H
20 7
8 #include "qlib.h"
9
10 class diffenc: public base{
11
25 12 FB *symb1;
13 FB *symb2;
14 double *qpsk;
15 double *diff_mode;
16 int iState;
30 17 int qState;
18
19 public:

```

T04090"ESSZ880

```

20   diffenc(char *name,
21           FB & _symb1,
22           FB & _symb2,
23           double &_qpsk,
5 24           double &_diff_mode);
25   int run();
26   int reset();
27 };
28
10 29#endif

```

3.4 tx/diffenc.cxx

```

1 // diffenc.cxx
15 2 // All rights reserved -- Imec 1998
3 // @(#)diffenc.cxx 1.8 98/03/31
4
5#include "diffenc.h"
6
20 7 diffenc::diffenc(char*name,
8           FB & _symb1,
9           FB & _symb2,
10           double &_qpsk,
11           double &_diff_mode): base(name)
25 12 {
13   symb1    = _symb1.asSource(this);
14   symb2    = _symb2.asSink(this);
15   qpsk     = &_qpsk;
16   diff_mode= &_diff_mode;
30 17   reset();
18 }
19

```

09673553-060401

```

20 int diffenc::reset() {
21     iState= 0;
22     qState= 0;
23     return 1;
5 24 }
25
26 int diffenc::run() {
27
28     //firing rule
10 29     if(symb1->getSize() < 1)
30         return 0;
31
32     //core func
33     intsymb = (int)Val(symb1->get( ) ) ;
15 34
35     if((int)*diff _mode) {
36         int a = ((int)*qpsk) ? (symb>> 1) & 1 : (symb>> 3) &
1 ;
// get msb's only
20 37         int b = ((int)*qpsk) ? (symb>> 0) & 1 : (symb>> 2) &
1 ;
38
39         int i = (((("a^b)) & (a^iState))|(a(^b)
&b(^qState))) &1; // encodemsb
25 40         int q = (((("a^b)) & (b^qState))|(a(^b)
&a(^iState))) &1;
41
42         iState= i;
43         qState= q;
30 44
45         symb = ((int)*qpsk)?(i<< 1)|q : (i<< 3)|(q<<
2)|(symb& 3);

```

```

46  }
47
48  symb2->put(symb);
49  return 1;
5 50 }
51

```

3.5 tx/map.h

```

10 1 //-----
   2 //  COPYRIGHT
   3 //  =====
   4 //
   5 //  Copyright1996 IMEC, Leuven,Belgium
15 6 //
   7 //  Allrights reserved.
   8 //
   9 //-----
  10 // Module:
20 11 //      MAP
   12 //
  13 // Purpose:
   14 //      Mapping of QAM16 constellations to symbols and
      back
25 15 //
   16 // Author:
   17 //      Patrick Schaumont
   18 //-----
   19
30 20#define  MAP_H
   21#define  MAP_H
   22

```

T04090" ESE2860

```

23#include "qlib.h"
24
25 classmap : public base{
26     double *qpsk;
5 27
28     FB * sIn;
29     FB * qOut;
30     FB * iOut;
31
10 32     dfix immediateQ(dfix v);
33     dfix immediateI(dfix v);
34
35 public:
36     map(char *name, FB& _sIn, FB & _iOut, FB& _qOut, double
15 &_qpsk);
37     int run();
38
39 };
40
20 41#endif

```

3.6 tx/map.cxx

```

1 //-----
25 2 //  COPYRIGHT
3 //  =====
4 //
5 //  Copyright1996 IMEC, Leuven,Belgium
6 //
30 7 //  Allrights reserved.
8 //
9 //-----

```

0987353-060404
F04090"E5E/860

```

10 // Module:
11 //      MAP
12 //
13 // Purpose:
5 14 //      Mapping of QAM16 constellationsto symbolsand back
15 //
16 // Author:
17 //      Patrick Schaumont
18 //-----
10 19
20
21#include "map.h"
22
23 // #   #   ##   #####
15 24 // ## ##  #  #  #
25 // #### #   #  #   #
26 // #   # ##### #####
27 // #   # #   #  #
28 // #   # #   #  #
20 29
30
31 // QAM16
32 static double vQMap16[]={
33   ( 0.0),
25 34   (+1 .0), (+1.0), (+3.0), (+3.0),
35   (-1 .0), (-3.0), (-1.0), (-3.0),
36   (+1 .0), (+3.0), (+1.0), (+3.0),
37   (-1 .0), (-3.0), (-1.0), (-3.0)
38 };
30 39
40 static double vIMap16[] = {
41   ( 0.0),

```

T04090"ESSE2860

```

42  (+1 .0), (+3.0), (+1.0), (+3.0),
43  (+1 .0), (+1.0), (+3.0), (+3.0),
44  (-1 .0), (-1.0), (-3.0), (-3.0),
45  (-1 .0), (-1.0), (-3.0), (-3.0)
5  46  };
47
48  // QPSK
49  static double vQMap4[]={
50  ( 0.0),
10 51  (+3 .0), (-3.0), (+3.0), (-3.0),
52  };
53  static double vIMap4[] = {
54  ( 0.0),
55  (+3 .0), (+3.0), (-3.0), (-3.0),
15 56  };
57
58  map::map(char*name,  FB&    _sIn,FB    &    _iOut,  FB&
    _qOut,double& _qpsk) : base(name) {
59      sIn = & _sIn;
20 60      qOut = & _qOut;
61      iOut= & _iOut;
62      qpsk= & _qpsk;
63  }
64
25 65 dfix map::immediateQ(dfiv) {
66      if((int)*qpsk) {
67          return dfix(vQMap4[(int)Val(v+1) ] ) ;
68      } else{
69          return dfix(vQMap16[(int)Val(v+1) ] ) ;
30 70  }
71  }
72

```

T04090" E55E4860

```

73 dfix map::immediateI(dfiv) {
74     if((int)*qpsk) {
75         return dfix(vIMap4[(int)Val(v+1) ] ) ;
76     } else{
5 77         return dfix(vIMap16[(int)Val(v+1) ] ) ;
78     }
79 }
80
81 intmap::run() {
10 82     if(sIn->getSize() < 1)
83         return 0;
84     dfix v = sIn->get();
85     *iOut << immediateI(v);
86     *qOut << immediateQ(v);
15 87     return 1;
88 }
89

```

3.7 tx/rnd.h

```

20
1 // rnd.h
2 // All rights reserved -- Imec1998
3 // @(#)rnd.h 1.5 03/31/98
4
25 5#define RND_H
6#define RND_H
7
8#include "qlib.h"
9
30 10#define SYNCPERIOD 54
11#define SYNCWORD1 0x00
12#define SYNCWORD2 0x55

```

00873553-060404

```

13#define SYNCWORD3 0x00
14#define SYNCWORD4 0x55
15
16 class rnd : public base{
5 17     FB     *input;
18     FB     *output;
19     int     syncctr;
20
21 public:
10 22     rnd(char *name, FB& _input, FB& _output);
23     int run();
24     int reset();
25 };
26
15 27#endif

```

3.8 tx/rnd.cxx

```

1 // rnd.cxx
20 2 // All rights reserved -- Imec 1998
3 // @(#)rnd.cxx 1.6 03/20/98
4
5#include "rnd.h"
6
25 7 int glbRandom = 1;
8
9 int glbRandState;
10
11 rnd::rnd(char *name,
30 12     FB & _input,
13     FB & _output) :base(name)
14 {

```

```

15  input = _input.asSource(this);
16  output= _output.asSink(this);
17  syncctr= 0;
18  reset();
5  19 }
20
21
22#define BIT(k, n)  ((k>> (n-1)) & 1)
23#define MASK(k, n) (k & ((1<< (n+1))-1))
10 24
25 int randbit() {
26     int r;
27
28     r= BIT(glbRandState, 5) ^ BIT(glbRandState, 6 );
15 29     glbRandState= MASK(r | (glbRandState<< 1) , 6);
30
31     if(glbRandom)
32         return r;
33     else
20 34         return 0;
35 }
36
37
38 // =====MEMBER
25 FUNCTIONS
39
40 int rnd::reset() {
41     //return to initial state
42     glbRandState= (1<< 7) -1;
30 43     return 1;
44 }
45

```

T:04090"0552/060

```

46 int rnd::run() {
47     //firing rule
48     if(input->getSize() < 1) {
49         return 0;
5 50 }
51
52
53     //core func
54     int i;
10 55     int outbyte = 0;
56     int inbyte = (int)Val(input->get( ) ) ;
57     for (i=7; i>=0; i--) {
58         outbyte= (outbyte<<1) | (randbit( ) ^(inbyte>>i &
1 1));
15 59 }
60     syncctr++;
61     if(syncctr == SYNCPERIOD) {
62         // cerr << "*** INFO:randomizer sends SYN\n";
63         output->put(outbyte);
20 64         output->put(SYNCWORD1);
65         output->put(SYNCWORD2);
66         output->put(SYNCWORD3);
67         output->put(SYNCWORD4);
68         syncctr= 0;
25 69         reset();
70     }
71     else {
72         output->put(outbyte);
73     }
30 74 return 1;
75 }
76

```

T04090-060404-09873553

77

3.9 tx/shape.h

```

5  1 // shape.h
    2 // All rights reserved -- Imec 1998
    3 // @(#)shape.h 1.3 03/18/98
    4
    5 #ifndef  SHAPE_H
10  6 #define  SHAPE_H
    7
    8 #include "qlib.h"
    9
   10 #define  MAXLEN 33
15  11
    12 class shape : public base{
    13     FB  * i_in;
    14     FB  * q_in;
    15     FB  * s_out;
20  16     double c[MAXLEN] ; // RC coefficients
    17
    18 public:
    19     shape(char *name, FB& _i_in, FB& _q_in, FB& _s_out);
    20     int run();
25  21     int run_old();
    22     int reset();
    23     void makecoeffs();
    24 };
    25
30  26 #endif

```

3.10 tx/shape.cxx

09873553-060401

```

1 // shape.cxx
2 // All rights reserved -- Imec 1998
3 // @(#)shape.cxx 1.7 06/26/98
4
5 #include "shape.h"
6
7 shape::shape(char *name,
8     FB & _i_in,
9     FB & _q_in,
10    FB & _s_out) :base(name)
11 {
12     i_in = _i_in.asSource(this);
13     q_in = _q_in.asSource(this);
14     s_out = _s_out.asSink(this);
15    makecoeffs( ) ;//RRC coeff generation
16    reset();
17 }
18
19 int shape::reset() {
20    //return to initial state
21    while(i_in->getSize() >0)
22        i_in->pop();
23    while(q_in->getSize() >0)
24        q_in->pop();
25
26    return 1;
27 }
28
29 void shape::makecoeffs() {
30    c[0] = 2.725985e-02;
31    c[1] = 2.079339e-01;
32    c[2] = 4.002601e-01;

```

09873553-060401

```

33  c[3] = 5.241213e-01;
34  c[4] = 5.241213e-01;
35  c[5] = 4.002601e-01;
36  c[6] = 2.079339e-01;
5  37  c[7] = 2.725985e-02;
38  }
39
40  int shape::run() {
41      int i ,j;
10 42  #define  NF 8
43  #define  SPS 4
44
45      static double deli[NF] ;
46      static double delq[NF] ;
15 47
48      if((i_in->getSize() <1) ||
49          (q_in->getSize() <1)) {
50          return 0;
51      }
20 52
53      for (j = 1; j <= SPS; j++) {
54
55          for (i = NF-1; i>= 1; i--) {
56              deli[i] = deli[i-1] ;
25 57              delq[i] = delq[i-1] ;
58          }
59          if(j == 1) {
60              deli[0] = Val(i_in->get( ) ) ;
61              delq[0] = Val(q_in->get( ) ) ;
30 62          }
63          else{
64              deli[0] =0;

```

09873553-060404

```
65     delq[0] = 0;
66 }
67
68     double acci = 0;
5 69     double accq = 0;
70     for(i = 0; i < NF; i++) {
71         acci += deli[i]*c[i] ;
72         accq += delq[i]*c[i] ;
73     }
10 74
75     switch (j) {
76         case 1: s_out->put(acci);break;
77         case 2: s_out->put(-accq);break;
78         case 3: s_out->put(-acci);break;
15 79         case 4: s_out->put(accq);break;
80     }
81
82 } //end for j
83
20 84 return 1;
85 }
86
87
88
25 89 // 5.9502848187909857e-03
90 // 7.1303339418111898e-03
91 // -9.0376125958858652e-04
92 // -1.2842591240125096e-02
93 // -1.6560488829370935e-02
30 94 // -3.1424796453581099e-03
95 // 2.2511451978267195e-02
96 // 4.0465840802261004e-02
```

T04090"ESSE/860

97 // 2.8302892670230756e-02
 98 // -1.9056064640367836e-02
 99 // -7.6814040516083981e-02
 100// -9.7464875081018337e-02
 5 101// -3.7506670742425155e-02
 102// 1.1136091774729967e-01
 103// 3.0772091871906165e-01
 104// 4.7526468799142091e-01
 105// 5.4107108989550989e-01
 10 106// 4.7526467788525789e-01
 107// 3.0772090304860350e-01
 108// 1.1136090307335493e-01
 109// -3.7506679314098741e-02
 110// -9.7464876235465986e-02
 15 111// -7.6814036683689066e-02
 112// -1.9056059903703605e-02
 113// 2.8302895170883653e-02
 114// 4.0465840334864417e-02
 115// 2.2511449901436539e-02
 20 116// -3.1424813892788860e-03
 117// -1.6560489169667160e-02
 118// -1.2842590440175973e-02
 119// -9.0376032591496101e-04
 120// 7.1303342199545879e-03
 25 121// 5.9502844100395589e-03
 122

3.11 tx/tuplelize.h

30 1 // tuplelize.h
 2 // All rights reserved -- Imec 1998
 3 // @(#)tuplelize.h 1.4 98/03/31

```

3.12    tx/tuplelize.cxx

25

    1 // tuplelize.cxx
    2 // All rights reserved--  Imec 1998
    3 // @(#)tuplelize.cxx    1.698/03/31
    4
30    5#include    "tuplelize.h"
    6
    7

```

```

8 tuplelize::tuplelize(char *name,
9     FB & _byte,
10    FB & _symb,
11    double &_qpsk) :base(name)
5 12 {
13     byte = _byte.asSource(this);
14     symb = _symb.asSink(this);
15     qpsk = &_qpsk;
16 }
10 17
18//-----
19
20 int tuplelize::reset() {
21     return 1;
15 22 }
23
24 int tuplelize::run() {
25
26     //firing rule
20 27     if(byte->getSize() < 1)
28         return 0;
29
30     //core func
31     int us, msk, sym;
25 32
33     if((int)*qpsk) {
34         us= 2; msk = 0x03;
35     } else{
36         us= 4; msk = 0x0F;
30 37 }
38
39     int tuple = (int)Val(byte->get( ) ) ;

```

```

40
41   for (int k = 1; k<= 8/us;k++) {
42       sym = (tuple >> (8-us) ) & msk;
43       tuple= (tuple << us) & 0xff;
5 44       symb->put(sym);
45   }
46
47   return 1;
48 }
10 49
50
51

```

15 4 Channel Model Code

4.1 chan/fir.h

```

1 // fir.h
20 2 // All rights reserved -- Imec 1998
3 // @(#)fir.h 1.2 03/31/98
4
5 #ifndef FIR_H
6 #define FIR_H
25 7
8 #define NRTAPS 20
9
10 #include "qlib.h"
11
30 12 class fir : public base{
13     FB      *input;
14     FB      *output;

```

0907353-060401
104050-ESSE2860

```

15 double x[NRTAPS] ; // filtertaps: 0,1,...,NRTAPS-1
16 double *t1, *t2, *t3, *t20;
17
18 public:
5 19 fir (char *name,FB & _input,FB & _output,
20 double &_t1, double &_t2,double &_t3, double &_t20)
;
21 int run();
22 int reset();
10 23 };
24
25 #endif

```

4.2 chan/fir.cxx

```

15
1 // fir.cxx
2 // All rights reserved -- Imec 1998
3 // @(#)fir.cxx 1.3 03/31/98
4
20 5#include "fir.h"
6
7 fir::fir(char *name,
8 FB & _input,
9 FB & _output,
25 10 double &_t1, double &_t2,double &_t3, double
&_t20):base(name)
11 {
12 input = _input.asSource(this);
13 output= _output.asSink(this);
30 14
15 for(int i=0; i<NRTAPS; i++) {
16 x [i] =0;

```

T04090" E55E2860

```

17  }
18  t1 = &_t1;
19  t2 = &_t2;
20  t3 = &_t3;
5  21  t20= &_t20;
22  }
23
24  int fir::reset() {
25      //return to initial state
10 26  for(int i=0; i<NRTAPS; i++) {
27      x [i] =0;
28  }
29  return 1;
30  }
15 31
32  int fir::run() {
33      //firing rule
34      if(input->getSize() < 1) {
35          return 0;
20 36  }
37
38      dfix in = input->get();
39
40      int i;
25 41  for (i=NRTAPS-1; i>=1; i--) {
42      x [i] =x[i-1] ;
43  }
44      x[0] =Val(in);
45
30 46  //core func
47      double out = x[0] + x[1]*(*_t1) +x[2]*(*_t2) +
x[3]*(*_t3) + x[20]*(*_t20);

```

09873553-060404

```

48  output->put(out);
49
50  return 1;
51  }
5  52
53

```

4.3 chan/noise.h

```

10  1 // noise.h
    2 // All rights reserved -- Imec 1998
    3 // @(#)noise.h 1.2 03/20/98
    4
    5 #ifndef NOISE_H
15  6 #define NOISE_H
    7
    8 #include "qlib.h"
    9 #include "pseudorn.h"
    10
20  11 class noise: public base{
    12  FB * in;
    13  FB * out;
    14  double *n;
    15  pseudorn RN;
25  16
    17 public:
    18  noise (char *name, FB & in, FB & out, double & _n);
    19  int reset();
    20  int run();
30  21 };
    22
    23 #endif

```

09873553-060401

4.4 chan/noise.cxx

```

1 // noise.cxx
5 2 // All rights reserved -- Imec 1998
3 // @(#)noise.cxx 1.3 03/20/98
4
5#include "noise.h"
6#include <math.h>
10 7
8 noise::noise(char *name,FB & _in,FB & _out, double & _n)
:
    base(name) {
9    in = _in.asSource(this);
15 10 out= _out.asSink(this);
11    n= &_n;
12 }
13
14
20 15 int noise::run() {
16    //firing rule
17    if(in->getSize() < 1) {
18        return 0;
19    }
25 20
21    //core function
22    double U1 = (double) (RN.out())/(double)PRNMAX +
1/(double) PRNMAX;
23    double U2 = (double) (RN.out())/(double)PRNMAX +
30 1/(double) PRNMAX;
24
25    double X = sqrt(-2.*log(U1)) *cos(2.*M_PI*U2);

```

```

4.5  chan/pseudorn.h

10  1 // pseudorn.h
    2 // All rights reserved  --  Imec 1998
    3 // @(#)pseudorn.h  1.2  03/31/98
    4
    5 #ifndef  pseudorn_H
15  6 #define  pseudorn_H
    7
    8 #define  MULT      0x015a4e35L
    9 #define  INCR      1
10 10 #define  PRNMAX  32767    // =2^15-1
20 11
    12 #include  <time.h>
    13
    14 class pseudorn {
    15     long seed;
25 16     unsigned range;
    17 public:
    18     pseudorn() {
    19         range= PRNMAX;
    20         seed= time(0);
30 21     }
    22     pseudorn(unsigned s, unsigned r) {
    23         seed= s;

```

```

24     range= r;
25 }
26 pseudorn(unsigned r) {
27     range= r;
5 28     seed = time(0);
29 }
30 unsigned out(void ) {
31     seed= MULT * seed+ INCR;
32     return ((unsigned) (seed>> 16) & 0x7fff) % range;
10 33 }
34 long getSeed() {return seed;}
35 void setSeed(long s) {seed= s;}
36 };
37
15 38
39#include "qlib.h"
40
41 class pseudorn _gen: publicbase {
42     pseudorn RN;
20 43     FB *out;
44 public:
45     pseudorn_gen(char *name, FB&_out) :
46         base(name),
47         RN(255) {
25 48         out= _out.asSink(this);
49     }
50     int run() {
51         out->put(RN.out( ) ) ;
52         return 1;
30 53     }
54 };
55

```

T04090" E55E2B60


```

13 void observe(double &v,char *name);
14 void obsAttr(Callback2wRet < int,double,int>
cb,int,char
    *name);
5 15 friend interpreter & operator<<(interpreter &p
,sysgen &s);
16 friend interpreter & operator<<(interpreter &p , clk
&c);
17 void go (int argc,char **argv);
10 18 };
19
20
21
22
15 23
24#endif

```

5.2 driver/driver.cxx

```

20 1#include "tcl.h"
2#include <iostream.h>
3
4#define MAKE_WISH
5
25 6#ifdef MAKE_WISH
7#include "tk.h"
8#endif
9
10 // @(#)driver.cxx 1.3 98/03/27
30 11
12#include "qlib.h"
13#include "qtb.h"

```

```

14#include "driver.h"
15#include "Callback2wRet.h"
16
17//-----interpreter OCAP1-related datastructures---
5  -----//
18
19 Callback2wRet<int,double,int>functorlist[100];
20 int numfunctors= 0;
21
10 22 int graphLines= 0;
23
24 FBQ (trace0);
25 FBQ (trace1);
26 FBQ (trace2);
15 27 FBQ (trace3);
28 FBQ (trace4);
29 FBQ (trace5);
30 FBQ (trace6);
31 FBQ (trace7);
20 32 dfbfix *traces[8] ;
33 dfbfix *tracedqueue[8] ;
34
35 Tcl_HashTable queue_hash;
36
25 37#define IF_SUFFIX(A) if((strlen(r->name()) >
strlen(A)) &&
(!strcmp(r->name() +strlen(r->name()) - strlen(A) ,A)))
38
39
30 40 void create_queue_hash() {
41 Tcl_InitHashTable(&queue_hash,TCL_STRING_KEYS);
42

```

```

43     dfbfix *r;
44     for(r = listOfFB; r; r=r->nextFB()) {
45         int present;
46         IF_SUFFIX("_mark")
5 47     continue;
48         IF_SUFFIX("_stim")
49     continue;
50         Tcl_SetHashValue(Tcl_CreateHashEntry(&queue_hash,r-
        >name(),&present) ,(char *) r);
10 51     }
52 }
53
54 // next are created by the interpreter object itself
55 Tcl_HashTable sched_hash;
15 56 Tcl_HashTable doubles_hash;
57 Tcl_HashTable attr_hashfunc;
58 Tcl_HashTable attr_hashint;
59
60 clk* glbClk;// global (single)clock
20 61
62//-----
---//
63 int  ListQueue(ClientData,  Tcl_Interp*interp,intargc,
char
25     **argv) {
64     if((argc > 2)) {
65         interp->result= "Usage:_listq?queue?\n";
66         return  TCL_ERROR;
67     }
30 68
69     char *match = 0;
70     if(argc == 2) {

```

```

71     match = argv[1] ;
72 }
73
74     if(match) {
5 75                                     Tcl_HashEntry*p=
Tcl_FindHashEntry(&queue_hash,argv[1] ) ;
76         if(p != 0) {
77             Tcl_AppendElement(interp,                (d(fbfix*)
Tcl_GetHashValue(p))-
10             >name( ) ) ;
78     }
79 } else{
80     Tcl_HashSearch k;
81                                     Tcl_HashEntry    *p=          Tcl
15 _FirstHashEntry(&queue_hash,k&);
82     while (p != 0) {
83         Tcl_AppendElement(interp, ((dfbfix *)
Tcl_GetHashValue(p))->name( ) ) ;
84         p = Tcl_NextHashEntry(&k);
20 85     }
86 }
87
88     return TCL_OK;
89 }
25 90
91//-----
---//
92 int  GetQueue(ClientData , Tcl _Interp * interp,int
argc,char
30     **argv) {
93     if(argc != 2) {
94         interp->result= "Usage:_getq_queue\n";

```

09873553-060404

```

95     return  TCL_ERROR;
96 }
97
98                                     Tcl_HashEntry*p           =
5  Tcl_FindHashEntry(&queue_hash,argv[1] ) ;
99     if(p != 0) {
100         dfbfix *q = (dfbfix *) Tcl_GetHashValue(p);
101         while (q->getSize()) {
102             strstream N;
10  103         N << Val(q->get()) <<ends;
104         Tcl_AppendElement(interp,N.str( ) ) ;
105     }
106 }
107
15 108 return  TCL_OK;
109}
110
111 //-----
----//
20 112 intPutQueue(ClientData ,  Tcl _Interp *  interp,int
    argc,char
        **argv) {
113     if(argc != 3) {
114         interp->result= "Usage:_putq_queue_value\n";
25 115     return  TCL_ERROR;
116 }
117
118                                     Tcl_HashEntry           *p           =
Tcl_FindHashEntry(&queue_hash,argv[1] ) ;
30 119 if(p != 0) {
120     double v;
121     sscanf(argv[2] ,"%lf",v&);

```

```

122     dfbfix *q = (dfbfix *) Tcl_GetHashValue(p);
123     q->put(v);
124 }
125
5 126 return  TCL_OK;
127}
128
129 //-----
----//
10 130 int      TraceQueue(ClientData,      Tcl      _Interp      *
      interp,intargc, char
          **argv) {
131
132     if((argc != 1)&&(argc!= 3 )) {
15 133                                     interp->result=
      "Usage:_traceq_?traceq_queueuname?\n";
134     return  TCL_ERROR;
135 }
136
20 137 if(argc == 1) {
138     intk;
139     for(k=0; k<8; k++) {
140         strstream N;
141         N << traces[k]->name() <<"_";
25 142         if(tracedqueue[k] !=0)
143             N << tracedqueue[k]->name();
144             N << ends;
145             Tcl_AppendElement(interp,N.str( ) ) ;
146     }
30 147 } else{
148                                     Tcl_HashEntry      *p=
      Tcl_FindHashEntry(&queue_hash,argv[2] );

```

```

149     dfbfix *q = 0;
150     if(p != 0) {
151         q = (dfbfix *) Tcl_GetHashValue(p);
152     } else {
5 153         return TCL_OK;
154     }
155
156     int num;
157     for (num=0; num < 8; num++) {
10 158         if(!strcmp(argv[1] ,traces[num]->name()))
159             break;
160     }
161
162     if(num > 7)
15 163         return TCL_OK;
164
165     if(tracedqueue[num] !=0) {
166         tracedqueue[num]->asDup(nilFB);
167     }
20 168
169     tracedqueue[num] =q;
170     q->asDup(*traces[num] ) ;
171 }
172 return TCL_OK;
25 173}
174
175 //-----
---//
176 intReadQueue(ClientData , Tcl_Interp * interp,intargc,
30 char
    **argv) {
177     if(argc != 2) {

```

```

178     interp->result= "Usage:_readq_queue\n";
179     return  TCL_ERROR;
180 }
181
5 182         Tcl_HashEntry      *p      =
Tcl_FindHashEntry(&queue_hash,argv[1] );
183     if(p != 0) {
184         dfbfix *q = (dfbfix *) Tcl_GetHashValue(p);
185         int k;
10 186         for(k=0; k<q->getSize( ); k++) {
187             strstream N;
188             N << Val ((*q) [k]) << ends;
189             Tcl_AppendElement(interp,N.str( ) );
190         }
15 191     }
192
193     return  TCL_OK;
194 }
195
20 196 //-----
-//
197 int PlotQueue(ClientData, Tcl_Interp * interp,intargc,
char
    **argv) {
25 198     inti;
199     if(argc < 2) {
200         interp->result= "Usage:_plotq_queue?...?\n";
201         return  TCL_ERROR;
202     }
30 203
204     char *f = tmpnam(NULL);
205     ofstream PLOTBUF(f);

```

```

206
207 //----- headers
208 PLOTBUF << "TitleText: _";
209 for(i=1; i<argc; i++) {
5 210                                Tcl_HashEntry          *p=
    Tcl_FindHashEntry(&queue_hash, argv[i]);
211     if(p != 0)
212         PLOTBUF << ((dfbfix *) Tcl_GetHashValue(p))->name()
    << "_";
10 213 }
214 PLOTBUF << "\n";
215
216 PLOTBUF << "BackGround: _Black\n";
217 PLOTBUF << "ForeGround: _White\n";
15 218 PLOTBUF << "XUnitText: __Sample\n";
219 PLOTBUF << "BoundingBox: ___True\n";
220 PLOTBUF << "0.Color: ____Yellow\n";
221 PLOTBUF << "LabelFont: __-adobe-helvetica-*--r-*--16-*--
    *--*--*--
20     *--*\n";
222 PLOTBUF << "Markers: ____True\n";
223 if( !graphLines)
224     PLOTBUF << "NoLines: ____True\n";
225
25 226 //----- data
227 for(i=1; i<argc; i++) {
228     PLOTBUF << "\n";
229                                Tcl_HashEntry          *p=
    Tcl_FindHashEntry(&queue_hash, argv[i]);
30 230     if(p != 0) {
231         int j;

```

T04090" E5E2B60

```

232     PLOTBUF << "\"" << (( dfbfix*) Tcl_GetHashValue(p)) -
        >name()
        << "\"\n";
233     for    (j=0;    j<((dfbfix*)    Tcl_GetHashValue(p)) -
5         >getSize();
        j++) {
234         PLOTBUF    <<    j    <<    "_" <<    ((dfbfix
            *)Tcl_GetHashValue(p)) -
            >getIndex(j) << "\n";
10 235     }
236 }
237 }
238 PLOTBUF.close();
239
15 240 system(strapp(strapp("xgraph_",f), "_&"));
241 return  TCL_OK;
242}
243
244 //-----
20 ----//
245 int ScatQueue(ClientData, Tcl _Interp * interp,intargc,
char
    **argv) {
246     int i;
25 247     if(argc != 3) {
248         interp->result= "Usage:_scatq_queuex_queuey\n";
249         return  TCL_ERROR;
250     }
251
30 252     ofstream PLOTBUF(".plotbuf");
253
254 //----- headers

```

0907353-050401

```

255 PLOTBUF << "TitleText: _";
256 for(i=1; i<argc; i++) {
257                                     Tcl_HashEntry      *p=
Tcl_FindHashEntry(&queue_hash,argv[i]);
5 258     if(p != 0)
259         PLOTBUF << ((dfbfix *) Tcl_GetHashValue(p))->name()
<< "_";
260 }
261 PLOTBUF << "\n";
10 262
263 PLOTBUF << "BackGround:_Black\n";
264 PLOTBUF << "ForeGround:_White\n";
265 PLOTBUF << "XUnitText: __Sample\n";
266 PLOTBUF << "BoundingBox: __True\n";
15 267 PLOTBUF << "0.Color: __Yellow\n";
268 PLOTBUF << "LabelFont: __-adobe-helvetica-*r-*-16-*
*-*-*-
    *-*\n";
269 PLOTBUF << "Markers: __True\n";
20 270 if( !graphLines)
271     PLOTBUF << "NoLines: __True\n";
272
273 //----- data
274 PLOTBUF << "\n";
25 275             Tcl_HashEntry      *      p1      =
Tcl_FindHashEntry(&queue_hash,argv[1]) ;
276             Tcl_HashEntry      *      p2      =
Tcl_FindHashEntry(&queue_hash,argv[2]) ;
277 if((p1 != 0)&&(p2 != 0)) {
30 278     int j;
279         int max = ((dfbfix *) Tcl_GetHashValue(p1))-
>getSize();

```

```

280      if(((dfbfix *) Tcl_GetHashValue(p2))->getSize()
<max) {
281      max = (((dfbfix *) Tcl_GetHashValue(p2))->getSize(
) ) ;
5 282  }
283  for(j=0; j<max; j++) {
284      PLOTBUF << ((dfbfix *) Tcl_GetHashValue(p1))-
>getIndex(j)
285      << " "
10 286      << ((dfbfix *) Tcl_GetHashValue(p2))-
>getIndex(j)<<"\n";
287  }
288  }
289  PLOTBUF.close();
15 290
291  system("xgraph_.plotbuf_&");
292  return  TCL_OK;
293}
294
20 295 //-----
---//
296 int StatQueue(ClientData, Tcl _Interp*interp,intargc,
char
    **argv) {
25 297  if(argc > 2) {
298      interp->result= "Usage:_statq_?queue?\n";
299      return  TCL_ERROR;
300  }
301
30 302  char *match = 0;
303  if(argc == 2) {
304      match = argv[1] ;

```

```

305 }
306
307 dfbfix *r;
308 for(r = listOfFB; r; r= r->nextFB()) {
5 309     IF_SUFFIX("_mark")
310         continue;
311     IF_SUFFIX("_stim")
312         continue;
313     if( !match || (s!trcmp(r->name( ),match))) {
10 314         strstreamN;
315         N << *r << ends;
316         Tcl_AppendElement(interp,N.str( ) ) ;
317     }
318
15 319 }
320
321 return  TCL_OK;
322}
323
20 324 //-----
----//
325 int ClearQueue(ClientData, Tcl _Interp*interp,intargc,
char
    **) {
25 326 if(argc > 1) {
327     interp->result= "Usage:_clearq\n";
328     return  TCL_ERROR;
329 }
330
30 331 dfbfix *r;
332 for(r = listOfFB; r; r= r->nextFB())
333     while (r->getSize() >0 )

```

```

334     r->pop();
335
336     return  TCL_OK;
337 }
5 338
339 //-----
----//
340     int      ListSchedule(ClientData,Tcl      _Interp*interp,
intargc, char
10     **argv) {
341     if((argc > 2)) {
342         interp->result= "Usage:_lists_?schedule?\n";
343         return  TCL_ERROR;
344     }
15 345
346     char *match = 0;
347     if(argc == 2) {
348         match  = argv[1] ;
349     }
20 350
351     if(match) {
352         Tcl_HashEntry  *p=      Tcl_FindHashEntry(&sched
_hash,argv[1]);
353         if(p != 0) {
25 354             Tcl_AppendElement(interp, ((sysgen *)
Tcl_GetHashValue(p))->getname( ));
355     }
356 } else{
357     Tcl_HashSearchk;
30 358     Tcl_HashEntry  * p=      Tcl _FirstHashEntry(&sched
_hash,k&);
359     while (p != 0) {

```

```

360     Tcl_AppendElement(interp,                ((sysgen*)
        Tcl_GetHashValue(p)) -
        >getname( ));
361     p = Tcl_NextHashEntry(&k);
5 362 }
363 }
364
365 return TCL_OK;
366}
10 367
368 //-----
--//
369 int RunSchedule(ClientData, Tcl _Interp*interp,intargc,
char
15     **argv) {
370
371     if((argc != 3)) {
372                                     interp->result=
        "Usage:_runs_schedule_clock_iterations\n";
20 373     return TCL_ERROR;
374 }
375
376     Tcl_HashEntry *p = Tcl_FindHashEntry(&sched
        _hash,argv[1] ) ;
25 377     if(p != 0) {
378         unsigned v;
379         sscanf(argv[2] ,"%d",&v);
380         sysgen *sys = (sysgen *) Tcl_GetHashValue(p);
381
30 382     while (v--)
383         sys->run(*glbClk);
384

```

09873553.050401

```

385 }
386
387 return TCL_OK;
388}
5 389
390 //-----
---//
391 int VhdlSchedule(ClientData,Tcl_Interp *interp,
intargc, char
10 **argv) {
392
393 if((argc != 2)) {
394     interp->result= "Usage:_vhdl_schedule\n";
395     return TCL_ERROR;
15 396 }
397
398     Tcl_HashEntry*p     =     Tcl_FindHashEntry(&sched
_hash,argv[1] ) ;
399 if(p != 0) {
20 400     sysgen *sys = (sysgen *) Tcl_GetHashValue(p);
401     sys->vhdllook();
402 }
403
404 return TCL_OK;
25 405}
406
407 //-----
----//
408 int ListParameter(ClientData,Tcl_Interp*interp,int
30 argc, char
**argv) {
409 if((argc > 2)) {

```

T04030" E55E2860

```

410     interp->result= "Usage:_listp_?parameter?\n";
411     return  TCL_ERROR;
412 }
413
5 414 char *match = 0;
415 if(argc == 2) {
416     match = argv[1] ;
417 }
418
10 419 if(match) {
420                                     Tcl_HashEntry      *p=
Tcl_FindHashEntry(&doubles_hash,argv[1]);
421     if(p != 0) {
422
15  Tcl_AppendElement(interp,Tcl_GetHashKey(&doubles_hash,p));
423     }
424 } else{
425     Tcl_HashSearchk;
426                                     Tcl_HashEntry      *p=
20  Tcl_FirstHashEntry(&doubles_hash,k&);
427     while (p != 0) {
428
Tcl_AppendElement(interp,Tcl_GetHashKey(&doubles_hash,p));
429         p = Tcl_NextHashEntry(&k);
25 430     }
431 }
432
433 return  TCL_OK;
434}
30 435 //-----
---//

```

```

436 int SetParameter(ClientData,Tcl _Interp *interp,
intargc, char
    **argv) {
437     if((argc != 3)) {
5 438         interp->result= "Usage:_setp_parameter_value\n";
439         return TCL_ERROR;
440     }
441
442         Tcl_HashEntry      *p      =
10 Tcl_FindHashEntry(&doubles_hash,argv[1]);
443     if(p != 0) {
444         double v;
445         sscanf(argv[2] ,"%lf",&v);
446         double *q = (double *) Tcl_GetHashValue(p);
15 447         *q = v;
448     }
449
450     return TCL_OK;
451 }
20 452
453 //-----
---//
454 int ReadParameter(ClientData,Tcl_Interp *interp,int
argc, char
25     **argv) {
455     if(argc != 2) {
456         interp->result= "Usage:_readp_parameter\n";
457         return TCL_ERROR;
458     }
30 459
460         Tcl_HashEntry      *p      =
Tcl_FindHashEntry(&doubles_hash,argv[1]);

```

```

461  if(p != 0) {
462      double *q = (double *) Tcl_GetHashValue(p);
463      strstreamN;
464      N << *q << ends;
5  465      Tcl_AppendElement(interp,N.str( ) ) ;
466  }
467
468  return  TCL_OK;
469}
10 470
471 //-----
---//
472 int  ListAttribute(ClientData,Tcl _Interp *interp,int
argc,char
15      **argv) {
473  if((argc > 2)) {
474      interp->result= "Usage:_lista_?attribute?\n";
475      return  TCL_ERROR;
476  }
20 477
478  char *match = 0;
479  if(argc == 2) {
480      match  = argv[1] ;
481  }
25 482
483  if(match) {
484
485      Tcl_HashEntry
486      *p=
487      Tcl_FindHashEntry(&attr_hashfunc,argv[1]);
488      if(p != 0) {
30 489
490      Tcl_AppendElement(interp,Tcl_GetHashKey(&attr_hashfunc,p));
491  }

```

FD04030"25557360

```

488 } else{
489     Tcl_HashSearchk;
490     Tcl_HashEntry *p= Tcl _FirstHashEntry(&attr
    _hashfunc,&k);
5 491     while (p != 0) {
492
Tcl_AppendElement(interp,Tcl_GetHashKey(&attr_hashfunc,p));
493     p = Tcl_NextHashEntry(&k);
494     }
10 495 }
496
497 return  TCL_OK;
498}
499
15 500 //-----
    ---//
501     int      SetAttribute(ClientData,Tcl_Interp      *interp,
intargc, char
        **argv) {
20 502     if((argc != 3)) {
503         interp->result= "Usage:_seta_attribute_value\n";
504         return  TCL_ERROR;
505     }
506
25 507         Tcl_HashEntry                *pf=
Tcl_FindHashEntry(&attr_hashfunc,argv[1]);
508         Tcl_HashEntry                *pi=
Tcl_FindHashEntry(&attr_hashint,argv[1]);
509
30 510     if(pf != 0) {
511         int n = (int) Tcl_GetHashValue(pi);
512         double v;

```

T04090"ESSEZ860

```

513     sscanf(argv[2] ,"%lf",&v);
514     //call member func
515     functorlist[(int)Tcl_GetHashValue(pf)](n,v);
516 }
5 517
518     return  TCL_OK;
519}
520
521 //-----
10 -----//
522     int      SetLineStyle(ClientData,Tcl_Interp      *interp,
intargc, char
        **argv) {
523     if((argc != 2)) {
15 524         interp->result= "Usage:_lines_1/0\n";
525         return  TCL_ERROR;
526 }
527
528     int v;
20 529     sscanf(argv[1] ,"%d", &v);
530     if(v != 0)
531         graphLines= 1;
532     else
533         graphLines= 0;
25 534
535     return  TCL_OK;
536}
537
538 //-----
30 //
539 int Testbenches(ClientData, Tcl_Interp *interp,intargc,
char

```

```

    **argv) {
540  if((argc != 2)) {
541      interp->result= "Usage:_testb_1/0\n";
542      return  TCL_ERROR;
5  543  }
544
545  int v;
546  sscanf(argv[1] ,"%d", &v);
547  if(v != 0)
10 548      qtb::glbDisableTestbenches=0;
549  else
550      qtb::glbDisableTestbenches=1;
551
552  return  TCL_OK;
15 553}
554
555  //-----
  --//
556  int OCAPIShelp(ClientData, Tcl_Interp *interp,int, char
20  **) {
557      Tcl_AppendElement(interp,"Available_OCAPI-
        related_commands:\n");
558
559      Tcl_AppendElement(interp,"listq ?queue_name?_____
25  _____
        List_queue(s)\n");
559  Tcl_AppendElement(interp,"statq ?queue_name?_____
        _____
        Queue(s)_statistics\n");
30 560
      Tcl_AppendElement(interp,"readq_queue_name_____
      _____

```

```

        Return _queue_contents\n");
561
Tcl_AppendElement(interp,"getq__queue_name_____
—
5      Return _and_empty_queue_contents\n");
562
Tcl_AppendElement(interp,"putq__queue_name_value_____
—
        Add_value_to_queue\n");
10 563  Tcl_AppendElement(interp,"plotq_queue_name?...?_____
        _____
        Display_queue_contents_graphically\n");
564  Tcl_AppendElement(interp,"scatq_queue_name_queue_name_
        _____
15      Display_queue_contents_graphically\n");
565  Tcl_AppendElement(interp,"traceq ?tracenum_queue_name?
        _____
        Trace_writes_to_the_queue\n");
566  Tcl_AppendElement(interp,"clearq_____
20      _____
        Clears_contents_of_queues\n");
567
Tcl_AppendElement(interp,"lists ?schedule_name?_____
—
25      List_available_schedules\n");
568
Tcl_AppendElement(interp,"runs_schedule_name_iter_____
—
        Runs_iter_iterations_of_a_schedule\n");
30 569
Tcl_AppendElement(interp,"vhdl_s_schedule_name_____
—

```

```

        Dumps_VHDL_code_for_a_schedule\n");
570 Tcl_AppendElement(interp,"listp_?parameter_name?_____
_____
        List_parameters\n");
5 571 Tcl_AppendElement(interp,"setp_parameter_name_value_____
_____
        List_parameters\n");
572 Tcl_AppendElement(interp,"readp_parameter_name_____
_____
10      Return _Variable_Contents\n");
573
Tcl_AppendElement(interp,"lista_?attribute_name?_____
_____
        List_attributes\n");
15 573 Tcl_AppendElement(interp,"seta_attribute_name_value_____
_____
        Set_attribute\n");
574 Tcl_AppendElement(interp,"lines_1/0_____
_____
20      Turns_on/off_line_drawing\n");
575 Tcl_AppendElement(interp,"testb_1/0_____
_____
        Disables_test_benches\n");
577 return  TCL_OK;
25 578}
579
580 //-----
//
581 // intialization and command definition
30 582 int AppInit(Tcl_Interp *interp) {
583
584     if( Tcl_Init(interp) ==TCL_ERROR)

```

```

585     return  TCL_ERROR;
586
587#ifdef MAKE_WISH
588     if (Tk_Init(interp) ==TCL_ERROR)
5 589     return  TCL_ERROR;
590#endif
591
592     create_queue _hash();
593
10 594     Tcl_CreateCommand(interp,"listq",ListQueue,      NULL,
        NULL);
595     Tcl_CreateCommand(interp,"statq",StatQueue,      NULL,
        NULL);
596     Tcl_CreateCommand(interp,"readq",ReadQueue,      NULL,
15 NULL);
597     Tcl_CreateCommand(interp,"getq", GetQueue,      NULL,
        NULL);
598     Tcl_CreateCommand(interp,"putq", PutQueue,      NULL,
        NULL);
20 599     Tcl_CreateCommand(interp,"plotq",PlotQueue,      NULL,
        NULL);
600     Tcl_CreateCommand(interp,"scatq",ScatQueue,      NULL,
        NULL);
601     Tcl_CreateCommand(interp,"traceq",TraceQueue,    NULL,
25 NULL);
602     Tcl_CreateCommand(interp,"clearq",ClearQueue,    NULL,
        NULL);
603
604     Tcl_CreateCommand(interp,"lists",ListSchedule,  NULL,
30 NULL);
605     Tcl_CreateCommand(interp,"runs", RunSchedule,    NULL,
        NULL);

```

```

606 Tcl_CreateCommand(interp,"vhdlS",VhdlSchedule, NULL,
NULL);
607
608 Tcl_CreateCommand(interp,"listp",ListParameter,NULL,
5 NULL);
609 Tcl_CreateCommand(interp,"setp", SetParameter, NULL,
NULL);
610 Tcl_CreateCommand(interp,"readp",ReadParameter,NULL,
NULL);
10 611
612 Tcl_CreateCommand(interp,"lista",ListAttribute,NULL,
NULL);
613 Tcl_CreateCommand(interp,"seta", SetAttribute, NULL,
NULL);
15 614
615 Tcl_CreateCommand(interp,"testb",Testbenches, NULL,
NULL);
616 Tcl_CreateCommand(interp,"lines",SetLineStyle, NULL,
NULL);
20 617 Tcl_CreateCommand(interp,"OCAPI",OCAPIHelp, NULL,
NULL);
618
619 return TCL_OK;
620}
25 621
622
623 //-----
-----//
624
30 625 interpreter & operator<<( interpreter &p, sysgen &s ) {
626 p.add(s);
627 return p;

```

```

628}
629
630 interpreter & operator<<( interpreter &p, clk &ck) {
631     glbClk= &ck;
5 632     return p;
633}
634
635 void interpreter::observe(double &v,char *name) {
636     int present;
10 637     Tcl_SetHashValue(Tcl_CreateHashEntry(&doubles_hash,na
        me,
            &present),(char*) &v);
638}
639
15 640                                     void
        interpreter::obsAttr(Callback2wRet<int,double,int>f,int
            n, char *name) {
641     int present;
642     functorlist [numfunctors++]=f;
20 643     if(numfunctors>100) {
644         cerr<< "***_ERROR:_max_num_functors_exceeded\n";
645         exit(0);
646     }
647     Tcl_SetHashValue(Tcl_CreateHashEntry(&attr_hashfunc,n
25     ame,
        &present),(char *)numfunctors-1);
648     Tcl_SetHashValue(Tcl_CreateHashEntry(&attr_hashint,na
        me,
            &present),(char *)n);
30 649}
650
651 interpreter::interpreter() {

```

```

652 Tcl _InitHashTable(&sched_hash,TCL_STRING_KEYS);
653 Tcl _InitHashTable(&doubles_hash,TCL_STRING_KEYS);
654 Tcl _InitHashTable(&attr_hashfunc,TCL_STRING_KEYS);
655 Tcl _InitHashTable(&attr_hashhint,TCL_STRING_KEYS);
5 656 numfunctors= 0;
657 traces[0] = &trace0; tracedqueue[0] = &nilFB;
658 traces[1] = &trace1; tracedqueue[1] = &nilFB;
659 traces[2] = &trace2; tracedqueue[2] = &nilFB;
660 traces[3] = &trace3; tracedqueue[3] = &nilFB;
10 661 traces[4] = &trace4; tracedqueue[4] = &nilFB;
662 traces[5] = &trace5; tracedqueue[5] = &nilFB;
663 traces[6] = &trace6; tracedqueue[6] = &nilFB;
664 traces[7] = &trace7; tracedqueue[7] = &nilFB;
665}
15 666
667 void interpreter::add(sysgen &s) {
668 int present;
669 Tcl_SetHashValue(Tcl_CreateHashEntry(&sched_hash,s.get
    name(),
20    &present),(char *) &s);
670}
671
672 void interpreter::go(intargc,char **argv) {
673#ifdef MAKE_WISH
25 674 Tk_Main(argc,argv, AppInit);
675#else
676 Tcl_Main(argc,argv, AppInit);
677#endif
678
30 679}
680
681

```

5.3 driver/sys.cxx

```

1 // sys.cxx
5 2 // All rights reserved -- Imec 1998
3 // @(#)sys.cxx 1.5 98/03/31
4
5#include "qlib.h"
6#include "hshake.h"
10 7#include "driver.h"
8#include "sys.h"
9
10 double glbQPSK      = 0. ; // for QPSK -> 1
11 double glbDiff      = 0. ; // for Diff Enc-> 1
15 12 double glbT1      = 0. ;
13 double glbT2      = 0. ;
14 double glbT3      = 0. ;
15 double glbT20      = 0. ;
16 double glbNoiseLevel= 0. ;
20 17 double glbADWbits  = 10. ;
18 double glbADLbits  = 6. ;
19
20 int main(int argc, char **argv) {
21
25 22 LOADTYPES( ../rx/TYPEDEF);
23
24 //global synchronous clock
25 clkck;
26
30 27 //-----
28 //
29 //byte source

```

```

30  //
31  FBQ( tx_bytes ) ;
32  pseudorn _gen GEN_RN("gen_rx",
33      tx_bytes);
5  34
35  sysgen GEN("GEN");
36  GEN << GEN_RN;
37
38  //-----
10 -----
39  //
40  //transmitter
41  //
42  FBQ( tx_rnd_bytes) ;
15 43  FBQ(tx_symbols ) ;
44  FBQ( tx_dif_symbols);
45  FBQ( tx_ival ) ;
46  FBQ( tx_qval ) ;
47  FBQ( tx_sig ) ;
20 48  FBQ( tx_sig_quant) ;
49
50  rnd      TX_RND  ("tx_derandm",
51      tx_bytes,
52      tx_rnd_bytes);
25 53  tuplelize TX_TUPLE("tx_tuple",
54      tx_rnd_bytes,
55      tx_symbols,
56      glbQPSK);
57  diffenc  TX_DIFFE("tx_diffe",
30 58      tx_symbols,
59      tx_dif_symbols,
60      glbQPSK,

```

T040910"E55E2B50

```

61          glbDiff);
62  map      TX_MAP  ("tx_map",
63          tx_dif_symbols,
64          tx_ival,
5  65          tx_qval,
66          glbQPSK);
67  shape    TX_SHAPE("tx_shape",
68          tx_ival,
69          tx_qval,
10 70          tx_sig);
71  ad       TX_AD   ("tx_ad",
72          tx_sig,
73          tx_sig_quant,
74          glbADWbits,
15 75          glbADLbits);
76
77  sysgen TX("TX");
78  TX << TX_RND;
79  TX << TX_TUPLE;
20 80  TX << TX_DIFFE;
81  TX << TX_MAP;
82  TX << TX_SHAPE;
83  TX << TX_AD;
84
25 85  //-----
-----
86  //
87  //channel
88  //
30 89  FBQ( chan_isi);
90  FBQ(chan_out);
91

```

FD4030-ESS2860

```

92  fir      CHAN_FIR("chan_fir",
93              tx_sig_quant,
94              chan_isi,
95              glbT1,
5  96              glbT2,
97              glbT3,
98              glbT20);
99
100 noise     CHAN_NOISE("chan_noise",
10  101         chan_isi,
102         chan_out,
103         glbNoiseLevel);
104
105 sysgen CHAN("CHAN");
15  106 CHAN << CHAN_FIR;
107 CHAN << CHAN_NOISE;
108
109  //-------
----
20  110  //
111  //receiver
112  //
113  FBQ(rx_constel_mode);
114  FBQ(rx_lms_i);
25  115  FBQ(rx_lms_q);
116  FBQ(rx_syntype);
117  lmsff RX_LMSFF("lmsff",
118              ck,
119              rx_constel_mode,
30  120              chan_out,
121
122              rx_lms_i,
```

F04090"ESE/850

```

123         rx_lms_q,
124         rx_symttype
125     );
126
5 127 RX_LMSFF.setAttr (lmsff::FWLENGTH, 8      ) ;
128 RX_LMSFF.setAttr (lmsff::STEP_PAR, 4      ) ;
129 RX_LMSFF.setAttr (lmsff::P0,          -0.2*2.0);
130 RX_LMSFF.setAttr (lmsff::P1,          0.7*2.0);
131 RX_LMSFF.setAttr (lmsff::P2,          0.7*2.0);
10 132 RX_LMSFF.setAttr (lmsff::P3,          -0.2*2.0);
133 RX_LMSFF.setAttr (lmsff::REF,          3.0    ) ;
134 RX_LMSFF.setAttr (lmsff::INIT          ) ;
135 RX_LMSFF.setAttr (lmsff::SPS_PAR, 4      ) ;
136
15 137 FBQ(rx_symttype_at);
138 FBQ( rx_diff_mode);
139 FBQ(rx_symbol);
140 demap RX_DEMAP("demap",
141         ck,
20 142         rx_symttype,
143         rx_diff_mode,
144         rx_lms_i,
145         rx_lms_q,
146
25 147         rx_symttype_at,
148         rx_symbol
149     ) ;
150
151 RX_DEMAP.setAttr (demap::DEBUGMODE,0);
30 152 RX_DEMAP.setAttr (demap::REF,3.0);
153
154 FBQ( rx_syncro);

```

T04090" ESE2860

```

155 FBQ( rx_byte _rnd);
156 detupleRX_DETUPLE("detuple",
157         ck,
158         rx_symbol,
5 159         rx_symttype _at,
160
161         rx_byte _rnd,
162         rx_syncro
163     ) ;
10 164
165 RX_DETUPLE.setAttr (detuple:D:EBUGMODE,0);
166
167 FBQ( rx_byte_out);
168 FBQ( rx_sync_out);
15 169 derandRX_DERAND("derand",
170         ck,
171         rx_byte_rnd,
172         rx_syncro,
173
20 174         rx_byte_out,
175         rx_sync_out
176     ) ;
177
178 RX_DERAND.setAttr (derand::DEBUGMODE,0    ) ;
25 179 RX_DERAND.setAttr (derand::SEED,        0x3f);
180 RX_DERAND.setAttr (derand::BYPASS,    0    ) ;
181
182 sysgen RX_UT("RX_UT");
183 RX_UT << RX_LMSFF;
30 184 RX_UT << RX_DEMAP;
185 RX_UT << RX_DETUPLE;
186 RX_UT << RX_DERAND;

```

090873553-050404

```

187
188 //-----clocktrue definition
189 handshake hsk1("h1",ck);
190 handshake hsk2("h2",ck);
5 191 handshake hsk3("h3",ck);
192
193 rx_lms_i.sethandshake(hsk1);
194 rx_symbol.sethandshake(hsk2);
195 rx_byte_rnd.sethandshake(hsk3);
10 196
197 RX_LMSFF .define();
198 RX_DEMAP .define();
199 RX_DETUPLE.define();
200 RX_DERAND .define();
15 201
202 sysgen RX_TI("RX_TI");
203 RX_TI << RX_LMSFF .fsm();
204 RX_TI << RX_DEMAP .fsm();
205 RX_TI << RX_DETUPLE.fsm();
20 206 RX_TI << RX_DERAND .fsm();
207
208 //--- iopad definition
209 dfix T_byte(0,8,0);
210 RX_TI.inpad(chan_out, T(T_sample_lms));
25 211 RX_TI.inpad(rx_diff_mode, T_bit);
212 RX_TI.inpad(rx_constel_mode,T_bit);
213 RX_TI.outpad(rx_byte_out, T_byte);
214 RX_TI.outpad(rx_sync_out, T_bit);
215
30 216 //--- insert clear registersstate
217 RX_LMSFF .fsm().clear_regs();
218 RX_DEMAP .fsm().clear_regs();

```

T04090"ESSE2860

```

219 RX_DETUPLE.fsm().clear_regs();
220 RX_DERAND .fsm().clear_regs();
221
222 //---- testbench generator for this clocktrue model
5 223 RX_LMSFF .fsm().tb_enable();
224 RX_DEMAP .fsm().tb_enable();
225 RX_DETUPLE.fsm().tb_enable();
226 RX_DERAND .fsm().tb_enable();
227 RX_TI .tb_enable();
10 228 RX_TI .generate();
229
230 //-----
-----
231 //
15 232 //interpreter
233 //
234 interpreter P;
235 P << GEN;
236 P << TX;
20 237 P << CHAN;
238 P << RX_UT;
239 P << RX_TI;
240 P << ck;
241
25 242 P.observe(glbQPSK , "QPSK" ) ;
243 P.observe(glbT1 , "T1" ) ;
244 P.observe(glbT2 , "T2" ) ;
245 P.observe(glbT3 , "T3" ) ;
246 P.observe(glbT20 , "T20" ) ;
30 247 P.observe(glbNoiseLevel, "NoiseLevel");
248 P.observe(glbADWbits , "ADWbits" ) ;
249 P.observe(glbADLbits , "ADLbits" ) ;

```

```

250 P.observe(glbDiff      ,"DiffEnc"    ) ;
251
252 P.ATTRIBUTE(lmsff ,RX_LMSFF ,FWLENGTH ,lmsff_fwlen) ;
253 P.ATTRIBUTE(lmsff ,RX_LMSFF ,STEP_PAR ,lmsff_step) ;
5 254 P.ATTRIBUTE(lmsff ,RX_LMSFF ,P0      ,lmsff_p0  ) ;
255 P.ATTRIBUTE(lmsff ,RX_LMSFF ,P1      ,lmsff_p1  ) ;
256 P.ATTRIBUTE(lmsff ,RX_LMSFF ,P2      ,lmsff_p2  ) ;
257 P.ATTRIBUTE(lmsff ,RX_LMSFF ,P3      ,lmsff_p3  ) ;
258 P.ATTRIBUTE(lmsff ,RX_LMSFF ,INIT    ,lmsff_init) ;
10 259 P.ATTRIBUTE(derand,RX_DERAND ,SEED   ,derand_seed) ;
260 P.ATTRIBUTE(derand,RX_DERAND ,BYPASS  ,derand_bypass) ;
261
262 P.go(argc,argv) ;
263
15 264}
265

```

5.4 driver/sys.h

```

20 1#ifndef  SYS_H
21 2#define  SYS_H
22 3
23 4
24 5 // @(#)sys.h  1.3 98/03/27
25 6
26 7#include "Callback2wRet.h"
27 8
28 9#define ATTRIBUTE(CLASS,INST,PARM,NAME) \
10  obsAttr(make_callback((Callback2wRet<int,double,int>0
30  *),
    &INST,CLASS::setAttr),CLASS::PARM,#NAME)
11

```

```

12
13                                     //
P.obsAttr(make_callback((Callback2wRet<int,double,int> *)0,

5  &RX_LMSFF,lmsff::setAttr),lmsff::FWLENGTH,"lmsff_fwlen");
14
15#define DEBUGQ(A)  FBQ(A) ;FBQ(db_##A) ;A.asDup(db_##A);
16
17#include "../tx/rnd.h"
10 18#include "../tx/tuplelize.h"
19#include "../tx/diffenc.h"
20#include "../tx/map.h"
21#include "../tx/shape.h"
22#include "../tx/ad.h"
15 23#include "../chan/fir.h"
24#include "../chan/noise.h"
25#include "../rx/lmsff.h"
26#include "../rx/demap.h"
27#include "../rx/detuple.h"
20 28#include "../rx/derand.h"
29
30#endif

```

25 6 Receiver Code

6.1 rx/demap.h

```

30 1//-----
-
2 // COPYRIGHT

```

T04090"ESSEZB60

```

3 // =====
4 //
5 // Copyright 1996 IMEC, Leuven,Belgium
6 //
5 7 // All rights reserved.
8 //
9//-----
-----
10 // Module:
10 11 //      MAP
12 //
13 // Purpose:
14 // Mapping of QAM16/QPSK constellations to symbols
@(#)demap.h
15      1.5 98/03/30
15 //
16 // Author:
17 //      Patrick Schaumont/ Radim Cmar
18//-----
20 ----
19
20#ifndef DEMAP_H
21#define DEMAP_H
22
25 23#include "qlib.h"
24#ifdef I2C
25#include "i2c_master.h"
26#include "i2c_slave.h"
27#endif
30 28#include "macros.h"
29#include "typedefine.h"
30

```

```

31 classdemap : public base{
32 public:
33
34     clk& _ck;
5 35#ifdef I2C
36     i2c_slave _slave;
37#endif
38     PRT(symtype_in);
39     PRT(diff_mode);
10 40     PRT(i_in);
41     PRT(q_in);
42     PRT(symtype_out);
43     PRT(symbol_out);
44     ctl_fsm _fsm;
15 45
46 public:
47     enum {DEBUGMODE, REF};
48     enum {QAM16, QPSK};
49     int debug_mode;
20 50     double ref;
51
52     demap(char *name,
53           clk& clk,
54           _PRT(symtype_in),
25 55           _PRT(diff_mode),
56           _PRT(i_in),
57           _PRT(q_in),
58           _PRT(symtype_out),
59           _PRT(symbol_out) );
30 60
61     "demap();
62     int setAttr(intAttr, double v=0);

```

T04090" E53E2B60

```

63  int decide(dfir constel, dfir est);
64  int run();
65  void define();
66  ctrlfsm & fsm();
5  67#ifdef I2C
68  i2c_slave&slave();
69#endif
70
71 };
10 72
73#endif

```

6.2 rx/demap.cxx

```

15  1//-----
--
2  //  COPYRIGHT
3  //  =====
4  //
20 5  //  Copyright1996 IMEC, Leuven,Belgium
6  //
7  //  Allrights reserved.
8  //
9//-----
25  ----
10 // Module:
11 //      MAP
12 //
13 // Purpose:
30 14 //      Mapping of QAM16/QPSKconstellations to symbols
@(#)demap.cxx 1.8 98/0*
*4/07

```

```

15 //
16 // Author:
17 //      Radim Cmar
18//-----
5  ----
19
20
21#include "demap.h"
22#include "trans.h"
10 23
24 // QAM16
25 static int vIQMap16[4] [4] = {
26 { 15,14, 10, 11},
27 { 13,12,  8,  9},
15 28 { 5 , 4,  0,  2},
29 { 7 , 6,  1,  3}};
30
31 // QPSK
32 static int vIQMap4[2] [2] = {
20 33 { 3,2}, {1, 0}};
34
35 demap::demap(char *name,
36             clk& clk,
37             _PRT(symtype_in),
25 38             _PRT(diff_mode),
39             _PRT(i_in),
40             _PRT(q_in),
41             _PRT(symtype_out),
42             _PRT(symbol_out)
30 43             ) : base(name),
44     _ck(clk),
45#ifdef I2C

```

T04090"ESSEZ860

```

46  _slave(strapp(name, "_i2c_host")),
47#endif
48  IS_SIG(symtype_in, T_bit),
49  IS_SIG(diff_mode, T_bit),
5  50  IS_SIG(i_in, T_float),
51  IS_SIG(q_in, T_float),
52  IS_REG(symtype_out, _ck, T_bit),
53  IS_REG(symbol_out, _ck, T_float)
54  {
10 55  IS_IP(symtype_in);
56  IS_IP(diff_mode);
57  IS_IP(i_in);
58  IS_IP(q_in);
59  IS_OP(symtype_out);
15 60  IS_OP(symbol_out);
61
62  debug_mode= 0;
63  }
64
20 65 demap::"demap()" {
66  }
67
68  int demap::setAttr(intAttr, double v) {
69  switch(Attr) {
25 70  case REF:
71      ref= v; break;
72  case DEBUGMODE:
73      debug_mode = (int) v; break;
74  }
30 75  return 1;
76  }
77

```

T:04090" E35E2860

```

78//-----
---
79
80 int demap::run() {
5 81
82     int thissym;
83     int ik, qk;
84     int n_ik,n_qk;
85     static int ik_at= 1;
10 86     static int qk_at= 1;
87
88     if( (FBID(i_in).getSize() <1) ||
89         (FBID(q_in).getSize() <1) ||
90         (FBID(symtype_in).getSize() <1) ||
15 91         (FBID(diff_mode).getSize() <1)
92         )
93     return 0;
94
95     dfix vi = FBID(i_in).get();
20 96     dfix vq = FBID(q_in).get();
97     dfix constel = FBID(symtype_in).get();
98     dfix diffdec= FBID(diff_mode).getIndex(0);
99
100     int indi = decide(constel,vi);
25 101     int indq = decide(constel,vq);
102
103     if( constel== QAM16) {
104         thissym= vIQMap16[indi][indq] ;
105     } else{
30 106         thissym= vIQMap4[indi][indq] ;
107     }
108     int thissym0 = thissym;

```

0907353-060401

```

109
110
111 if( diffdec== 1) {
112     if(constel == QAM16) {
5 113         ik = (thissym>> 3) &1;
114         qk = (thissym>> 2) &1;
115
116                                     n_ik=
117         (((("ik^qk))&(ik^ik_at))|((ik^qk)&(qk^qk_at)))&1;
118                                     n_qk=
10  (((("ik^qk))&(qk^qk_at))|((ik^qk)&(ik^ik_at)))&1;
117         ik_at= ik;
118         qk_at= qk;
119         thissym = (n_ik<<3 ) + (n_qk<< 2) + (thissym &
120         3);
15 120
121     } else {
122         ik = (thissym>> 1) &1;
123         qk = (thissym ) & 1;
124
125                                     n_ik=
20  (((("ik^qk))&(ik^ik_at))|((ik^qk)&(qk^qk_at)))&1;
125                                     n_qk=
126         (((("ik^qk))&(qk^qk_at))|((ik^qk)&(ik^ik_at)))&1;
126         ik_at= ik;
127         qk_at= qk;
25 128         thissym = (n_ik<<1 ) + (n_qk ) ;
129     }
130 }
131
132 if(debug_mode)
30 133 cout<< "_constel:"<<constel
134     << "_i:"<<vi
135     << "_q:"<<vq

```

```

136     << "_thissym0:"<<thissym0
137     << "_ik:"<<ik
138     << "_qk:"<<qk
139     << "_n_ik:"<<n_ik
5 140     << "_n_qk:"<<n_qk
141     << "_thissym:"<<thissym<<endl;
142
143 FBID(symbol_out) << (thissym);
144 FBID(symtype_out) << (constel);
10 145
146     return 1;
147 }
148
149 int demap::decide(dfix constel,dfix est) {
15 150     double c = ref/3;
151     if(constel== QAM16) {
152         if(est > dfix(2*c))
153             return 3;
154         else if (est > dfix(0))
20 155             return 2;
156         else if (est > dfix(-2*c))
157             return 1;
158         else
159             return 0;
25 160 } else{
161     if(est > dfix(0.))
162         return 1;
163     else
164         return 0;
30 165 }
166 }
167

```

```

168//-----
-----
169
170 ctrlfsm & demap::fsm() {
5 171   return _fsm;
172}
173
174#ifdef I2C
175 i2c_slave & demap::slave() {
10 176   return _slave;
177}
178#endif
179
180 void demap::define() {
15 181   int i;
182
183   dfixT_2bit(0,2,0,dfix::tc);
184   dfixT_cnt(0,3,0,dfix::ns) ;    // symbol counter upto
4
20 185   dfixT_symb(0,4,0,dfix::ns) ;    // symbol type 0..15
186
187   PORT_TYPE(i_in,T(T_sample_demap) );//user type
188   PORT_TYPE(q_in,T(T_sample_demap) );//user type
189   PORT_TYPE(symbol_out,T_symb);
25 190
191   FSM(_fsm);
192   INITIAL(rst);
193   STATE(phase1);
194   STATE(phase2);
30 195   STATE(phase3);
196
197   SIGCK(constelqam, _ck, T_bit);

```

T04090" E35E2860

```

198 SIGCK(diffdecod, _ck, T_bit);
199 SIGCK(i_inp, _ck, T(T_sample_demap));
200 SIGCK(q_inp, _ck, T(T_sample_demap));
201 SIGW(indi, T_2bit);
5 202 SIGW(indq, T_2bit);
203 SIGCK(start_frame, _ck, T_bit);
204 _sigarraymaps16("maps",16, &_ck, T_symb);
205 _sigarraymaps4("maps",4 , &_ck,T_symb);
206 SIGW(symb0, T_symb);
10 207 SIGW(symb1, T_symb);
208 SIGW(ik, T_bit);
209 SIGW(qk, T_bit);
210 SIGW(ik _1,T_bit);
211 SIGW(qk_1, T_bit);
15 212 SIGCK(ik_at, _ck, T_bit);
213 SIGCK(qk_at, _ck, T_bit);
214 SIGW(ak, T_bit);
215 SIGW(bk, T_bit);
216
20 217#ifdef I2C
218   for(i = 0; i < 16; i++)
219     _slave.put(&maps16[i] ) ;
220   for(i = 0; i < 4; i++)
221     _slave.put(&maps4[i] ) ;
25 222#endif
223
224
225 SFG(demap_allways);
226 GET(diff_mode);
30 227   diffdecod= diff_mode;
228
229

```

T04090"ESSE/860

```

230 SFG(demap_reset);
231   for(i = 0; i < 16; i++)
232     maps16[i] = W(T_symb,vIQMap16[i/4] [i%4] ) ;
233   for(i = 0; i < 4; i++)
5 234     maps4[i] = W(T_symb,vIQMap4[i/2] [i%2] ) ;
235
236   setv(start_frame,0);
237   setv(ik_at,0);
238   setv(qk_at,0);
10 239
240
241 SFG(demap_qam16);
242   double c = ref/3;
243   indi= (i_inp<= C(i_inp,-2*c) )c.assign(C(indi,0),
15 244       (i_inp<= C(i_inp,0.0) )c.assign(C(indi,1),
245
246       (i_inp<=C(i_inp,+2*c))c.assign(C(indi,2),C(indi,3))));
247   indq= (q_inp<= C(q_inp,-2*c) )c.assign(C(indq,0),
20 248       (q_inp<= C(q_inp,0.0) )c.assign(C(indq,1),
249
250       (q_inp<=C(q_inp,+2*c))c.assign(C(indq,2),C(indq,3))));
251
25 252 symb0=((indi==W(T_2bit,0))&(indq==W(T_2bit,0))).cassign(maps16[
0],
253
254   ((indi==W(T_2bit,0))&(indq==W(T_2bit,1))).cassign(maps16[1],
30 16[2],
255   ((indi==W(T_2bit,0))&(indq==W(T_2bit,2))).cassign(maps
16[3],

```

```

255
    ((indi==W(T_2bit,1))&(indq==W(T_2bit,0))).cassign(maps16[4]
,
256
5    ((indi==W(T_2bit,1))&(indq==W(T_2bit,1))).cassign(maps16[5]
,
257
    ((indi==W(T_2bit,1))&(indq==W(T_2bit,2))).cassign(maps16[6]
,
10 258
    ((indi==W(T_2bit,1))&(indq==W(T_2bit,3))).cassign(maps16[7]
,
259
    ((indi==W(T_2bit,2))&(indq==W(T_2bit,0))).cassign(maps16[8]
15 ,
260
    ((indi==W(T_2bit,2))&(indq==W(T_2bit,1))).cassign(maps16[9]
,
261
20 ((indi==W(T_2bit,2))&(indq==W(T_2bit,2))).cassign(maps16[10
],
262
    ((indi==W(T_2bit,2))&(indq==W(T_2bit,3))).cassign(maps16[11
],
25 263
    ((indi==W(T_2bit,3))&(indq==W(T_2bit,0))).cassign(maps16[12
],
264
    ((indi==W(T_2bit,3))&(indq==W(T_2bit,1))).cassign(maps16[13
30 ],

```

09073553-060401

```

265
    ((indi==W(T_2bit,3))&(indq==W(T_2bit,2))).cassign(maps16[14
],
266
5 maps16[15]
267    ) ) ) ) ) ) ) ) ) ) ) ) ) ) ;
268
269    ik_1= (start_frame).cassign(W(T_bit,0)i,k_at);
270    qk_1= (start_frame).cassign(W(T_bit,0)q,k_at);
10 271
272    ik = cast(T_bit,symb0>> W(T_cnt,3) ) ;
273    qk = cast(T_bit,symb0>> W(T_cnt,2) ) ;
274    ak = ((("ik ^ qk)) & (ik ^ ik_1) ) | ((ik^qk) & (qk^
qk_1));
15 275    bk = ((("ik ^ qk)) & (qk ^ qk_1) ) | ((ik^qk) & (ik^
ik_1));
276    ik_at=ik;
277    qk_at=qk;
278
20 279    symb1 = (symb0 &W (T_symb,3) ) |
280                ((cast(T_symb,ak) <<W(T_symb,3)) &W
(T_symb,8) ) |
281                ((cast(T_symb,bk) <<W(T_symb,2)) &W
(T_symb,4) ) ;
25 282    symbol_out= (diffdecod).cassign(symb1,symb0);
283
284
285 SFG(demap_qpsk);
286                indi=        (i_inp<        C(i_inp,0)
30 )c.assign(C(indi,0),C(indi,1) ) ;
287                indq=        (q_inp<        C(q_inp,0)
)c.assign(C(indq,0),C(indq,1) ) ;

```

```

288
289 symb0=((indi==W(T_2bit,0))&(indq==W(T_2bit,0)))
      .cassign(maps4[0],
290
291
5  ((indi==W(T_2bit,0))&(indq==W(T_2bit,1))).cassign(maps4[1],
291
      ((indi==W(T_2bit,1))&(indq==W(T_2bit,0))).cassign(maps4[2],
292
      maps4[3]
10 293      ) ) ) ;
294
295      ik_1= (start_frame).cassign(W(T_bit,0),ik_at);
296      qk_1= (start_frame).cassign(W(T_bit,0),qk_at);
297
15 298      ik= cast(T_bit,symb0>> W(T_bit,1) ) ;
299      qk = cast(T_bit,symb0);
300      ak = (("ik ^ qk)) & (ik^ ik_1) ) | ((ik^qk) & (qk^
      qk_1));
301      bk = (("ik ^ qk)) & (qk^ qk_1) ) | ((ik^ qk) & (ik^
20 ik_1));
302      ik_at=ik;
303      qk_at=qk;
304
305      symb1 = ((cast(T_symb,ak) <<W(T_symb,1)) &W
25 (T_symb,2) ) |
306      (cast(T_symb,bk) &W(T_symb,1) ) ;
307      symbol_out= (diffdecod).cassign(symb1,symb0);
308
309
30 310 SFG(demap_in);
311 GET(i_in);
312 GET(q_in);

```

```

313 GET(symtype_in);
314 i_inp=i_in;
315 q_inp=q_in;
316 constelqam= "symtype_in;
5 317 symtype_out= symtype_in;
318
319 SFG(demap_out);
320 PUT(symbol_out);
321 PUT(symtype_out);
10 322
323
324 //-----
325
326 DEFAULTDO(demap_allways);
15 327 AT (rst) ALWAYS
328 DO(demap_reset)
329 GOTO(phase1);
330
331 AT (phase1) ALWAYS
20 332 DO(demap_in)
333 GOTO(phase2);
334
335 AT (phase2) ON (_cnd(constelqam))
336 DO(demap_qam16)
25 337 GOTO(phase3);
338
339 AT (phase2) ON ( !_cnd(constelqam))
340 DO(demap_qpsk)
341 GOTO(phase3);
30 342
343 AT (phase3) ALWAYS
344 DO(demap_out)

```

```

345 GOTO(phase1);
346
347
348#ifdef I2C
5 349 _slave.attach(_fsm, *state_phase2,_ck);
350#endif
351
352 _fsm.setinfo(verbose);
353 ofstream F0("demap_trans0.dot");
10 354 F0<<_fsm;
355 F0.close();
356
357 transform TRANSF(_fsm);
358 TRANSF.fsm_handshake1(_ck);
15 359
360 ofstream F("demap_trans.dot");
361 F << _fsm;
362 F .close();
363 _fsm.setinfo(silent);
20 364
365 FSMEXP(typeName( ) ) ;
366}
367

```

25 6.3 rx/derand.h

```

1//-----
----
2 // COPYRIGHT
30 3 // =====
4 //
5 // Copyright 1996 IMEC, Leuven,Belgium

```

```

6 //
7 // All rights reserved.
8 //
9//-----
5 ----
10 // Module:
11 // PRBS
12 //
13 // Purpose:
10 14 // De-randomises data usinga 6-bit or 15-bit
15 // Pseudo Random Binary Sequence.  @(#)derand.h1.2
98/03/30
16 //
17 // Author:
15 18 // r cmar
19 //
20//-----
----
21
20 22#include "qlib.h"
23#ifdef I2C
24#include "i2c_master.h"
25#include "i2c_slave.h"
26#endif
25 27#include "macros.h"
28#include "typedefine.h"
29
30 30#include DERAND_H
31#define DERAND_H
30 32
33 class derand : public base
34 {

```

"04090"ESSEZB60

```

35
36 public:
37     clk & _ck;
38 #ifdef I2C
5 39     i2c_slave _slave;
40 #endif
41     PRT(byte_in);
42     PRT(syncro);
43     PRT(byte_out);
10 44     PRT(sync_out);
45     ctl_fsm_fsm;
46
47     enum {SEED, BYPASS, DEBUGMODE};
48
15 49     derand(char *name,
50             clk& clk,
51             _PRT(byte_in),
52             _PRT(syncro),
53             _PRT(byte_out),
20 54             _PRT(sync_out)
55     ) ;
56
57     setattr(int Attr, double v=0);
58     int run();
25 59     void define();
60     ctl_fsm & fsm();
61 #ifdef I2C
62     i2c_slave &slave();
63 #endif
30 64
65 public:
66     int bypass;

```

```

67  int seed;
68  int debug;
69  };
70
5  71#endif

```

6.4 rx/derand.cxx

```

1//-----
10 ----
    2 //  COPYRIGHT
    3 //  =====
    4 //
    5 //  Copyright 1996 IMEC, Leuven,Belgium
15  6 //
    7 //  Allrights reserved.
    8 //
    9//-----
    ----
20 10 // Module:
    11 //  PRBS
    12 //
    13 //  Purpose:
    14 //  De-randomises data usinga 6-bit or 15-bit
25 15 //  Pseudo Random Binary Sequence. @(#)derand.cxx1.8
    98/04/07
    16 //
    17 //  Authors:
    18 //  r cmarr
30 19 //
    20//-----
    ----

```

T04090-ESSC/060

```

21
22#include "derand.h"
23#include "trans.h"
24
5 25 derand::derand(char *name,
26             clk& clk,
27             _PRT(byte_in),
28             _PRT(syncro),
29             _PRT(byte_out),
10 30             _PRT(sync_out)
31             ) : base(name),
32             _ck(clk),
33#ifdef I2C
34             _slave(strapp(name, "_i2c_host")),
15 35#endif
36             IS_SIG(byte_in, T_8bit),
37             IS_SIG(syncro, T_bit),
38             IS_REG(byte_out, clk, T_8bit),
39             IS_REG(sync_out, clk, T_bit)
20 40 {
41     IS_IP(byte_in);
42     IS_IP(syncro);
43     IS_OP(byte_out);
44     IS_OP(sync_out);
25 45
46     bypass= 0;
47     seed= 0x3f;
48     debug= 0;
49 }
30 50
51//-----
---
```

T01030"EESE/350

```

52
53 int derand::setAttr(int Attr,double v)
54 {
55     switch(Attr)
5 56 {
57     case SEED:
58         seed= (int)v; break;
59     case BYPASS:
60         bypass = (int)v; break;
10 61     case DEBUGMODE:
62         debug = (int)v; break;
63     }
64     return 1;
65 }
15 66
67//-----
---
68
69 int derand::run()
20 70 {
71     static unsigned shiftreg= 0;
72
73     #define BiT(k, n)  ((k>> (n-1)) & 1)
74     #define MaSK(k, n) (k & ((1<< (n+1))-1))
25 75
76                                     if((FBID(byte_in).getSize()
<1)||F(BID(syncro).getSize()<1))
77     return 0;
78
30 79     dfix data _in=FBID(byte _in).get();
80     dfix sync  = FBID(syncro).get();
81

```

T04090"ESSE/860

```

82 unsigned data = unsigned(data_in.Val( ) ) ;
83
84 if(bypass == 0) {
85
5 86     if(sync == dfix(1))
87         shiftreg= seed;
88
89     unsigned mask = 0;
90     int xbit;
10 91     for(int k=0; k<8; k++) {
92         xbit      = BiT(shiftreg,5) ^ BiT(shiftreg,6 );
93         shiftreg= MaSK(xbit | (shiftreg<< 1) ,6);
94         mask      = (mask<< 1) |xbit;
95     }
15 96
97     data ^= mask;
98 }
99
100 FBID(byte_out) <<dfix((double)(data) ) ;
20 101 return  1;
102}
103
104//-----
-----

25 105
106 ctrlfsm & derand::fsm() {
107     return _fsm;
108}
109
30 110#ifdef I2C
111 i2c_slave & derand::slave() {
112     return _slave;

```

```

113}
114#endif
115
116 void derand::define() {
5 117
118     dfix T_byte(0,8,0,dfix::ns);
119     dfix T_sreg(0,16,0,dfix::ns);
120     dfix T_num(0,4,0,dfix::ns) ;    // to express constants
0..15
10 121
122     PORT_TYPE(byte_in,T_byte) ;    // 8 bits
123     PORT_TYPE(byte_out,T_byte) ;    // 8 bits
124
125     SIGW(mask, T_byte) ;            // 8 bits
15 126     SIGCK(shiftreg, _ck, T_sreg) ; // 16 bits
127     SIGCK(seed, _ck, T_sreg) ;      // 16 bits
128     SIGCK(bypass, _ck, T_bit);
129     _sigarray xbits("xbits",8+1, T_bit);
130     _sigarray shifts("shifts",8+1,T_sreg);
20 131     _sigarray masks("masks",8+1, T_byte);
132
133#ifdef I2C
134     _slave.put(&seed);
135     _slave.put(&bypass);
25 136#endif
137
138     FSM( _fsm);
139     INITIAL(rst);
140     STATE(phase1);
30 141     STATE(phase2);
142
143     SFG( rnd_reset);

```

T04030"ESSEZ860

```

144  byte_out=W(T_byte,0);
145  seed    = W(T_sreg,0x3f);
146  sync_out=W(T_bit,0);
147  bypass  = W(T_bit,0);
5  148  shiftreg= W(T_sreg,0);
149
150
151  SFG(rnd_read);
152  GET(byte_in);
10 153  GET(syncro);
154
155
156 #define BIT(s,k)  cast(T_bit,s>> W(T_num,k-1))
157 #define MASK(s,n) (s& W (T_sreg,(1<< (n+1))-1))
15 158
159  SFG(rnd_prbs6);
160
161                                shifts[0]=          (syncro==W
(T_bit,1)).cassign(seed,shiftreg);
20 162
163  masks[0] =W(T_byte,0);
164  for(int k=0; k<8; k++) {
165      xbits[k] = BIT(shiftreg,s,5) ^BIT(shifts[k],6);
166  shifts[k+1]=MASK((cast(T_sreg,xbits[k])&W(T_sreg,1)) |
25  shifts[k]W<<(T_num,1)),6);
167  masks[k+1]=(masks[k]<<W(T_byte,1)) |
      (cast(T_byte,xbits[k])&W(T_byte,1));
168  }
169  shiftreg= shifts[8] ;
30 170  mask = masks[8] ;
171
172  byte_out= (bypass).cassign(byte_in,byte_in^mask);

```

```

173   sync_out=W(T_bit,1);
174
175
176 SFG( rnd _write);
5 177   PUT(byte_out);
178   PUT(sync_out);
179   sync_out=W(T_bit,0);
180
181
10 182//-----
----
183
184 AT (rst)ALLWAYS
185   DO( rnd_reset)
15 186   GOTO(phase1);
187
188 AT (phase1)ALLWAYS //state << cond <<sfg <<sfg <<
state
189   DO(rnd_read) //phase1<<allways<<rnd_read <<rnd_prb6<<
20 phase2
190   DO(rnd_prbs6)
191   GOTO(phase2);
192
193 AT (phase2)ALLWAYS
25 194   DO rnd_write)
195   GOTO(phase1);
196
197#ifdef I2C
198   _slave.attach(_fsm, *state_phase2,_ck);
30 199#endif
200
201   _fsm.setinfo(verbose);

```

```

202 ofstream F0("derand_trans0.dot");
203 F0<< _fsm;
204 F0.close();
205
5 206 transform TRANSF(_fsm);
207 TRANSF.fsm_handshake1(_ck);
208
209 ofstream F("derand_trans.dot");
210 F << _fsm;
10 211 F .close();
212 _fsm.setinfo(silent);
213
214 FSMEXP(typeName( ) ) ;
215}
15 216

```

6.5 rx/detuple.h

```

1 //-----
20 -----
2 // COPYRIGHT
3 // =====
4 //
5 // Copyright 1996 IMEC, Leuven,Belgium
25 6 //
7 // All rights reserved.
8 //
9 //-----
-----
30 10 // Module:
11 // TUPLE
12 //

```

```

13 // Purpose:
14 //header detection + detuplelization @(#)detuple.h 1.2
8/03/30
15 //
5 16 // Author:
17 //      Radim Cmar
18//-----
----
19
10 20#ifndef DETUPLE_H
21#define DETUPLE_H
22
23#include "qlib.h"
24#include "macros.h"
15 25#include "typedefine.h"
26
27 class detuple : public base{
28 public:
29
20 30     clk& _ck;
31     PRT(symbol);
32     PRT(symtype);
33     PRT(byte);
34     PRT(syncro);
25 35     ctl fsm_fsm;
36
37     int debug_mode;
38
39 public:
30 40     enum {DEBUGMODE};
41     enum {QAM16, QPSK};
42

```

```

43  detuple(char *name,
44          clk& clk,
45          _PRT(symbol),
46          _PRT(symtype),
5  47          _PRT(byte),
48          _PRT(syncro)
49      ) ;
50
51  "detuple();
10 52  int setAttr(intAttr, doublev=0);
53  int run();
54  void define();
55  ctl fsm & fsm();
56 };
15 57
58#endif

```

6.6 rx/detuple.cxx

```

20  1//-----
-----
2  //  COPYRIGHT
3  //  =====
4  //
25 5  //  Copyright 1996 IMEC, Leuven,Belgium
6  //
7  //  All rights reserved.
8  //
9//-----
30  ----
10 // Module:
11 //      TUPLE

```

```

12 //
13 // Purpose:
14//header detection + detuplelization @(#)detuple.cxx1.3
98/04/07
5 15 //
16 // Author:
17 //      Radim Cmar
18//-----
----
10 19
20
21#include "detuple.h"
22#include "trans.h"
23
15 24 detuple::detuple(char *name,clk& clk,
25         _PRT(symbol),
26         _PRT(symtype),
27         _PRT(byte),
28         _PRT(syncro)
20 29         ) : base(name),
30     _ck(clk),
31     IS_SIG(symbol,T_4bit),
32     IS_SIG(symtype,T_bit),
33     IS_REG(byte,_ck, T_8bit),
25 34     IS_REG(syncro,_ck, T_bit)
35 {
36     IS_IP(symbol),
37     IS_IP(symtype);
38     IS_OP(byte);
30 39     IS_OP(syncro);
40
41     debug_mode= 0;

```

```

42 }
43
44
45 detuple::"detuple() {
5 46 }
47
48
49 int detuple::setAttr(intAttr,double v) {
50     switch(Attr) {
10 51     case DEBUGMODE:
52         debug_mode = (int)v; break;
53     }
54     return 1;
55 }
15 56
57
58 static int QAM16_sync[] = {0,0,5,5,0,0,5,5 };
59     static      int      QPSK_sync[      ]=      {
0,0,0,0,1,1,1,1,0,0,0,0,1,1,1,1};
20 60 static int QAM16_headlen= 8 ;
61 static int QPSK_headlen= 16;
62
63
64 int detuple:r:un() {
25 65     int i;
66
67     static int tuplcnt= 0;
68     static int corrcnt= 0;
69     static int sync = 0;
30 70     static dfix oldstype= 0;
71     static dfix corrarr[16] ;
72     static dfix tuplarr[4] ;

```

T04090"ESSEZB50

```

73
74  int headlen;
75  int symbcount;
76  dfix tuple;
5  77
78                                if((FBID(symbol).getSize()
<1) || (FBID(symtype).getSize() <1))
79    return 0;
80
10 81  dfix symb = FBID(symbol).get();
82  dfix stype = FBID(symtype).get();
83
84  if(stype == QAM16){ //length of header depends on
                        QAM16/QPSK constel
15 85    headlen= QAM16_headlen;
86    symbcount= 2;
87  }
88  else{
89    headlen= QPSK_headlen;
20 90    symbcount= 4;
91  }
92
93  if( corrcnt== headlen) {
94
25 95    int equal = 1;                                // search for
header
96    for(i = 0; i < headlen;i++) {
97      if(stype == QAM16)
98        equal = equal & ( corrrarr[i] ==QAM16_sync[headlen-
30 1-i]);
99    else

```

T04090-ESS2850

```

100      equal = equal & ( corrarr[i] ==QPSK_sync[headlen-
101      1-i]);
102      }
103      if(equal) {                                     // header
appeared
104
105          if(stype == QAM16) //flush tuplarr (evenif not
complete)
10  106      tuple = tuplarr[0] + tuplarr[1]*16;
107      else
108
tuple=tuplarr[0]+tuplarr[1]*4+tuplarr[2]*16+tuplarr[3]*64;
109      FBID(byte) << (tuple);
15  110      FBID(syncro) << (sync);
111
112      sync = 1;                                     // indicates start of
frame
113      corrcnt= 1;
20  114      tuplcnt= 0;
115      }
116      else{                                         // normal processing
117
118          if(tuplcnt== symbcount) {
25  119          if (stype== QAM16)
120      tuple = tuplarr[0] +tuplarr[1]*16;
121      else
122
tuple=tuplarr[0]+tuplarr[1]*4+tuplarr[2]*16+tuplarr[3]*64;
30  123      FBID(byte) << (tuple);
124      FBID(syncro) << (sync);
125

```

0987353-060404

```

126         sync = 0;
127         tuplcnt = 1;
128     }
129     else
5 130         tuplcnt++;
131     }
132 }
133 else
134     corrcnt++;
10 135
136     for(i = symbcount-1; i> 0 ;i--)
137         tuplarr[i] =tuplarr[i-1] ;
138     tuplarr[0] =corrarr[headlen-1]; //shift out the oldest
symbol
15 139
140     for(i = headlen-1; i> 0 ;i--)    // shift in new symbol
141         corrarr[i] =corrarr[i-1] ;
142     corrarr[0] =symb;
143
20 144     if( oldstype!= stype) {    // QPSK/QAM16 change
145         corrcnt= 0;
146         tuplcnt= 0;
147     }
148     oldstype= stype;
25 149
150     return  1;
151 }
152
153
30 154// -----
-----
155

```

```

156 ctrlfsm & detuple::fsm() {
157     return _fsm;
158 }
159
5 160 void detuple:d:efine() {
161     int i;
162
163     int headlen_qam = 8;
164     int headlen_qpsk= 16;
10 165     int symbcount_qam = 2;
166     int symbcount_qpsk= 4;
167     #define max(a,b) ((a> b) ?a : b)
168
169     dfix T_cnt(0,5,0,dfix: :ns) ;           // symbol counter
15 upto 32
170     dfix T_symb(0,4,0,dfix: :ns) ;           // symbol type 0..15
171     dfix T_tuple(0,8,0,dfix:n:s);
172
173     FSM( _fsm);
20 174     INITIAL(rst);
175     STATE(phase1);
176     STATE(phase2);
177     STATE(phase3);
178     STATE(phase4);
25 179
180     SIGCK(qamtype, _ck, T_bit);
181     SIGCK(old_qamtype, _ck, T_bit);
182     SIGCK(symbol_reg,_ck, T_symb);
183
30 184     SIGCK(iniphase, _ck, T_bit);
185     SIGCK(correlated, _ck, T_bit);
186     SIGCK(tuple_ready,_ck, T_bit);

```

T04090"ESSE/860

```

187
188 SIGCK(corrrent, _ck, T_cnt);
189 SIGCK(tuplcnt, _ck, T_cnt);
190
5 191 SIGCK(byte, _ck, T_tuple);
192 SIGW(tuple_qam, T_tuple);
193 SIGW(tuple_qpsk, T_tuple);
194
195 _sigarray          tuplarr("tarr",max(symbcount_qam,
10     symbcount_qpsk),
        &_ck,T_symb);
196 _sigarray          corrrarr("carr",max(headlen_qam,
        headlen_qpsk),
        &_ck,T_symb);
15 197     _sigarray    ref("ref",    max(headlen_qam,headlen
        _qpsk)T,_symb);
198     _sigarray    equal("equal",max(headlen_qam,
        headlen_qpsk),
        T_bit);
20 199
200 //-----
-----
201
202 SFG( tupler_reset);
25 203     setv(corrrent,0);
204     setv(tuplcnt,0);
205     setv(old_qamtype,1);
206     setv(syncro,0);
207
30 208 SFG( tupler_read);
209     GET(symbol);
210     GET(symtype);

```

```

211     symbol_reg=symbol;
212     qamtype = "symtype;
213
214
5 215 SFG( tupler_test);
216         iniphase=      ((qamtype)      &      (corrcnt!=
W(T_cnt,headlen_qam)))
217         |      (("qamtype)      &(corrcnt!=
W(T_cnt,headlen_qpsk))) );
10 218
219
tuple_ready=(qamtype).cassign(tuplcnt==W(T_cnt,symbcount_qa
m),
220
15 221 tuplcnt==W(T_cnt,symbcount_qpsk));
222
223 SFG( tupler_corr);
224     for(i= 0; i < max(headlen_qam,headlen_qpsk);i++) {
20 225         int iqam  = (headlen_qam-1-i< 0) ? 0 : headlen_qam-
1-i;
226         int iqpsk = headlen_qpsk-1-i;
227
ref[i]
=
(qamtype).cassign(W(T_symb,QAM16_sync[iqam] ) ,
25 228
W(T_symb, QPSK_sync[iqpsk]
) ) ;
229         if(i == 0)
230             equal[i] = (corrarr[i] ==ref[i] ) ;
231         else
30 232             equal[i] = equal[i-1] & (corrarr[i] ==ref[i] ) ;
233     }
234     correlated=(qamtype).cassign(equal[headlen_qam-

```

```

        1],equal[headlen_qpsk-1]);
235
236
237
5 238 SFG(tupler_compose);
239     tuple_qam= (cast(T_tuple,tuplarr[0]) &W(T_tuple,15)
)
240         | ((cast(T_tuple,tuplarr[1])W&(T_tuple,15))
<<W(T_cnt,4));
10 241
242     tuple_qpsk=(cast(T_tuple,tuplarr[0] & W(T_tuple,3))
243         | ((cast(T_tuple,tuplarr[1])&   W(T_tuple,3))
<<W(T_cnt,2))
244         |   (   (cast(T_tuple,tuplarr[2])&   W(T_tuple,3))
15 <<W(T_cnt,4))
245         |   (   (cast(T_tuple,tuplarr[3])&   W(T_tuple,3))
<<W(T_cnt,6));
246
247     byte= (qamtype).cassign(tuple_qam,tuple_qpsk);
20 248
249     tuplcnt= (correlated).cassign(W(T_cnt,0-1),
250         (tuple_ready).cassign(W(T_cnt,1-1),
251         tuplcnt));
252
25 253     corrcnt= (correlated).cassign(W(T_cnt, 1-1),
254         corrcnt);
255
256
257 SFG(tupler_out);
30 258 PUT(byte);
259 PUT(syncro);
260     syncro= correlated;

```

T04090" ESS2860

```

261
262
263 SFG(tupler_shiftin );
264     for(i = 1; i < max(symbcount_qam,symbcount_qpsk)
5 ;i++)
265         tuplarr[i] =tuplarr[i-1] ;
266     tuplarr[0]=(qamtype).cassign(corrarr[headlen_qam-
        1],corrarr[headlen_qpsk-1] ) ;
267
10 268     for(i = max(headlen_qam,headlen_qpsk)-1;i> 0 ;i--)
269         corrarr[i] =corrarr[i-1] ;
270     corrarr[0] =symbol_reg;
271
272
15 273
274 SFG( tupler_finish_qam);
275     corrcnt= (old_qamtype!= qamtype).cassign(W (T_cnt,0),
276                                             (corrcnt== W
        (T_cnt,headlen_qam)).cassign(corrcnt,
20 277                                     corrcnt+ W (T_cnt,1) ) ) ;
278     tuplcnt= (old_qamtype!= qamtype).cassign(W (T_cnt,0),
279                                     (correlated).cassign(W(T_cnt,0),
280                                             (corrcnt !=W
        (T_cnt,headlen_qam)).cassign(tuplcnt,
25 281
        (tuplcnt==W(T_cnt,symbcount_qam)).cassign(W(T_cnt,1),
282                                     tuplcnt+ W (T_cnt,1) ) ) ) ) ;
283     old_qamtype= qamtype;
284
30 285 SFG( tupler_finish_qpsk);
286     corrcnt= (old_qamtype!= qamtype).cassign(W (T cnt,0),

```

```

287                                     (corrcnt==W(T_cnt,headlen
_qpsk)).cassign(corrcnt,
288                                     corrcnt+ W (T_cnt,1) ) ) ;
289     tuplcnt= (old_qamtype!= qamtype).cassign(W (T_cnt,0),
5 290         (correlated).cassign(W(T_cnt,0),
291                                     (corrcnt      !=W
(T_cnt,headlen_qpsk)).cassign(tuplcnt,
292
(tuplcnt==W(T_cnt,symbcount_qpsk)).cassign(W(T_cnt,1),
10 293         tuplcnt+ W (T_cnt,1) ) ) ) ) ;
294     old_qamtype= qamtype;
295
296 //-----
---
15 297
298 AT (rst)ALLWAYS
299     DO(tupler_reset)
300     GOTO(phase1);
301
20 302 AT (phase1)ALLWAYS
303     DO(tupler_read)
304     DO( tupler_test)
305     DO( tupler_corr)
306     GOTO(phase2);
25 307
308 AT (phase2)ON (_cnd(iniphase)||(!_cnd(correlated)&&
        !_cnd(tuple_ready)))
309     GOTO(phase4);
310
30 311 AT (phase2)ON ( !_cnd(iniphase) .&& _cnd(correlated))
312     DO(tupler_compose)
313     GOTO(phase3);

```

T04090"ESSE4860

```

314
315 AT (phase2)ON ( !_cnd(iniphase) && _cnd(tuple_ready) &&
    !_cnd(correlated) )
316 DO(tupler_compose)
5 317 GOTO(phase3);
318
319 AT (phase3)ALLWAYS
320 DO(tupler_out)
321 GOTO(phase4);
10 322
323 AT (phase4)ON (_cnd(qamtype))
324 DO(tupler_shiftin)
325 DO(tupler_finish_qam)
326 GOTO(phase1);
15 327
328 AT (phase4)ON (!_cnd(qamtype))
329 DO(tupler_shiftin)
330 DO(tupler_finish_qpsk)
331 GOTO(phase1);
20 332
333 _fsm.setinfo(verbose);
334 ofstream F0("detuple_trans0.dot");
335 F0<< _fsm;
336 F0.close();
25 337
338 transform TRANSF(_fsm);
339 TRANSF.fsm_handshake1(_ck);
340
341 ofstream F("detuple_trans.dot");
30 342 F << _fsm;
343 F .close();
344 _fsm.setinfo(silent);

```

T04090"ESSE2B60

```

345
346 FSMEXP(typeName( ) ) ;
347
348}
5 349

```

6.7 rx/lmsff.h

```

1
10 2 // Author:Radim Cmar
3 // Purpose:ADAPTIVE EQUALIZER(LMS)  @(#)lmsff.h 1.4
98/03/30
4
5#ifdef LMS_H
15 6#define LMS_H
7
8#include "qlib.h"
9#ifdef I2C
10#include "i2c_master.h"
20 11#include "i2c_slave.h"
12#endif
13#include "macros.h"
14#include "typedefine.h"
15
25 16 class lmsff: public base{
17
18 public:
19   clk & _ck;
20#ifdef I2C
30 21   i2c_slave _slave;
22#endif
23   PRT(constel_mode);

```

```

24  PRT(in_sample);
25  PRT(out_i);
26  PRT(out_q);
27  PRT(symtype);
5  28  ctrlfsm_fsm;
29
30  int constel_type; //QAM16or QPSK
31  intSPS;           // samples per symbol
32  intCPS;           // cycles per sample
10 33  intNF;           // forward taps
34  intSTEP;          // step adaptation constant
35  double p0,p1,p2,p3;
36  double ref;
37
15 38 public:
39      enum { SPS_PAR, FWLENGTH, STEP_PAR, INIT,
40      P0,P1,P2,P3,REF };
41  enum { QAM16, QPSK };
42
20 42  lmsff(char *name,
43      clk & clk,
44      _PRT(constel_mode),
45      _PRT(in_sample),
46      _PRT(out_i),
25 47      _PRT(out_q),
48      _PRT(symtype)
49      ) ;
50
51  int setAttr(int Attr, double v=0);
30 52  int run();
53  void define();
54  ctrlfsm & fsm();

```

T04090" 05522860

```

55#ifdef I2C
56    i2c_slave &slave();
57#endif
58
5 59    //untimed mode
60    dfix decide(dfix constel, dfix est);
61    dfix coefi[111] ;
62    dfix coefq [111] ;
63    dfix sample[111] ;
10 64
65 };
66
67#endif

15    6.8    rx/lmsff.cxx

1
2 // Author:Radim Cmar
3 // Purpose:ADAPTIVE EQUALIZER(LMS)  @(#)lmsff.cxx 1.18
20 98/04/07
4
5#include "lmsff.h"
6#include <math.h>
7#include "trans.h"
25 8
9 lmsff::lmsff(char *name,
10         clk & clk,
11         _PRT(constel_mode),
12         _PRT(in_sample),
30 13         _PRT(out_i),
14         _PRT(out_q),
15         _PRT(symtype)

```

T04090"ESSE4860

```

16         ) : base(name),
17         _ck(clk),
18 #ifdef I2C
19         _slave(strapp(name, "_i2c_host")),
5 20 #endif
21         IS_SIG (constel_mode, T_bit),
22         IS_SIG (in_sample, T_float),
23         IS_REG (out_i, _ck, T_float),
24         IS_REG (out_q, _ck, T_float),
10 25         IS_REG (symtype, _ck, T_bit)
26 {
27     IS_IP(constel_mode);
28     IS_IP(in_sample);
29     IS_OP(out_i);
15 30     IS_OP(out_q);
31     IS_OP(symtype);
32
33     SPS = 4;
34     STEP = 4;
20 35     NF = 8;
36     ref= 3.0;
37 }
38
39 int lmsff::setAttr(int Attr, double v) {
25 40     switch(Attr) {
41         case SPS_PAR :        // parametrizable only for untimed
model
42             SPS = (int) v;
43             break;
30 44         case FWLENGTH :
45             NF = (int) v;
46             break;

```

00873553-050401
FOI090-ESSZ860

```

47  case STEP_PAR :
48      STEP = (int) v;
49      break;
50  case P0:
5  51      p0 = v;
52      break;
53  case P1:
54      p1 = v;
55      break;
10 56  case P2:
57      p2 = v;
58      break;
59  case P3:
60      p3 = v;
15 61      break;
62  case REF:
63      ref= v;
64      break;
65  case INIT :
20 66      cerr<< "***_INFO:_LMSFF_equalizer_reset\n";
67      for(int i=0; i < NF; i++) {
68          sample[i] = dfix(0);
69          coefi[i] = dfix(0);
70          coefq[i] = dfix(0);
25 71      }
72      int offs = (NF-4)/2;
73      coefq[offs+ 0] = p0;
74      coefi[offs+ 1] = p1;
75      coefq[offs+ 2] = p2;
30 76      coefi[offs+ 3] = p3;
77      break;
78  }

```

T040930"ESSE4860

```

79 return 1;
80 }
81
82//-----
5 -
83
84 int lmsff::run() {
85     int i;
86     dfix acci,accq, equali, equalq,esti, estq, erri,errq;
10 87
88     if((FBID(in_sample).getSize()<SPS)||
        (FBID(constel_mode).getSize()1<))
89         return 0;
90
15 91     dfix constel= FBID(constel_mode).getIndex(0);
92     dfix step = 1.0/pow(2.0,STEP);
93
94     // ---ff filtering---
95     acci= 0;
20 96     accq= 0;
97     for(i = 0; i < NF ; i++) {
98         acci= acci + sample[i] * coefi[i] ;
99         accq= accq + sample[i] * coefq[i] ;
100 }
25 101 equali= acci;
102 equalq= accq;
103
104 // ---output----
105 FBID(out_i) <<(equali);
30 106 FBID(out_q) << (equalq);
107 FBID(symtype) << (constel);
108

```

09873563-060401

```

109 // ---slicing---
110 esti= decide(constel, equali);
111 estq= decide(constel, equalq);
112
5 113 // ---error evaluation---
114 erri= esti - equali;
115 errq= estq - equalq;
116
117 // ---coefficient adaptation---
10 118 for(i = 0; i < NF; i++) {
119     coefi[i] =coefi[i] + step* erri * sample[i] ;
120     coefq[i] =coefq[i] + step* errq * sample[i] ;
121 }
122
15 123 // ---reading in samples---
124 for(i = NF-1; i>= SPS; i--)
125     sample[i] =sample[i-SPS] ;
126 for(i = SPS-1; i>= 0; i--)
127     sample[i] =FBID(in_sample).get();
20 128
129 return 1;
130}
131
132 dfix lmsff::decide(dfixed constel,dfixed est) {
25 133 double c = ref/3;
134 if( constel== QAM16) {
135     if(est > dfixed(2*c))
136         return dfixed(3*c);
137     else if (est > dfixed(0))
30 138         return dfixed (1*c);
139     elseif (est > dfixed(-2*c))
140         return dfixed (-1*c);

```

```

141     else
142         return dfix (-3*c);
143 } else{
144     if(est > dfix (0.))
5 145         return dfix (3*c);
146     else
147         return dfix (-3*c);
148 }
149}
10 150
151//-----
-----
152
153 ctl fsm & lmsff::fsm() {
15 154 return_fsm;
155}
156
157#ifdef I2C
158 i2c_slave &lmsff::slave() {
20 159 return _slave;
160}
161#endif
162
163
25 164#define CC(a) cast(accum_type,a)
165 void    adder_tree(_sigarray & ops,int l, int h,
    _sig&res) {
166     if(h-l+1 > 5) {
167         cerr<< "lmsff_error:_maximum_5_operands_suported\n";
30 168         exit(1);
169     }
170     dfix& accum_type= res.Rep()->getVal();

```

T04090" ESSCZ860

```

171  switch(h-1+1) {
172      case 0: res = C(res,0) ;break;
173      case 1: res = CC(ops[1] );break;
174      case 2: res = CC(ops[1] +ops[1+1] ) ;break;
5 175      case 3: res = CC(ops[1] +ops[1+1]) + CC(ops[1+2]
    );break;
176      case 4: res = CC( ops[1] +ops[1+1] ) + CC( ops[1+2]
    +ops[1+3] ) ;break;
177      case 5: res = CC( ops[1] +ops[1+1] ) + CC(CC
10 (ops[1+2]
    + ops[1+3] ) +CC(ops[1+4] ) ) ;break;

178  }
179  }
180
15 181  void  balance_coefs2(int  numcoefs,int  numcycles,int*
    l,int* h){
182      int i,j,k;
183
184      int orig_numcycles=numcycles;
20 185      if(numcoefs < numcycles)
186          numcycles= numcoefs;
187
188      int paral = numcoefs/numcycles;
189      int incs= numcoefs-( numcoefs/numcycles) *numcycles;
25 190
191      for(k = 1; k <= numcycles;k++)
192          l[k] = (k-1)*paral;
193
194      for(i = 1; i <= incs; i++)
30 195          for(j = i+1; j<= numcycles;j++)
196              l[j]++;
197

```

09873553-060401

```

198 . for(k = 1; k <= numcycles-1;k++)
199   h [k] =l[k+1]-1;
200   h[numcycles] =numcoefs-1;
201
5 202   for(k = numcycles+1; k<= orig_numcycles;k++) {
203     l[k] =0;
204     h [k] = -1;
205   }
206
10 207   if(1) {
208     cout<< "lmsff_info:_filter_balancing\n";
209     for(k = 1; k <= orig _numcycles;k++)
210       cout<< l[k] << ":"<< h [k] <<"_";
211     cout<< endl;
15 212   }
213}
214
215
216 void lmsff::define() {
20 217
218   if(NF < 6) {
219     cerr<< "lmsff_error:_minimum_6_coefs_required\n";
220     exit(1);
221   }
25 222
223   int i,k,p;
224
225   //SPS .... samples per symbolparameter
226   //CPS .... cycles per sample(every CPS-phase read
30 sample)
227   //NCYC ... cycle budget in the loop
228   // F_max _delay...extra delay line positions due to

```

00073553-030401
FOI090"ESSEZ860

```

229 SPS = 4;
230 CPS = 2;
231 int F_max_delay = 7;
5 232 int NCYC = SPS*CPS;
233
234 //==distribute filtering operation slices into NCYC-2
cycles=
235
10 236 int l_f[i1100] ;
237 int h_f[i1100] ;
238 int l_upd[100] ;
239 int h_upd[100] ;
240
15 241 //budget is fixed : 8-2=6cycles
242 //let's have 8 coefs
243 //can be more elaborate(e.g. interleaved slicing)
244 int start_fil = 1 //for filtering to know to store
first time
20 245 int end_fil = 6 ; //for filtering to know to store to
I_equal
246
l_fil[1]=0;l_fil[2]=2;l_fil[3]=4;l_fil[4]=5;l_fil[5]=6;l_fil[6]=
7;
25 247
h_fil[1]=1;h_fil[2]=3;h_fil[3]=4;h_fil[4]=5;h_fil[5]=6;h_fil[6]=
7;
248
l_upd[1]=0;l_upd[2]=2;l_upd[3]=4;l_upd[4]=5;l_upd[5]=6;l_upd[6]=
30 7;

```

```

249
h_upd[1]=1;h_upd[2]=3;h_upd[3]=4;h_upd[4]=5;h_upd[5]=6;h_upd[6]=
7;
250 //was example what input we need for parametrizable
5 filter
    definition
251
252 balance_coefs2(NF,6,l_fil,h_fil);
253 balance_coefs2(NF,6,l_upd,h_upd);
10 254
255 // =====definition of signals=====
256
257 PORT_TYPE(in _sample,T(T_sample_lms));
258 PORT_TYPE(out_i,T(T_sample_lms));
15 259 PORT_TYPE(out_q,T(T_sample_lms));
260
261 dfix T_step(0,5,0,dfix::ns) ;// shifts 0-> 31
262
263 _sigarray Fi_coef("Fi_coef",NF,&_ck,T(T_Fcoef_lms));
20 264 _sigarray Fq_coef("Fq_coef",NF,&_ck,T(T_Fcoef_lms));
265 _sigarray I_sample("I_sample",NF+F_max_delay,
    &_ck,T(T_sample_lms));
266 _sigarray Fi_mult ("Fi_mult",NF,T(T_accu_lms));
267 _sigarray Fq_mult ("Fq_mult",NF,T(T_accu_lms));
25 268 _sig Fi_sum("Fi_sum",T (T_accu_lms));
269 _sig Fq_sum("Fq_sum",T (T_accu_lms));
270 _sigarray fm_i("fm_i",NF,T(T_accu_lms));
271 _sigarray fm_q("fm_q",NF ,T(T_accu_lms));
272 _sigarray fmult_i("fmult_i",NF,T(T_Fcoef_lms));
30 273 _sigarray fmult_q("fmult_q",NF,T(T_Fcoef_lms));
274 SIGCK(I_accu,_ck, T(T_accu_lms));
275 SIGCK(Q_accu, _ck, T(T_accu_lms));

```

```

276 SIGW(I_equal, T(T_accu_lms));
277 SIGW(Q_equal, T(T_accu_lms));
278 SIGCK(I_error,_ck, T(T_accu_lms));
279 SIGCK(Q_error,_ck, T(T_accu_lms));
5 280 SIGW( I_slice,T(T_equal _lms));
281 SIGW(Q_slice, T(T_equal _lms));
282 SIGCK(step, _ck, T_step);
283 SIGCK(constel, _ck, T_bit);
284
10 285#ifdef I2C
286 _slave.put(&step);
287 for(i = 0; i < NF; i++)
288 _slave.put(&Fi_coef[i] );
289 for(i = 0; i < NF; i++)
15 290 _slave.put(&Fq_coef[i] );
291#endif
292
293
294 //----- definition of states-----
20 -----
295
296 cfsn= &_fsm;          // controller handle
297
298 int phi;
25 299 state* loop_cycle[100] ;
300 state* rst_cycle;
301
302 rst_cycle=new state;    // define the state
303 * rst_cycle <<"rst";    // name the state
30 304 * cfsn<< deflt(*rst_cycle); // assign the state to the
                                controller
305

```

```

306   for(phi = 1; phi<= NCYC ;phi++) {
307     loop_cycle[phi] =newstate;
308     * loop_cycle[phi] <<strapp("cycle_",phi);
309     * cfsm<< *loop_cycle[phi] ;
5  310 }
311
312//----- definition of sfg's-----
-----
313
10 314   sfg* _lms_filt[100] ;
315   sfg* _lms _update _coefs[100] ;
316
317
318   SFG( lms_read_allways);
15 319   GET(constel_mode);
320     constel= constel_mode;
321
322
323   SFG( lms_initialize_coefs);
20 324     int offs= (NF-4)/2;
325     Fq_coef[offs+0] =W (T(T_Fcoef_lms),p0);
326     Fq_coef[offs+1] =W (T(T_Fcoef_lms),0);
327     Fq_coef[offs+2] =W (T(T_Fcoef_lms),p2);
328     Fq_coef[offs+3] =W (T(T_Fcoef_lms),0);
25 329
330     Fi_coef[offs+0] =W (T(T_Fcoef_lms),0);
331     Fi_coef[offs+1] =W (T(T_Fcoef_lms),p1);
332     Fi_coef[offs+2] =W (T(T_Fcoef_lms),0);
333     Fi_coef[offs+3] =W (T(T_Fcoef_lms),p3);
30 334
335     for(i = 0; i < NF; i++) {
336       if((i < offs) && (i> offs+3)) {

```

```

337     Fi_coef[i] =W(T(T_Fcoef_lms),0) ;
338     Fq_coef[i] =W(T(T_Fcoef_lms),0) ;
339 }
340 }
5 341
342
343 SFG( lms_reset);
344 for(i = 0; i < NF+F_max_delay;i++) {
345     I_sample[i] =W(T(T_sample_lms)0,);
10 346 }
347     setv(I_error,0);
348     setv(Q_error,0);
349     setv(step,STEP);
350
15 351
352 //----- FILTER(1.cycle to 8.cycle) -----
    *---
353 int delay = 0; int cnt= 0 ;
354 int L,H;
20 355
356 //no filtering in 1st clockcycle
357 cnt++;if (cnt == CPS) { cnt= 0; delay++; }
358
359
25 360 for(p = 1; p <= NCYC-2;p++) {
361     REGISTER_SFG(lms_filt,p);
362     cnt++; if (cnt== CPS) {cnt = 0; delay++; }
363
364     //---- filter feedforward
30 365     L = l_fil[p];H= h_fil[p] ;
366 for (k = L; k<= H; k++)

```

09873553-060404

```

367
Fi_mult[k]=cast (T(T_accu_lms),Fi_coef[k] I*_sample[k+delay])
;
368     if(H >= 0) adder_tree(Fi_mult,L,H,Fi_sum);
5 369
370     for (k = L; k<= H; k++)
371
Fq_mult[k]=cast (T(T_accu_lms),Fq_coef[k]*I_sample[k+delay])
;
10 372     if(H >= 0) adder_tree(Fq_mult,L,H,Fq_sum);
373
374
375     //----- sum I over start_ff-> end_ff
376     if(p == start_fil) {
15 377         I_accu= Fi_sum;
378         Q_accu = Fq_sum;
379     }
380     else if ((p > start_fil)&&(p< end_fil)){
381         I_accu= I_accu+ Fi_sum;
20 382         Q_accu = Q_accu+ Fq_sum;
383     }
384     else if (p == end_fil){
385         I_accu= I_accu+ Fi_sum;
386         Q_accu = Q_accu+ Fq_sum;
25 387         I_equal= I_accu+ Fi_sum;
388         Q_equal = Q_accu+ Fq_sum;
389     }
390 } //end for
391
30 392 //compensate for 1 clockcycle vacancy
393 cnt++;if (cnt == CPS) { cnt= 0; delay++; }
394

```

09873553-050404

```

395
396 //----- UPDATE(1.cycle to 8.cycle) -----
-----397      int STEPSAFE = 4; // safety region for
downshifting
5 398 for(p = 1; p <= NCYC-2;p++) {
399     REGISTER_SFG(lms_update_coefs,p);
400     cnt++; if (cnt== CPS) {cnt = 0; delay++; }
401
402     L = l_upd[p] ;H=h_upd[p] ;
10 403     for (k=L; k<= H; k++)
404         {
405                                                     fm_i[k]
=cast(T(T_accu_lms),I_sample[k+delay]*I_error);
406         vshr(fm_i[k],fm_i[k],step,STEPSAFE);
15 407         Fi_coef[k] =Fi_coef[k] + fm_i[k] ;
408
409
fm_q[k]=cast(T(T_accu_lms),I_sample[k+delay]*Q_error);
410         vshr(fm_q[k],fm_q[k],step,STEPSAFE);
20 411         Fq_coef[k] =Fq_coef[k] +fm_q[k] ;
412     }
413 }
414
415 SFG(lms_outready);
25 416 out_i=cast(T(T_sample_lms) ,I_equal);
417 out_q= cast(T(T_sample_lms) ,Q_equal);
418 symtype= constel;
419
420
30 421 //-----SLICER-----
-----
422 SFG( lms_slice_and_error);

```

09873553-060401
T04090-ESSE/860

```

423 double c = ref/3;
424 I_equal=I_accu;
425 Q_equal= Q_accu;
426
5 427 I_slice =(constel==W(T_bit,0) )c.assign(
428
429                                     (I_equal>
C(I_equal,+2*c)).cassign(C(I_slice,+3*c),
430                                     (I_equal>
10 C(I_equal,0*c)).cassign(C(I_slice,+1*c),
431         (I_equal> C(I_equal,-2*c)).cassign(C(I_slice,-
1*c),
432                                     C(I_slice,-
3*c))))
15 433 ,
434                                     (I_equal>
C(I_equal,0*c)).cassign(C(I_slice,+3*c),
435                                     C(I_slice,-
3*c))
20 436 ) ;
437
438 Q_slice= (constel==W (T_bit,0) )c.assign(
439
440                                     (Q_equal
>
25 C(Q_equal,+2*c)).cassign(C(Q_slice,+3*c),
441         (Q_equal > C(Q_equal,0*c)).cassign(
C(Q_slice,+1*c),
442         (Q_equal > C(Q_equal,-2*c)).cassign(C(Q_slice,-
1*c),
30 443                                     C(Q_slice,-
3*c))))
444 ,

```

```

445          (Q_equal > C(Q_equal,0*c)).cassign(
C(Q_slice,+3*c),
446          C(Q_slice,-
3*c))
5 447  ) ;
448
449  I_error=cast(T(T_accu_lms) , I_slice)-I_equal;
450  Q_error=cast(T(T_accu_lms) , Q_slice)-Q_equal;
451
10 452
453  //-----IO definition-----
-----
454  SFG(lms_in);
455  GET(in_sample);
15 456  I_sample[0] =in_sample;
457  for(i = NF+F_max_delay-1;i > 0; i--) {
458      I_sample[i] =I_sample[i-1] ;
459  }
460
20 461  SFG(lms_out);
462  PUT(out_i);
463  PUT(out_q);
464  PUT(symtype);
465
25 466
467  //=====define the fsmfor fixed 8 cycle timebudget
=====
468
469  DEFAULTDO(lms_read_allways);
30 470  * rst_cycle ALWAYS
471      DO(lms_reset)
472      DO(lms_initialize_coefs)

```

098353-03041
T04030"EE2850

```

473      << *loop_cycle[1] ;
474
475      * loop_cycle[1] ALWAYS
476          DO(lms_in)
5 477      << *_lms_update_coefs[1]
478      << *loop_cycle[2] ;
479
480      * loop_cycle[2] ALWAYS
481      << *_lms_filt[1]
10 482      << *_lms_update_coefs[2]
483      << *loop_cycle[3] ;
484
485      * loop_cycle[3] ALWAYS
486      DO(lms_in)
15 487      << *_lms_filt[2]
488      << *_lms_update_coefs[3]
489      << *loop_cycle[4] ;
490
491      * loop_cycle[4] ALWAYS
20 492      << *_lms_filt[3]
493      << *_lms_update_coefs[4]
494      << *loop_cycle[5] ;
495
496      * loop_cycle[5] ALWAYS
25 497      DO(lms_in)
498      << *_lms_filt[4]
499      << *_lms_update_coefs[5]
500      << *loop_cycle[6] ;
501
30 502      * loop_cycle[6] ALWAYS
503      << *_lms_filt[5]
504      << *_lms_update_coefs[6]

```

```

505      << *loop_cycle[7] ;
506
507  * loop_cycle[7] ALWAYS
508      DO(lms_in)
5 509      << *_lms_filt[6]  // filtering finished-> ready to
output
510      DO(lms_outready)
511      << *loop_cycle[8] ;
512
10 513  * loop_cycle[8] ALWAYS
514      DO(lms_out)
515      DO(lms_slice_and_error)
516      << *loop_cycle[1] ;
517
15 518
519 #ifdef I2C
520     _slave.attach(_fsm, *loop_cycle[1], _ck);
521 #endif
522
20 523     _fsm.setinfo(verbose);
524     ofstream F0("lmsff_trans0.dot");
525     F0 << _fsm;
526     F0 .close();
527
25 528     transform TRANSF(_fsm);
529     TRANSF.fsm_handshake1(_ck);
530
531     ofstream F("lmsff_trans.dot");
532     F << _fsm;
30 533     F .close();
534     _fsm.setinfo(silent);
535

```

093353-060404
T04090"ESSE2850

```
536  FSMEXP(typeName( ) ) ;
```

```
537
```

```
538}
```

```
539
```

```
5
```

```
6.9  rx/macros.h
```

```
1  // @(#)macros.h1.1 98/01/22
```

```
2
```

```
10 3#infdef MACROS_H
```

```
4#define MACROS_H
```

```
5
```

```
6 // #define max(a,b) (a> b) ?a : b
```

```
7
```

```
15 8#include "qlib.h"
```

```
9
```

```
10 extern dfix T_bit;
```

```
11 extern dfix T_2bit;
```

```
12 extern dfix T_4bit;
```

```
20 13 extern dfix T_8bit;
```

```
14 extern dfix T_float;
```

```
15
```

```
16 extern dfix T_Cshift; // type for constant shifter
```

```
17 extern dfix* overcast;
```

```
25 18 extern dfix ycast;
```

```
19 extern strstream* gstr;
```

```
20
```

```
21
```

```
22#define PRT(v)          FB      & __##v; _sigv
```

```
30 23#define _PRT(v)        FB      & __##v
```

```
24#define IS_SIG(v,t)     __##v(__##v) ,v(#v,t)
```

```
25#define IS_REG(v,c,t)   __##v(__##v) ,v(#v,c,t)
```

F04090" E3E2/950

```

26#define GET(v)                IN (v, __##v)
27#define PUT(v)                OUT(v, __##v)
28#define IS_OP(v)              __##v.asSink (this)
29#define IS_IP(v)              __##v.asSource(this)
5 30#define FBID(v)              __##v
31
32#define C(y, x) W((y).Rep()->getVal( ),x)
33#define acast(y, x) cast((y).Rep()->getVal(), ##x)
34
10 35#define setv(y,x) y =W (y.Rep()->getVal( ),x);
36
37#define REGISTER_SFG(s,i) __##s[i] =new sfg; \
38                          __##s[i]->next= glbListOfSfg; \
39                          glbListOfSfg = __##s[i] ; \
15 40                          * __##s[i]
<<strapp(strapp(#s,"_"),i); \
41                          __##s[i]->starts( ) ; \
42                          csfg= __##s[i]
43
20 44#define PORT_TYPE(v,t) v.Rep()->dupVal(t); \
45                          if (v.Rep()->isregister())v.Rep()-
>dupRegVal(t)
46
47#define DSIGW(s,n,w) s[n]
25 =new_sig(strapp(strapp(#s,"_"),n),w)
48
49//----- constant right-shift (division) -----
50//-----
-
30 51#define shr(y, x, b) \
52                          overcast= new dfix(0, x.Rep()-
>getVal().TypeW()+b,x.Rep()-

```

```

>getVal().TypeL()+b) ; \
53 ycast.duplicate(y.Rep()->getVal()); \
54 y= cast (ycast, cast(*overcast,x) >> W(T_Cshift,b) ) ;
\
5 55 delete overcast;
56
57//----- constant left-shift(multiplication) -----
58//-----
-
10 59#define shl(y, x, b) \
60 if(x.Rep()->getVal().isFix()) \
61 overcast= new dfix(0,x.Rep()-
>getVal().TypeW()+b,x.Rep()-
>getVal().TypeL( ) ) ; \
15 62 else\
63 overcast= new dfix(0); \
64 ycast.duplicate(y.Rep()->getVal( ) ) ; \
65 y= cast (ycast, cast(*overcast,x) << W(T_Cshift,b) ) ;
\
20 66 delete overcast;
67
68//----- variable shifters with safety region-----
-
69//-----
25 --
70 //
71 // description vshl(y,x,e,b)::y = x<<e (with 'b' as a
safety
region)
30 72 //
73#define vshl(y, x, e, b) \

```

T04090" E55E2860

```

74         overcast=      new      dfix(0,      x.Rep() -
>getVal().TypeW()+b,x.Rep() -
        >getVal().TypeL( ) ) ; \
75     y= acast (y, cast(*overcast,x) << e ) ; \
5 76     delete overcast;
77
78#define vshr(y, x, e, b) \
79     if(x.Rep()->getVal().isFix()) \
80         overcast=      new      dfix(0,x      .Rep() -
10 >getVal().TypeW()+b,x.Rep() -
        >getVal().TypeL()+b) ; \
81     else\
82         overcast= new dfix(0); \
83     y= acast (y, cast(*overcast,x) >> e ) ; \
15 84     delete overcast;
85
86
87#endif
88
20
        6.10    rx/macros.cxx

#include "macros.h"
2
25 3 dfix T_bit(0,1,0,dfix::ns);
4 dfix T_2bit(0,2,0,dfix::tc);
5 dfix T_4bit(0,4,0,dfix::ns);
6 dfix T_8bit(0,8,0,dfix::ns);
7 dfix T_float(0);
30 8
9 dfix T_Cshift(0,4,0,dfix::n:s);//type for constantshifter
0..15

```

T04090" E55E2860

```

10 dfix* overcast;
11 dfix ycast;
12 strstream* gstr;

```

5 6.11 rx/typedefine.cxx

```

1#include "typedefine.h"
2
3#include <fstream.h>
10 4
5 typedefine glbTypes;
6
7 typedefine::typedefine() {
8     numt= 0;
15 9 }
10
11 void typedefine::load(char *_name) {
12     ifstream IF(_name);
13
20 14     if(IF.fail()) {
15
16         cerr<<"***_ERROR:_typedefine:_cannot_open_file_"<<_name<<"\
n";
16         exit(0);
25 17 }
18
19     while(!IF.eof() && !IF.f a(i)l) {
20         char buf[100] ;
21         IF >> buf;
30 22
23         if(!strlen(buf))
24             continue;

```

T01030"255E/860

```

25
26     if(buf[0] == '/' && buf[1] == '/') {
27         int endoftype = 0;
28         while (!endoftype) {
5 29     char c;
30     IF.get(c);
31     endoftype= (c == '\n' ) ;
32     }
33     continue;
10 34 } else {
35     name[numt] = new char[strlen(buf) +1] ;
36     strcpy(name[numt] ,buf);
37     int i;
38     for (i=0; i<numt; i++)
15 39     if(!strcmp(name[i],buf)) {
40
41                                     cerr<<
42                                     "****_ERROR:_typedefine:_type_"<<buf<<"_defined_twice\n";
43                                     exit(0);
44     }
20 45
46                                     int
47     W,L,repr=dfix::tc,overflow=dfix:e:rr,truncate=dfix:f:l;
48
49     IF >> buf;
50     W = atoi(buf);
25 47     if(W == 0) {
48     cerr<<"****_ERROR:_typedefine:_bad_W_for_type_"
49     <<name[numt]"<<\n";
50     exit(0);
51     }
30 52
53     int endcom = 0;
54

```

F04090" E55E2860

```

54     IF >> buf;
55     L = atoi(buf);
56     if(buf[strlen(buf)-1] == ' ; ' ) {
57     endcom = 1;
5 58     buf[strlen(buf)-1] =0;
59     }
60     while (1) {
61     if(endcom)
62     break;
10 63
64     IF >> buf;
65
66     if(buf[strlen(buf)-1] == ' ; ' ) {
67     endcom = 1;
15 68     buf[strlen(buf)-1] =0 ;
69     }
70
71     if( !strcmp(buf,"ns"))
72     repr = dfix::ns;
20 73     else if (!strcmp(buf,"tc"))
74     repr = dfix::tc;
75     else if ( !strcmp(buf,";"))
76     break;
77     else if ( !endcom) {
25 78     cerr<< "***_ERROR:_typedefine:_"<<name[numt] "<<:
        _bad_repr_"<<buf<<"\n";
79     exit(0);
80     }
81
30 82
83     if(endcom)
84     break;

```

```

85
86     IF >> buf;
87
88     if(buf[strlen(buf)-1] == ' ; ' ) {
5 89         endcom = 1;
90         buf[strlen(buf)-1] = 0 ;
91     }
92
93     if( !strcmp(buf,"wp"))
10 94         overflow = dfix::wp;
95     elseif ( !strcmp(buf,"st"))
96         overflow = dfix::st;
97     elseif ( !strcmp(buf,"er"))
98         overflow = dfix::err;
15 99     elseif ( !strcmp(buf,";"))
100         break;
101     elseif ( !endcom) {
102         cerr<<"***_ERROR:_typedefine:_"<<name[numt]"<<:
            _bad_ovf_"<<buf<<"\n";
20 103         exit(0);
104     }
105
106     if(endcom)
107         break;
25 108
109     IF >> buf;
110
111     if(buf[strlen(buf)-1] == ' ; ' ) {
112         endcom = 1;
30 113         buf[strlen(buf)-1] = 0 ;
114     }
115

```

0987353-060404


```

144     }
145 }
146 }
147}
5 148
149 void typedefine::list() {
150     int i;
151
152     for(i=0; i<numt; i++) {
10 153         cout.width(20);
154         cout<< name[i] ;
155
156         cout.width(5);
157         cout<< types[i] .TypeW();
15 158
159         cout.width(5);
160         cout<< types[i] .TypeL();
161
162         cout.width(4);
20 163         if(types[i] .TypeSign() ==dfix::ns)
164             cout << "ns";
165         else
166             cout << "tc";
167
25 168         cout.width(4);
169         if(types[i] .TypeOverflow() ==dfix::wp)
170             cout << "wp";
171         elseif (types[i] .TypeOverflow() ==dfix::st)
172             cout << "st";
30 173         else
174             cout << "err";
175

```

0907353-060401
"09090" E55E7850

```

176     cout.width(4);
177     if(types[i] .TypeRound() ==dfix::fl)
178         cout << "fl";
179     else
5 180         cout << "rd";
181
182     cout<< "\n";
183 }
184}
10 185
186 static dfix dummy(0);
187
188dfix &typedefine::find(char *_name) {
189     int i;
15 190     if( !numt)
191         return dummy;
192     for(i=0; i<numt; i++)
193         if( !strcmp(name[i] ,_name))
194             return types[i] ;
20 195     cerr<<"***_WARNING:_typedefine:
        _type_"<<_name<<"_was_not_found\n";
196     return dummy;
197}
198
25 199 dfix &typedefine::find(char *_name, dfix& v) {
200     int i;
201     if( !numt)
202         return v;
203     for(i=0; i<numt; i++)
30 204         if( !strcmp(name[i] ,_name))
205             return types[i] ;
206     cerr<< "***_WARNING:_typedefine:

```

0987353-06401

```

        _type_ "<<_name<<"_was_not_found\n";
207 return v;
208}
209

```

5

6.12 rx/typedefine.h

```

1#ifndef TYPEDEFINE_H
2#define TYPEDEFINE_H
10 3
4#define MAXT 100
5
6#include "qlib.h"
7
15 8
9 class typedefine{
10 char *name[100] ;
11 dfix types[MAXT] ;
12 int numt;
20 13 public:
14 typedefine();
15 void load(char *file);
16 void list();
17 dfix &find(char *name);
25 18 dfix &find(char *name, dfix& v);
19 };
20
21 extern typedefine glbTypes;
22
30 23#define LOADTYPES(a) glbTypes.load(#a) ;glbTypes.list()
24#define T(a) glbTypes.find(#a)
25#define TT(a,b) glbTypes.find(#a,b)

```

T.04090" ESE2860

26

27#endif

Part C: Generated VHDL code of the QAM system

5

6.13 vhd1/RX_TI.vhd

1-----

-

10 2 --OCAPI - alpha release- generated Fri Jun 12
16:45:441998

3-----

-

4

15 5 - System Link Cell for design RX_TI

6

7 library IEEE;

8 use IEEE.std_logic_1164.all;

9

20 10 entity RX_TI is

11 port(

12 reset: in std_logic;

13 clk: in std_logic;

14 chan_out: in std_logic_vector(11 downto

25 0);

15 rx_diff_mode: in std_logic;

16 rx_constel_mode: in std_logic;

17 rx_byte_out: out std_logic_vector(7 downto

0);

30 18 rx_sync_out: out std_logic

19);

20 end RX_TI;

T04090" E5E2860

```

21
22 architecture structure of RX_TI is
23
24     component lmsff
5 25         port (
26             reset: in std_logic;
27             clk: in std_logic;
28             hlwack: in std_logic;
29             constel_mode: in std_logic;
10 30             in_sample: in std_logic_vector(11 downto
                0);
31             hlwreq: out std_logic;
32             out_i: out std_logic_vector(11 downto
                0);
15 33             out_q: out std_logic_vector(11 downto
                0); 34             symtype: out std_logic
35         ) ;
36     endcomponent;
37
20 38     component demap
39         port (
40             reset: in std_logic;
41             clk: in std_logic;
42             h2wack: in std_logic;
25 43             hlrack: in std_logic;
44             diff_mode: in std_logic;
45             i_in: in std_logic_vector(11 downto
                0);
46             q_in: in std_logic_vector(11 downto
30             0);
47             symtype_in: in std_logic;
48             h2wreq: out std_logic;

```

09873553.060401

```

49             h1rreq: out std_logic;
50             symbol_out: out std_logic_vector(3 downto
0);
51             symtype_out: out std_logic
5 52     ) ;
53     endcomponent;
54
55     component detuple
56     port (
10 57         reset: in std_logic;
58         clk: in std_logic;
59         h3wack: in std_logic;
60         h2rack: in std_logic;
61         symbol: in std_logic_vector(3 downto
15 0);
62         symtype: in std_logic;
63         h3wreq: out std_logic;
64         h2rreq: out std_logic;
65         byte: out std_logic_vector(7 downto
20 0);
66         syncro: out std_logic
67     ) ;
68     endcomponent;
69
25 70     component derand
71     port (
72         reset: in std_logic;
73         clk: in std_logic;
74         h3rack: in std_logic;
30 75         byte_in: in std_logic_vector(7 downto
0);
76         syncro: in std_logic;

```

```

77         h3rreq: out std_logic;
78         byte_out:out std_logic_vector(7 downto
0);
79         sync_out:out std_logic
5 80     ) ;
81     endcomponent;
82
83     signal          unused : std_logic;
84     signal          h1_ffshk: std_logic;
10 85     signal          rx_lms_i: std_logic_vector(11
downto 0);
86     signal          rx_lms_q: std_logic_vector(11
downto 0);
87     signal          rx_syntype : std_logic;
15 88     signal          h2_ffshk: std_logic;
89     signal          h1_fbshk: std_logic;
90     signal          rx_symbol : std_logic_vector(3
downto 0);
91     signal          rx_syntype_at:std_logic;
20 92     signal          h3_ffshk: std_logic;
93     signal          h2_fbshk: std_logic;
94     signal          rx_byte_rnd: std_logic_vector(7
downto 0);
95     signal          rx_syncro: std_logic;
25 96     signal          h3_fbshk: std_logic;
97
98 begin
99
100 lmsff_proc:lmsff
30 101     port map (
102
reset=>
reset,

```

```

103                                     clk=>
clk,
104                                     h1wack=>
h1_fbshk,
5 105                                     constel_mode=>
rx_constel_mode,
106                                     in_sample=>
chan_out,
107                                     h1wreq=>
10 h1_ffshk,
108                                     out_i=>
rx_lms,_i
109                                     out_q=>
rx_lms,_q
15 110                                     symtype=>
rx_symtype
111     ) ;
112
113     demap_proc: demap
20 114     port map (
115                                     reset=>
reset,
116                                     clk=>
clk,
25 117                                     h2wack=>
h2_fbshk,
118                                     h1rack=>
h1_ffshk,
119                                     diff_mode=>
30 rx_diff_mode,
120                                     i_in=>
rx_lms,_i

```

09873553-060401

```

121                                     q_in=>
rx_lms,_q
122                                     symtype_in=>
rx_symtype,
5 123                                     h2wreq=>
h2_ffshk,
124                                     h1rreq=>
h1_fbshk,
125                                     symbol_out=>
10 rx_symbol,
126                                     symtype_out=>
rx_symtype_at
127    ) ;
128
15 129 detuple_proc:detuple
130     port map (
131                                     reset=>
reset,
132                                     clk=>
20 clk,
133                                     h3wack=>
h3_fbshk,
134                                     h2rack=>
h2_ffshk,
25 135                                     symbol=>
rx_symbol,
136                                     symtype=>
rx_symtype_at,
137                                     h3wreq=>
30 h3_ffshk,
138                                     h2rreq=>
h2_fbshk,

```

10987553-030401
T04030 "E55E2860"

```

139                                     byte=>
rx_byte_rnd,
140                                     syncro=>
rx_syncro
5 141    ) ;
142
143    derand_proc:derand
144        port map (
145                                     reset=>
10 reset,
146                                     clk=>
clk,
147                                     h3rack=>
h3_ffshk,
15 148                                     byte_in=>
rx_byte_rnd,
149                                     syncro=>
rx_syncro,
150                                     h3rreq=>
20 h3_fbshk,
151                                     byte_out=>
rx_byte_out,
152                                     sync_out=>
rx_sync_out
25 153    ) ;
154
155 end structure;

```

6.14 vhd1/derand_proc_ENT.vhd

30

1-----

-

09873553-060404

```

2  --OCAPI - alpha release- generated Thu Jun 11 14:57:23
1998
3  -- -- includes sfg
4  -- derandrstphase10
5  5  -- derandphase1phase20
6  -- derandphase1phase11
7  -- derandphase2phase10
8  -- derandinireg_derandrst0
9  -----
10 -
10
11 library IEEE;
12 use IEEE.std_logic_1164.all;
13 use IEEE.std_logic_arith.all;
15 14 library FXT_PNT_LIB;
15 use FXT_PNT_LIB.pck_fixed_point.all;
16
17 entity derand_proc is
18     port (
20 19     clk: in std_logic;
20     reset: in std_logic;
21     h3rack: in FX (0 downto 0);
22     syncro: in FX (0 downto 0);
23     byte_in: in FX (7 downto 0);
25 24     h3rreq: out FX (0 downto 0 );
25     h3rackreg_reg: out FX (0 downto 0);
26     byte_outT_reg: out FX (7 downto 0);
27     sync_outT_reg: out FX (0 downto 0)
28     ) ;
30 29 end derand_proc;

```

```

1-----
-
2 --OCAPI - alpha release- generated Thu Jun 11 14:57:23
5 1998
3 -- -- includes sfg
4 -- derandrstphase10
5 -- derandphase1phase20
6 -- derandphase1phase11
10 7 -- derandphase2phase10
8 -- derandinireg_derandrst0
9-----
-
10
15 11 library IEEE;
12 use IEEE.std_logic_1164.all;
13 useIEEE. std_logic_arith.all;
14 library FXT_PNT_LIB;
15 use FXT_PNT_LIB.pck_fixed_point.all;
20 16
17 architecture RTL of derand_proc is
18
19 -- State Declaration
20 signal seed_at1: FX (15 downto 0);
25 21 signal seed : FX (15 downto 0);
22 signal shiftreg_at1:FX (15 downto 0);
23 signal shiftreg : FX (15downto 0);
24 signal bypass_at1: FX(0 downto 0);
25 signal bypass : FX (0 downto 0);
30 26 signal h3rackreg_at1:FX (0 downto 0);
27 signal h3rackreg : FX(0 downto 0);
28 signal byte_out_at1:FX(7 downto 0);

```

09873553-060401

```

29  signal byte_out: FX (7 downto 0);
30  signal sync_out_at1:FX(0 downto 0);
31  signal sync_out: FX (0 downto 0);
32  type STATE_TYPE is (
5  33      rst,
34      phase1,
35      phase2,
36      inireg_derand);
37  signal current_state,next_state:STATE_TYPE;
10 38
39  begin
40
41      h3rackreg_reg<=h3rackreg_at1;
42
15 43      byte_out_reg<=byte_out_at1;
44
45      sync_out_reg<=sync_out_at1;
46
47      -- Register clocking
20 48  SYNC : process (clk)
49
50      begin
51          if(clk'event and clk= '1' )then
52              -- state update
25 53              current_state<= next_state;
54              -- tick all registers
55              seed_at1<= seed;
56              shiftreg_at1<= shiftreg;
57              bypass_at1<= bypass;
30 58              h3rackreg_at1<= h3rackreg;
59              byte_out_at1<=byte_out;
60              sync_out_at1<=sync_out;

```

09873553-060404

```

61     end if;
62 end process;
63
64 -- SFG evaluation
5 65 COMB : process (
66     current_state,
67     reset,
68     h3rack,
69     syncro,
10 70     seed_at1,
71     shiftreg_at1,
72     bypass_at1,
73     byte_in,
74     h3rackreg_at1,
15 75     byte_out_at1,
76     sync_out_at1 )
77
78 -- intermediate variables
79     variable shifts_0 : FX(15 downto 0);
20 80     variable xbits_0: FX (0 downto 0);
81     variable masks_0 :FX (7 downto 0);
82     variable shifts_1 : FX(15 downto 0);
83     variable xbits_1:FX (0 downto 0);
84     variable masks_1 :FX (7 downto 0);
25 85     variable shifts_2 : FX(15 downto 0);
86     variable xbits_2:FX (0 downto 0);
87     variable masks_2 :FX (7 downto 0);
88     variable shifts_3 : FX(15 downto 0);
89     variable xbits_3:FX (0 downto 0);
30 90     variable masks_3 :FX (7 downto 0);
91     variable shifts_4 : FX(15 downto 0);
92     variable xbits_4:FX (0 downto 0);

```

T04090"ESSE2850

```

93     variable masks_4 :FX (7 downto 0);
94     variable shifts_5 :FX(15 downto 0);
95     variable xbits_5:FX (0 downto 0);
96     variable masks_5 :FX (7 downto 0);
5 97     variable shifts_6 : FX(15 downto 0);
98     variable xbits_6:FX (0 downto 0);
99     variable masks_6:FX (7 downto 0);
100    variable shifts_7 : FX(15 downto 0);
101    variable xbits_7:FX (0 downto 0);
10 102    variable masks_7 :FX (7 downto 0);
103    variable shifts_8 : FX(15 downto 0);
104    variable masks_8 :FX (7 downto 0);
105    variable mask : FX(7 downto 0);
106
15 107    begin
108
109        -- update all registers and outputs
110        h3rreq <= CAST ("0. " ) ;
111        seed <= seed_at1;
20 112        shiftreg<= shiftreg_at1;
113        bypass <= bypass_at1;
114        h3rackreg <= h3rackreg_at1;
115        byte_out<= byte_out_at1;
116        sync_out<= sync_out_at1;
25 117
118
119        -- default update state register
120        next_state<=current_state;
121
30 122    case current_state is
123
124        when rst=>

```

```

125
126      byte_out<= CAST("00000000. " ) ;
127      seed <= CAST ("0000000000111111. " ) ;
128      sync_out<= CAST("0 . " ) ;
5 129      bypass <= CAST("0 . " ) ;
130      shiftreg<= CAST("0000000000000000. " ) ;
131      h3rackreg<= h3rack;
132      h3rreq <= CAST("1 . " ) ;
133      next_state<= phasel;
10 134
135
136      when phasel=>
137
138      if ((true) and( ToBool(h3rackreg_at1)))then
15 139      shifts_0:= cassign(syncro=CAST("1. " ) ,
140      seed_at1,
141      shiftreg_at1);
142 masks_0 :=CAST ("00000000. " ) ;
143 xbits_0:=
20
(CAST(0,0,SHR(shifts_0,4)))xor(CAST(0,0,SHR(shifts_0,5)));
144
shifts_1:=((CAST(15,0,xbits_0))and(CAST("0000000000000001."
)))
25      or((SHL(shifts_0,1))and(CAST("000000001111111. " ) ) )
;
145 masks_1 :=(SHL(masks_0,1))or((CAST(7,0,xbits_0))and
(CAST("00000001. " ) ) ) ;
146 xbits_1:=
30
(CAST(0,0,SHR(shifts_1,4)))xor(CAST(0,0,SHR(shifts_1,5)));

```

T04090"ESSE/350

```

147
shifts_2:=((CAST(15,0,xbits_1))and(CAST("0000000000000001."
)))
      or((SHL(shifts_1,1))and(CAST("0000000001111111. " ) ) )
5 ;
148 masks_2 SHL(masks_1,1))or((CAST(7,0,xbits_1))and
      (CAST("00000001. " ) ) ) ;
149
                                                    xbits_2:=
(CAST(0,0,SHR(shifts_2,4)))xor(CAST(0,0,SHR(shifts_2,5)));
10 150
shifts_3:=((CAST(15,0,xbits_2))and(CAST("0000000000000001."
)))
      or((SHL(shifts_2,1))and(CAST("0000000001111111. " ) ) )
;
15 151 masks_3 SHL(masks_2,1))or((CAST(7,0,xbits_2))and
      (CAST("00000001. " ) ) ) ;
152
                                                    xbits_3:=
(CAST(0,0,SHR(shifts_3,4)))xor(CAST(0,0,SHR(shifts_3,5)));
153
20 shifts_4:=((CAST(15,0,xbits_3))and(CAST("0000000000000001."
)))
      or((SHL(shifts_3,1))and(CAST("0000000001111111. " ) ) )
;
154 masks_4 := SHL(masks_3,1))or((CAST(7,0,xbits_3))and
25 (CAST("00000001. " ) ) ) ;
155
                                                    xbits_4:=
(CAST(0,0,SHR(shifts_4,4)))xor(CAST(0,0,SHR(shifts_4,5)));
156
shifts_5:=((CAST(15,0,xbits_4))and(CAST("0000000000000001."
30 )))
      or((SHL(shifts_4,1))and(CAST("0000000001111111. " ) ) )
;

```

FOR "E5E2860"

```

157 masks_5 := SHL(masks_4,1))or((CAST(7,0,xbits_4))and
      (CAST("00000001. " ) ) ) ;
158                                     xbits_5:=
      (CAST(0,0,SHR(shifts_5,4)))xor(CAST(0,0,SHR(shifts_5,5)));
5 159
      shifts_6:=((CAST(15,0,xbits_5))and(CAST("0000000000000001."
      )))
      or((SHL(shifts_5,1))and(CAST("0000000001111111. " ) ) )
      ;
10 160 masks_6 := SHL(masks_5,1))or((CAST(7,0,xbits_5))and
      (CAST("00000001. " ) ) ) ;
161                                     xbits_6:=
      (CAST(0,0,SHR(shifts_6,4)))xor(CAST(0,0,SHR(shifts_6,5)));
162
15 shifts_7:=((CAST(15,0,xbits_6))and(CAST("0000000000000001."
      )))
      or((SHL(shifts_6,1))and(CAST("0000000001111111. " ) ) )
      ;
163 masks_7 := SHL(masks_6,1))or((CAST(7,0,xbits_6))and
20      (CAST("00000001. " ) ) ) ;
164                                     xbits_7:=
      (CAST(0,0,SHR(shifts_7,4)))xor(CAST(0,0,SHR(shifts_7,5)));
165
      shifts_8:=((CAST(15,0,xbits_7))and(CAST("0000000000000001."
25      )))
      or((SHL(shifts_7,1))and(CAST("0000000001111111. " ) ) )
      ;
166 masks_8 := SHL(masks_7,1))or((CAST(7,0,xbits_7))and
      (CAST("00000001. " ) ) ) ;
30 167      shiftreg<= shifts_8;
168      mask := masks_8;
169      byte_out<= cassign(bypass_at1=CAST("1. " ) ,

```

09873553-0604-01

```

170         byte_in,
171         (byte_in) xor (mask));
172         sync_out<=CAST ("1. " ) ;
173         h3rackreg<= h3rack;
5 174         h3rreq<=  CAST("0 . " ) ;
175         next_state<= phase2;
176     end if;
177
178     if (not (ToBool(h3rackreg_at1)))then
10 179         h3rreq<=  CAST("1 . " ) ;
180         h3rackreg<= h3rack;
181         next_state<= phase1;
182     end if;
183
15 184
185     when phase2=>
186
187         h3rackreg<= h3rack;
188         sync_out<= CAST("0 . " ) ;
20 189         h3rreq <= CAST("1 . " ) ;
190         next_state<= phase1;
191
192
193     when inireg_derand=>
25 194
195         seed <= CAST ("0000000000000000. " ) ;
196         shiftreg<=  CAST("0000000000000000. " ) ;
197         bypass <= CAST("0 . " ) ;
198         byte_out<= CAST("00000000. " ) ;
30 199         sync_out<= CAST("0 . " ) ;
200         next_state<= rst;
201

```

09873553-060404

```

202
203     when others=>
204         next_state<= current_state;
205     end case;
5 206
207     if(reset = '1' )then
208         next_state<= inireg_derand;
209         seed <= CAST ("0000000000000000. " ) ;
210         shiftreg <= CAST(" 0000000000000000. " ) ;
10 211         bypass <= CAST ("0. " ) ;
212         h3rackreg<= CAST("0 . " ) ;
213         byte_out<= CAST(" 00000000. " ) ;
214         sync_out<= CAST("0 . " ) ;
215     end if;
15 216
217
218     end process;
219
220 end RTL;
20
    6.16    vhdl/derand_proc_STD.vhd

1-----
-
25  2 --OCAPI - alpha release- generatedThu Jun 11 14:57:23
1998
    3 - includes sfg
    4 -- derandrstphase10
    5 -- derandphase1phase20
30  6 -- derandphase1phase11
    7 -- derandphase2phase10
    8 -- derandinireg_derandrst0

```

T04030" E55E4850

```

9-----
-
10
11 library IEEE;
5 12 use IEEE.std_logic_1164.all;
13 use IEEE.std_logic.arith.all;
14 library FXT_PNT_LIB;
15 use FXT_PNT_LIB.pck_fixed_point.all;
16
10 17 entity derand is
18     port(
19         clk : in std_logic;
20         reset: in std_logic;
21         h3rack : in std_logic;
15 22         syncro: in std_logic;
23         byte_in: in std_logic_vector(7
downto 0);
24         h3rreq: out std_logic;
25         h3rackreg: out std_logic;
20 26         byte_out:out std_logic_vector(7
downto 0);
27         sync_out:out std_logic
28     ) ;
29 end derand;
25 30
31 architecture structure of derand is
32
33     component derand_proc
34     port(
30 35         clk : in std_logic;
36         reset: in std_logic;
37         h3rack : in FX (0 downto 0);

```

0987353-060401
104090-ESSE/860

```

38     syncro : in FX (0 downto 0);
39     byte_in : in FX (7 downto 0);
40     h3rreq : out FX (0 downto 0);
41     h3rackreg_reg:outFX (0 downto 0);
5 42     byte_out_reg:outFX(7 downto 0);
43     sync_out_reg:outFX(0 downto 0)
44 ) ;
45 endcomponent;
46
10 47 signal FX_h3rack : FX( 0 downto 0);
48 signal FX_syncro : FX( 0 downto 0);
49 signal FX_byte_in : FX(7 downto 0);
50 signal FX_h3rreq : FX( 0 downto 0);
51 signal FX_h3rackreg :FX (0 downto 0);
15 52 signal FX_byte_out :FX (7 downto 0);
53 signal FX_sync_out :FX (0 downto 0);
54
55 begin
56
20 57     FX_h3rack(0) <=h3rack;
58     FX_syncro(0) <=syncro;
59     FX_byte_in<= FX(SIGNED(byte_in));
60     h3rreq<= FX_h3rreq(0);
61     h3rackreg<= FX_h3rackreg(0);
25 62     byte_out<=CONV_STD_LOGIC_VECTOR
        (ToSigned(FX_byte_out),byte_out'length);
63     sync_out<=FX_sync_out(0);
64
65     derand: derand_proc
30 66     port map (
67         clk    => clk,
68         reset  => reset,

```

09873553-060401

```

69      h3rack => FX_h3rack,
70      syncro => FX_syncro,
71      byte_in=> FX_byte_in,
72      h3rreq => FX_h3rreq,
5 73      h3rackreg_reg=> FX_h3rackreg,
74      byte_out_reg=>FX_byte_out,
75      sync_out_reg=>FX_sync_out
76  ) ;
77
10 78
79  end structure;

```

6.17 vhd1/derand_tb.vhd

```

15  1-----
   -
   2 --OCAPI-alpha release-generated Fri Jun 12 16:45:45 1998
   3-----
   -
20  4
   5 -- TestBench for design derand
   6
   7 library IEEE;
   8 use IEEE.std_logic_1164.all;
25  9
   10 use IEEE.std_logic_textio.all;
   11 use std.textio.all;
   12
   13 library clock;
30  14 use clock.clock.all;
   15
   16 entity derand_tb is

```

"E93E/860"

```

17 end derand_tb;
18
19 architecture rtl of derand_tb is
20
5 21     signal                reset : std_logic;
22     signal                clk : std_logic;
23     signal                h3rack : std_logic;
24     signal                byte_in : std_logic_vector(7
downto 0);
10 25     signal                syncro : std_logic;
26     signal                h3rreq : std_logic;
27     signal                h3rackreg : std_logic;
28     signal                byte_out : std_logic_vector(7
downto 0);
15 29     signal                sync_out: std_logic;
30
31     component derand
32     port (
33
20 34         reset: in std_logic;
35         clk: in std_logic;
36         h3rack: in std_logic;
37         byte_in: in std_logic_vector(7
downto 0);
38         syncro: in std_logic;
25 39         h3rreq: out std_logic;
40         byte_out: out std_logic_vector(7
downto 0);
41         sync_out: out std_logic
42     ) ;
30 42 end component;
43
44

```

09873553-060404

```

45 begin
46
47   crystal(clk,50 ns);
48
5 49   derand_dut: derand
50       port map (
51
52                                     reset=>
reset,
53                                     clk=>
10 clk,
54                                     h3rack=>
h3rack,
55                                     byte_in=>
byte_in,
15 56                                     syncro=>
syncro,
57                                     h3rreq=>
h3rreq,
58                                     byte_out=>
20 byte_out,
59                                     sync_out=>
sync_out ) ;
60   ini:process
61       begin
25 62         reset<= '1' ;
63         wait until clk'event and clk = '1' ;
64         reset<= '0' ;
65         wait;
66   end process;
30 67   input:process
68       file stimuli: text is in "derand_tb.dat";

```

T04090"ESSEZ860

```

69     variable aline : line;
70
71     file stimulo: text is out "derand_tb.sim_out";
72     variable oline : line;
5 73
74     variable          v_h3rack: std_logic;
75     variable          v_byte_in: std_logic_vector(7
downto 0);
76     variable          v_syncro: std_logic;
10 77     variable          v_h3rreq: std_logic;
78     variable          v_byte_out: std_logic_vector(7
downto 0);
79     variable          v_sync_out: std_logic;
80     variable          v_h3rack_hx: std_logic;
15 81     variable          v_byte_in_hx: std_logic_vector(7
downto 0);
82     variable          v_syncro_hx: std_logic;
83     variable          v_h3rreq_hx: std_logic;
84     variable          v_byte_out_hx: std_logic_vector(7
20 downto 0);
85     variable          v_sync_out_hx: std_logic;
86
87     begin
88         wait until reset'event and reset = '0' ;
25 89     loop
90         if (not(endfile(stimuli)))then
91             readline(stimuli, aline);
92             read(aline,          v_h3rack);
93             read(aline,          v_byte_in);
30 94             read(aline,          v_syncro);
95         else
96             assert false

```

```

97         report "End of inputfile reached"
98         severity warning;
99     end if;
100
5 101     h3rack <= v_h3rack;
102     byte_in<= v_byte_in;
103     syncro <= v_syncro;
104
105     wait for 50 ns;
10 106
107     v_h3rreq:= h3rreq;
108     v_byte_out:=byte_out;
109     v_sync_out:=sync_out;
110
15 111     v_h3rack_hx:=v_h3rack;
112     v_byte_in_hx:=v_byte_in;
113     v_syncro_hx:=v_syncro;
114     v_h3rreq_hx:=v_h3rreq;
115     v_byte_out_hx:=v_byte_out;
20 116     v_sync_out_hx:=v_sync_out;
117
118     write(oline, v_h3rack_hx);
119     write(oline, ' ' ) ;
120     hwrite(oline, v_byte_in)_hx;
25 121     write(oline, ' ' ) ;
122     write(oline, v_syncro_hx);
123     write(oline, ' ' ) ;
124     write(oline, v_h3rreq_hx);
125     write(oline, ' ' ) ;
30 126     hwrite(oline, v_byte_out)_hx;
127     write(oline, ' ' ) ;
128     write(oline, v_sync_out)_hx;

```

```
129      write(oline, ' ' ) ;
130
131      writeline(stimulo, oline);
132
5 133      wait until clk'event and clk = '1' ;
134
135      end loop;
136  end process;
137  end rtl;
10 138
139  configuration tbc_rtl of derand_tb is
140  for rtl
141      for all : derand
142          use entity work.derand(structure);
15 143  end for;
144  end for;
145  end tbc_rtl;
```

T04090" E55E2860